SERVICE MANUAL

AE-5A CHASSIS

MODEL	COMMANDER	DEST	CHASSIS NO.	MODEL	COMMANDER	DEST	CHASSIS NO.
KV-28FQ75A	RM-893	ET	SCC-Q45B-A	KV-32FQ75A	RM-893	ET	SCC-Q45C-A
KV-28FQ75B	RM-893	FR	SCC-Q44B-A	KV-32FQ75B	RM-893	FR	SCC-Q44C-A
KV-28FQ75D	RM-893	AEP	SCC-Q41E-A	KV-32FQ75D	RM-893	AEP	SCC-Q41F-A
KV-28FQ75E	RM-893	ESP	SCC-Q43C-A	KV-32FQ75E	RM-893	ESP	SCC-Q43B-A
KV-28FQ75U	RM-893	UK	SCC-Q46B-A	KV-32FQ75U	RM-893	UK	SCC-Q46A-A

FD Trinitron

TRINITRON ® COLOR TV

SONY ®

TABLE OF CONTENTS

CAUTION

SHORT CIRCUIT THE ANODE OF THE PICTURE TUBE AND THE ANODE CAP TO THE METAL CHASSIS, CRT SHIELD, OR THE CARBON PAINTED ON THE CRT, AFTER REMOVAL OF THE ANODE CAP.

WARNING !!

AN ISOLATION TRANSFORMER SHOULD BE USED DURING ANY SERVICE WORK TO AVOID POSSIBLE SHOCK HAZARD DUE TO LIVE CHASSIS, THE CHASSIS OF THIS RECEIVER IS DIRECTLY CONNECTED TO THE POWER LINE.

SAFETY-RELATED COMPONENT WARNING !!

COMPONENTS IDENTIFIED BY SHADING AND MARKED ⚠ ON THE SCHEMATIC DIAGRAMS, EXPLODED VIEWS AND IN THE PARTS LIST ARE CRITICAL FOR SAFE OPERATION. REPLACE THESE COMPONENTS WITH SONY PARTS WHOSE PART NUMBERS APPEAR AS SHOWN IN THIS MANUAL OR IN SUPPLEMENTS PUBLISHED BY SONY.

ATTENTION

APRES AVOIR DECONNECTE LE CAP DE'LANODE, COURT-CIRCUITER L'ANODE DU TUBE CATHODIQUE ET CELUI DE L'ANODE DU CAP AU CHASSIS METALLIQUE DE L'APPAREIL, OU AU COUCHE DE CARBONE PEINTE SUR LE TUBE CATHODIQUE OU AU BLINDAGE DU TUBE CATHODIQUE.

ATTENTION !!

AFIN D'EVITER TOUT RISQUE D'ELECTROCUTION PROVENANT D'UN CHÁSSIS SOUS TENTION, UN TRANSFORMATEUR D'ISOLEMENT DOIT ETRE UTILISÈ LORS DE TOUT DÈPANNAGE LE CHÁSSIS DE CE RÈCEPTEUR EST DIRECTMENT RACCORDÈ Á L'ALIMENTATION SECTEUR.

ATTENTION AUX COMPOSANTS RELATIFS Á LA SECURITÈ!!

LES COMPOSANTS IDENTIFIÈS PAR UNE TRAME ET PAR UNE MARQUE ⚠ SUR LES SCHÈMAS DE PRINCIPE, LES VUES EXPLOSÈES ET LES LISTES DE PIECES SONT D'UNE IMPOR-TANCE CRITIQUE POUR LA SÈCURITÈ DU FONCTIONNEMENT, NE LES REMPLACER QUE PAR DES COMPSANTS SONY DONT LE NUMÈRO DE PIÈCE EST INDIQUÈ DANS LE PRÈSENT MANUEL OU DANS DES SUPPLÈMENTS PUBLIÈS PAR SONY.

ITEM MODEL	Television System	Stereo System	Channel Coverage	Color System
Italian	B/G/H, D/K	GERMAN Stereo	B/G/H VHF : E2-E12 UHF : E21-E69 DK : R01-R12, R21-R69, S01-S05	PAL, SECAM NTSC4.43, NTSC3.58 (VIDEO IN)
French	B/G/H, D/K,L,I	GERMAN/NICAM Stereo	B/G/H VHF : E2-E12 UHF : E21-E69 DK : R01-R12, R21-R69, S01-S05	PAL, SECAM NTSC4.43, NTSC3.58 (VIDEO IN)
AEP	B/G/H, D/K	GERMAN Stereo	B/G/H VHF : E2-E12 UHF : E21-E69 DK : R01-R12, R21-R69, S01-S05	PAL, SECAM NTSC4.43, NTSC3.58 (VIDEO IN)
Spanish	B/G/H, D/K	GERMAN /NICAM Stereo	B/G/H VHF : E2-E12 UHF : E21-E69 DK : R01-R12, R21-R69, S01-S05	PAL, SECAM NTSC4.43, NTSC3.58 (VIDEO IN)
UK	I	NICAM Stereo	B/G/H VHF : E2-E12 UHF : E21-E69 DK : R01-R12, R21-R69, S01-S05	PAL, SECAM NTSC4.43, NTSC3.58 (VIDEO IN)

Model	KV-28FQ75A	KV-28FQ75B	KV-28FQ75D	KV-28FQ75E	KV-28FQ75U
Power Consumption	128W	152W	152W	152W	152W
Model	KV-32FQ75A	KV-32FQ75B	KV-32FQ75D	KV-32FQ75E	KV-32FQ75U
Power Consumption	138W	160W	160W	160W	160W

Picture Tube	FD Trinitron Wide Approx 72 cm (28 inches) (Approx 67cm picture measured diagonally) Approx 82 cm (32 inches) (Approx 77cm picture measured diagonally) 110 degree deflection	Sound output

Subwoofer | Right and Left speaker 2x20W (Music Power) 2x10W (RMS)

1x30W (Music Power) 1x15W (RMS) |
| **Input/Output Terminals [REAR]** | | Power Requirements | 220 - 240V |
| 1: 21-pin Euro connector (CENELEC standard) | Inputs for Audio and Video signals. Inputs for RGB. Outputs of TV Video and Audio signals. | Dimensions | 28" Approx 788x571x563mm

32" Approx 886x620x592mm |
| 2: 21-pin Euro connector | Inputs for Audio and Video signals. Inputs for S Video. Outputs of TV Video and Audio signals. (selectable) | Weight | 28" Approx 46.0kg

32" Approx 74.0kg |
3: 21-pin Euro connector	Inputs for Audio and Video signals. Inputs for S Video. Outputs for Video and Audio signals (monitor out)	Supplied Accessories	RM-893 Remote Commander (1) IEC designated R6 battery (2)
RCA Connectors	Variable output for Audio Signals	Other Features	NexTView, Digital Comb Filter, Noise Reduction, DRC 100Hz Picture, DRC 50Hz Picture, Graphic Equaliser
Input/Output Terminals [FRONT]		Remote control system	Infrared control
Headphone jack	stereo mini jack	Power requirements	3V dc 2 batteries IEC designation R6 (size AA)
Audio inputs	phono jacks	Dimensions	Approx 210x55x23mm (w/h/d)
Video inputs	phono jacks	Weight	Approx 110g (not including battery)
S Video input	4 pin DIN		
Design and specifications are subject to change without notice.			

| Model Name Item	KV-28FQ75A KV-32FQ75A	KV-28FQ75B KV-32FQ75B	KV-28FQ75D KV-32FQ75D	KV-28FQ75E KV-32FQ75E	KV-28FQ75U KV-32FQ75U
Pal Comb	ON	ON	ON	ON	ON
PIP	OFF	OFF	OFF	OFF	OFF
RGB Priority	ON	ON	ON	ON	ON
Woofer Box	ON	ON	ON	ON	ON
Scart 1	ON	ON	ON	ON	ON
Scart 2	ON	ON	ON	ON	ON
Scart 3	ON	ON	ON	ON	ON
Front in (4)	ON	ON	ON	ON	ON
Projector	OFF	OFF	OFF	OFF	OFF
AKB in 16:9 mode	ON	ON	ON	ON	ON
Norm B/G	ON	ON	ON	ON	OFF
Norm I	OFF	ON	OFF	OFF	ON
Norm D/K	ON	ON	ON	ON	OFF
Norm AUS	OFF	OFF	OFF	OFF	OFF
Norm L	OFF	ON	OFF	OFF	OFF
Norm SAT	OFF	OFF	OFF	OFF	OFF
Norm M	OFF	OFF	OFF	OFF	OFF
Teletext	ON	ON	ON	ON	ON
Nicam Stereo	OFF	ON	OFF	ON	ON

WARNING (UK Models only)

The flexible mains lead is supplied connected to a **B.S. 1363** fused plug having a fuse of **13 AMP** rating. Should the fuse need to be replaced, use a **13 AMP FUSE** approved by ASTA to **BS 1362**, ie one that carries the ⬦ mark.

IF THE PLUG SUPPLIED WITH THIS APPLIANCE IS NOT SUITABLE FOR THE OUTLET SOCKETS IN YOUR HOME, IT SHOULD BE CUT OFF AND AN APPROPRIATE PLUG FITTED. THE PLUG SEVERED FROM THE MAINS LEAD MUST BE DESTROYED AS A PLUG WITH BARED WIRES IS DANGEROUS IF ENGAGED IN A LIVE SOCKET.

When an alternative type of plug is used, it should be fitted with a **13 AMP FUSE**, otherwise the circuit should be protected by a **13 AMP FUSE** at the distribution board.

How to replace the fuse.
Open the fuse compartment with a screwdriver blade and replace the fuse.

FUSE

21 pin connector

Pin No	1	2	4	Signal	Signal level
1	○	○	○	Audio output B (right)	Standard level : 0.5V rms Output impedence : Less than 1kohm*
2	○	○	○	Audio output B (right)	Standard level : 0.5V rms Output impedence : More than 10kohm*
3	○	○	○	Audio output A (left)	Standard level : 0.5V rms Output impedence : Less than 1kohm*
4	○	○	○	Ground (audio)	
5	○	○	○	Ground (blue)	
6	○	○	○	Audio input A (left)	Standard level : 0.5V rms Output impedence : More than 10kohm*
7	○	●	●	Blue input	0.7 +/- 3dB, 75 ohms positive
8	○	○	○	Function select (AV control)	High state (9.5-12V) : Part mode Low state (0-2V) : TV mode Input impedence : More than 10K ohms Input capacitance : Less than 2nF
9	○	○	○	Ground (green)	
10	○	○	○	Open	
11	○	●	●	Green	Green signal : 0.7 +/- 3dB, 75 ohms, positive
12	○	○	○	Open	
13	○	○	○	Ground (red)	
14	○	○	○	Ground (blanking)	
15	○	–	–	Red input	0.7 +/- 3dB, 75 ohms, positive
15	–	○	○	(S signal Chroma input)	0.3 +/- 3dB, 75 ohms, positive
16	○	●	●	Blanking input (Ys signal)	High state (1-3V) Low state (0-0.4V) Input impedence : 75 ohms
17	○	○	○	Ground (video output)	
18	○	○	○	Ground (video input)	
19	○	○	○	Video output	1V +/- 3dB, 75ohms, positive sync 0.3V (-3+10dB)
20	○	–	–	Video input	1V +/- 3dB, 75ohms, positive sync 0.3V (-3+10dB)
20	–	○	○	Video input Y (S signal)	1V +/- 3dB, 75ohms, positive sync 0.3V (-3+10dB)
21	○	○	○	Common ground (plug, shield)	

○ Connected   ● Not Connected (open)   * at 20Hz - 20kHz

Rear Connection Panel

| S Video socket pin configuration		
Pin No	Signal	Signal Level
1	Ground	-
2	Ground	-
3	Y (S signal) input	1V +/- 3dB 75ohm, positive Sync. 0.3V -3 +10dB
4	C (S signal) input	0.3V +/- 3dB 75ohm, positive Sync.

S-Video socket

AE-5A SELF DIAGNOSTIC SOFTWARE

The identification of errors within the AE-5A chassis is triggered in one of two ways :- 1: Busy or 2: Device failure to respond to IIC. In the event of one of these situations arising the software will first try to release the bus if busy (Failure to do so will report with a continuous flashing LED) and then communicate with each device in turn to establish if a device is faulty. If a device is found to be faulty the relevant device number will be displayed through the LED (Series of flashes which must be counted) See table 1., non fatal errors are reported using this method.

Diagnostic Item Description	No of times Standby LED Flashes	Probable cause Location	Detected Symptoms
Power does not turn on	Does not light	Power cord is not plugged in. Fuse is open circuit.	Power does not come on No power is supplied to the TV AC power supply is faulty
+B Overcurrent (OCP)	2 times	H.OUT (Q6803/6804) is shorted. (D Board) Linearity FET (Q6806) is shorted. (D Board) IC6604 Power IC is shorted. (D Board)	Power does not come on Load on power line has shorted
Vertical Deflection stopped	4 times	+15V is not supplied R6835 open (D Board) -15V is not supplied R6834 open (D Board) IC6700 is shorted (D Board)	Vertical deflection pulse has stopped Power line has shorted

Error Message	LED Code
No error	00
Reserved	01
OCP (Over Current Protection)	02
OVP (Over Voltage Protection)	03
Vertical Protection	04
Unstable AKB (check starts after 30's, enable TT61 disable TT62)	05
Horizontal Protection	06
Speaker Protection	07
I2C bus 0 error	08
M-B Tele-Text-Decoder	09
M-B ST24C32, NVM	10
J-B TDA9320, Main Colour Decoder	11
B1/B2-B Feature Box	12
B1-B D/A-Converter	13
E-B Backend	14
J-B MSP3410D, Sound Processor	15
J-B CXD2057, Auto Wide	16
External RAM	17

Flash Timing Example : e.g. error number 3

StBy LED

Device acknowledge is used to check IIC errors. Device acknowledge is checked by sending an IIC start sequence during CRT power on. Each device is checked three times, if there is no acknowledge after each attempt, it will be regarded as an error.
There are three steps to check for errors.

1. IIC line 0
    If all devices except the NVM have errors, IIC line 0 error is displayed.
2. Board check
    If all devices mounted on one board have errors, board error is displayed.
3. Each device check
    If IIC line error and board error are not detected then the device with the error is displayed.

The detected errors can be displayed as follows :

1. Error Monitor Menu.
2. Error Reader.

1. Error Monitor Menu

ERROR MONITOR

  1. IGNORE ERRORS   OFF   ON   OFF

Operating Time :   000075   h   15   min

Stored Errors :
   1.   D1 - B CXA1875 or MB88141
   2.   No Error Occured
   3.   No Error Occured
   4.   No Error Occured
   5.   No Error Occured
Current Error :
   Start Error Sequence

Last menu   ◄   Enter Item   ►

2. Error Reader Display

The error reader display is connected to the service connector to read actual error codes. The part number for the error reader display is S-188-900-10. Once an error has been detected it will then be displayed on the two digit error reader. The errors displayed refer to the following table.

Error Code	Error Message
000h	No error occurred
001h	Bus error, IIC0
002h	Bus error, IIC1
100h	**A-Board**
101h	A-B CXA1875, Port Expander
102h	A-B TU1326, Main Tuner
103h	A-B TU1350, Sub Tuner
200h	**B1-Board**
201h	B1-B P83C654, Feature Box B1-B. SDA9280, *D/A Convertor*
202h	B1-B *P83C654, Feature Box B1-B. SDA9280*, D/A Convertor
300h	**B2-Board**
301h	B2-B. SAA4977, BESIC
302h	B2-B. SAA495X, Field Memory
400h	**B3-Board**
401h	B3-B. MID-X
402h	B3-B. Panorama
403h	B3-B. DRC
404h	BK-B. Picture Booster
500h	**D1-Board**
501h	D1-B CXA8070, Dynamic Convertor
502h	D1-B CXA1875, Port Expander
600h	**E-Board**
601h	E-B CXD2100, Backend
700h	**J-Board**
701h	J-B CXD2057, Auto Wide
702h	J-B SDA9288, PIP
703h	J-B TDA9320, Sub Colour Decoder
704h	J-B TDA9320, Main Colour Decoder
705h	J-B CXA1875, Sub-Sound
706h	J-B TDA7309, HP-Amplifier
707h	J-B TEA6422DT, Audio Switch
708h	J-B MSP3410D, Sound Processor
709h	J-B TC9337F, Sound DSP
70Ah	J-B CXA21X69, AV Switch
800h	**M-Board**
801h	M-B ST24C32, NVM

The operating instructions mentioned here are partial abstracts from the 'Operating Instruction Manual'. The page numbers of the 'Operating Instruction Manual' remain as in the manual.

Installation

6. Tuning your TV

Before you tune your TV, you will be asked to set your language and country.

1. The Language/Country menu appears on the TV screen with the word 'English' highlighted.

2. Press the ▲ or ▼ buttons on the remote control to select your chosen language then press the OK button to confirm. The country menu appears on screen with the word 'OFF' highlighted. Select 'OFF' if you do not want your channels stored in a given channel sequence starting from programme position 1.

3. Press ▲ or ▼ to select the country in which you wish to operate the TV then press the OK button to confirm your choice.

4. The 'autotune' menu appears on the TV screen in your selected language. Press the OK button to confirm.

5. Ensure the aerial is connected as instructed, then press the OK button to confirm. The TV starts to automatically search and store all available channels for you. This may take a few minutes - please be patient and do not press any buttons.

6. Once the TV has tuned all available channels the 'Programme Sorting' menu appears on the TV screen enabling you to change the order of the channels on your TV. If you wish to change the channel order, press the ▲ or ▼ buttons to select the channel you want to move, then press ▶. Press the ▲ or ▼ buttons to select the new programme number position for your selected channel then press the OK button to confirm. The selected channel now moves to its new programme position and the other channels move accordingly. Repeat this procedure if you wish to sort the order of other channels on your TV.

7. Press the MENU button to remove the menu from the TV screen.

8. Press the PROGR+/- or the numbered buttons to view the TV channels.

Note: If you would like to stop the autotune process at any stage, press the OK button.

7. Finding your video channel

If you have connected a VCR to your TV, you now need to find your video channel.

1. Press the PROGR+/- buttons on the TV remote control until your video picture appears on the TV screen.

Note: If you wish to move your video channel to a different programme position, refer to the 'Re-arranging TV channels' section of this instruction manual.

Operation

NexTView*

* depending on availability of service

ⓘ NexTView is an on-screen electronic programme guide, providing you with programme information for different broadcasters.

Selecting your NexTView provider

Your TV set automatically selects the best NexTView provider for you. This provider is available about 30 minutes after the channel tuning. You can however change this selection of provider if you wish.

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▲ or ▼ buttons to select the 🏠 symbol on the menu screen then press ▶ to enter the 'Set Up' menu.
3. Press ▲ or ▼ to highlight 'Select NexTView' then press ▶ to confirm. A list is displayed containing all available NexTView providers.
4. Press ▲ or ▼ to select the desired NexTView provider then press the OK button to store.
5. Press the MENU button to remove the menu from the TV screen.

Displaying NexTView

1. Press the 📺 button repeatedly on the remote control to switch NexTView on and off.
   * In some cases, you may also need to press the ▼ button to display the Sony electronic programme guide.
2. Press the ▲, ▼, ◀ or ▶ buttons to move the cursor around the screen.
3. Press the OK button to confirm a selection.
   a. If you press the OK button in the date, time or icon (themes) columns, you change the programme list according to the selection.
   b. If you press the OK button in the programme list, you directly display the channel if the broadcast is currently running, or, you display the 'Long Info' menu if the broadcast is running at some future time.

Index

	full selection list
📋	personal selection
ⓘ	news broadcasts
📺	movies
✈	sports
🎭	entertainment
⚙	children
↩	return to last menu

Using the 'Individual Setting' menu

You can make a personal list of the types of programmes you wish to view on the programme guide.

1. Press the ▲ or ▼ buttons to select the ⊕ icon then press ▶ to display the 'Individual Setting' menu.
2. Press ▲ or ▼ to select your chosen item on the screen then press the OK button to confirm your choice.
3. Repeat step 2 for all the items you wish to have in your list.
4. When you have finished the list, press ▶ to select ↩ on the menu screen.
5. Press the OK button to return to the previous menu.
6. Press the ▲ or ▼ buttons to select the ⊕ icon then press the OK button again to activate your 'Individual Setting' filter.

Teletext

ℹ Most TV channels broadcast information via Teletext. The index page of the teletext service (usually page 100) gives you information on how to use the service. Please use a TV channel with a strong signal, otherwise there may be Teletext errors.

Switching Teletext on and off

1. Select the TV channel which carries the teletext service you want to view.
2. Press the 🔲 button once for Picture and Teletext (P&T). The screen is divided in two, with the TV channel in the right corner and the Teletext display on the left.

ℹ In P&T mode press 🔲 then press PROGR+/- to change the channel of the TV screen. Press ▼ or ▶ to change the size of the TV screen then press 🔲 again to resume normal teletext reception.

3. Press 🔲 twice to get Teletext only.
4. Press 🔲 three times for Mix mode.
5. Press 🔲 a fourth time to switch off Teletext.

Selecting a Teletext page

Input three digits for the page number using the numbered buttons on the remote control. If you make a mistake, type in any three digits then re-enter the correct page number.

Using Other Teletext Functions

Selecting the next or preceding page
Press the 🔳 or 🔳 buttons on the remote control to select the previous or next page.

Selecting a sub page
A teletext page may consist of several sub pages. In this case an information line is displayed, showing the number of subpages. Select the sub page by pressing ▲ or ▼.

To freeze a Teletext page
Press the 🔲 button to freeze the page. Press again to cancel the freeze.

Revealing the index page
Press the 🔲 button to reveal the index page (normally page 100).

Using colour buttons to access pages (Fastext)
(only available if the TV station broadcasts Fastext signals)
When the colour coded menu appears at the bottom of a page, press a coloured button on the remote control (green, red, yellow or blue) to access the corresponding page.

Using the feature 'Page Catching'
1. Press the numbered buttons on the remote control to select a teletext page which has several page numbers on it (eg the index page).
2. Press the OK button.
3. Press ▲ or ▼ to select the desired page number then press the OK button. The requested page is displayed after some seconds.

NexTView

Using the 'Long Info' menu

With this 'Long Info' menu screen, you can set timers or record selected programmes.

1. Press ▲ or ▼ to select a future programme in the programme list column.
2. Press the OK button to display the 'Long Info' menu on the TV screen.

To set the timer
Press the ▼ or ▶ buttons to highlight the ⏻ icon then press the OK button repeatedly to 'set the timer' or 'cancel the timer'. If you choose to set the timer, the programme is marked with a clock symbol and a message appears on the screen shortly before the programme is due to start asking whether you wish to still view this programme.

To view the timer table
Press the ▼ or ▶ buttons to highlight the 🔲 icon then press the OK button repeatedly to switch on/off the timer table. This table shows the programmes on which you have already set a timer. (You can set a timer on up to 5 programmes).

To record programmes*
* (only with Smartlink VCRs)

1. Connect your Smartlink VCR.
2. Press ▼ or ▶ to select 🔲 then press the OK button to download the information to your VCR.
3. To set up the VCR:

VPS/PDC
Press ▼ to select VPS/PDC then press the OK button repeatedly to select 'On' or 'Off'. With this setting on you have the guaranteed recording of the whole broadcast should there be a change in the TV programme. This only works if the selected channel broadcasts a VPS/PDC signal.

Speed
Press ▼ to select 'Speed' the press the OK button repeatedly to select between 'SP' for standard play or 'LP' for longplay. With longplay you can record twice as much on a videotape. The picture quality however may suffer.

VCR Setup
Press ▼ to select 'VCR Setup' then press the OK button repeatedly to select which VCR you wish to programme, namely 'VCR1' or 'VCR2'.

4. Finally, press ▶ to select the 🔲 icon then press the OK button to remove the menu from the TV screen.

Teletext

Using the Teletext menu

1. With Teletext switched on, press the MENU button on the remote control to display the menu on the TV screen.
2. Press ▲ or ▼ to select your chosen item on the screen then press ▶ to display the relevant sub menu.
3. To remove the Teletext menu from the screen, press the MENU button.

Top/Bottom/Full

The Top/Bottom/Full sub menu allows you to enlarge different sections of the Teletext page. Press ▲ to enlarge the upper half of the screen, Press ▼ to enlarge the lower half. Press the OK button to restore the page to normal size. Press ◀ to return to the Teletext menu screen.

Text Clear*

*available on Teletext Only and Mix modes (Refer to 'Switching Teletext on and off')

Text Clear is a function that displays a TV channel while a Teletext page is being searched for.

1. Press the ▤ button on the remote control twice to select full screen text.
2. Press the MENU button to display the 'Teletext' menu.
3. Press ▲ or ▼ to highlight 'Text Clear' and press ▶ to select.
4. The current TV channel is displayed. Once the text page has been found a blue ▤ symbol will appear in the top left hand corner of the screen.
5. Press the ▤ button on the remote control to view the page.

Reveal

Some Teletext pages contain hidden information (eg for a quiz), which can be revealed.

1. In text mode press the MENU button on the remote control to access the 'Teletext' menu.
2. Press ▲ or ▼ to highlight 'Reveal' and press ▶ to select. The hidden information is displayed on the screen.

Time Page*

*depending on availability of service.Time Page is available on Teletext Only and Mix modes

Time Page allows a time-coded Teletext page (such as an alarm page), to be displayed at a set time.

1. In Text mode press the MENU button on the remote control to access the 'Teletext' menu.
2. Press ▲ or ▼ to highlight 'Time Page' and press ▶ to select. The 'Time Page' sub menu is displayed.
3. Enter the desired page number using the numbered buttons on the remote control.
4. Enter the desired time using the remote control.
5. Press OK to confirm the settings. The TV will exit Teletext mode and the time will be displayed in the top left hand corner of the screen. At the requested time the desired page is displayed.

Page Overview*

*only available if TOP-Text is transmitted by the TV station.

In this menu the TOP-Text pages are divided into two columns, the first column showing 'blocks' of pages and the second showing 'groups' of pages.

1. Press ◀ or ▶ to select the first or second column.
2. Press ▲ or ▼ to select the relevant 'group' or 'block' of pages.
3. Press the OK button to display the chosen pages.

Teletext
Top / Bottom / Full
Text Clear
Reveal
Time Page
Page Overview
Select: ▲▼   Enter Menu ▶

Top: ▲   Bottom: ▼   Full: OK

Time Page
PAGE   TIME
Select Page 0-9   Next ▶

Using the TV menu system

The TV consists of a menu system which is based on a series of user friendly on-screen displays and menus. These displays will help you get the most from your TV, helping you to change picture and sound settings, to alter the size of the TV picture and to rearrange the TV channels etc.

Adjusting the picture and sound

The picture and sound are preset at the factory. You can however adjust them to suit your own taste.

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▲ or ▼ buttons to select ▮ for picture settings or ♪ for sound settings then press ▶ to enter either the 'Picture Adjustment' menu or the 'Audio Adjustment' menu.
3. Press the ▲ or ▼ buttons to select the item on the screen you wish to adjust then press ▶ to confirm. For a description of the menu items and their effects, see the table below.
4. Press the ▲, ▼, or ◀ buttons to adjust your selected item.
5. As soon as you have adjusted the item, press the OK button to store the new setting.
6. Repeat steps 3-5 if you wish to adjust any of the other items.
7. Press the MENU button to remove the menu from the TV screen.

Picture Control

Item	Effect/Operation
Picture Mode	▶ Live (for live broadcasts)
	Personal (for individual settings)
	Movie (for movie broadcasts)
	◀ Game (for computer games)
Contrast	Less ▲ More
Brightness*	Darker ▼ Brighter
Colour*	Less ▲ More
Hue**	Reddish ▼ Greenish
Sharpness*	Softer ▲ Sharper

*Only available if 'Personal' is selected in 'Picture Mode'
**Only available for NTSC colour signal (eg. US video tapes)

Item	Effect/Operation
Reset	Resets picture to the factory preset levels
AI (Artificial Intelligence)	▶ Off: Normal
	◀ On: Automatic optimization of contrast level according to the TV signal.
Noise Reduction	▶ High: High noise reduction.
	Mid: Medium noise reduction.
	Low: Low noise reduction.
	Auto: Optimum noise reduction automatically selected.
	◀ Off: No noise reduction.
Digital Mode	▶ Normal: Basic 100Hz picture quality
	DRC 50: Improved picture resolution for viewing scrolling characters
	◀ DRC 100: Optimum picture resolution creating flicker-free pictures
Colour Tone	▶ Warm: Gives a warm tint to the picture.
	Normal: Normal.
	◀ Cool: Gives a cool tint to the picture.

Picture Adjustment
Picture Mode   Personal
Contrast
Brightness
Colour
Sharpness
Reset
AI
Noise Reduction
Digital Mode
Colour Tone
Select: ▲▼ Enter ▶

Picture Mode
Contrast
AI   On
Noise Reduction   Off
Digital Mode   DRC 100
Colour Tone   Normal

Using the TV menu system:

Sound Control

Item	Effect/Operation
Equaliser Mode	▼ Personal Vocal Jazz Rock Pop ▲ Flat (fixed setting, cannot be adjusted)
Equaliser adjustment	You can adjust the mode selected in Equaliser mode by cutting and boosting the 5 selected frequency bands. Press ▼ or ► to select the frequency band then ▼ or ▲ to adjust the frequency. Finally, press the OK button to store the new adjustment.

ⓘ If you want to store the new setting, you need to set the Equaliser mode to 'Personal'. Personal mode permanently stores the setting, all other modes (Vocal, Jazz, Rock, Pop) store only until the next mode change.

Balance	▼ More left ▲ More right
Loudness	▼ Off: Normal ▲ On: For music broadcasts
Space	▼ Off: Normal ▲ On: Special acoustic effect
Auto Vol. Control	▼ On: Volume level of the channels will stay the same independent of the broadcast signal (eg in the case of advertisements) ◄ Off: Volume level changes according to the broadcast signal.
Dual Sound	For a bilingual broadcast: ▼ A for channel 1 ◄ B for channel 2 For a stereo broadcast: ▼ Mono ◄ Stereo

ⓘ When NICAM stereo is being broadcast, the indication NICAM appears briefly on the screen.

Headphones ∩ Volume	Adjusts headphone volume. Can also adjust the volume level of additional equipment connected to the RCA sockets on the rear of the TV.
∩ Dual Sound	Only available when PAP feature is selected: ▼ Stereo: The sound of one screen comes through both the TV loudspeakers and the headphones. ◄ PAP: The sound of the left screen comes through the TV loudspeakers, the sound of the right screen is selectable via headphones.

For more detail on PAP, refer to the 'Operating PAP' section of this manual.

Using the TV menu system:

Using the Features menu

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▲ or ▼ buttons to select ✳ for the 'Features' menu then press ► to enter the 'Features' menu.
3. Press the ▲ or ▼ buttons to select the desired menu item then press ► to confirm. For a description of the menu items and their effects, see the table below.
4. Press the ▲, ▼, ► or ◄ buttons to select the desired setting.
5. Press the OK button to confirm your choice of setting.
6. Repeat steps 3-5 if you wish to select any of the other items.
7. Press the MENU button to remove the menu from the TV screen.

Item	Effect/Operation
Auto Format* *only for aerial signal	▼ Off: Size of picture does not automatically adjust. Normal: Size of picture automatically adjusts according to information from the broadcaster. ◄ Full: The TV will automatically adjust the picture size to eliminate any dark areas on the TV picture (as shown below):
Format Correction* (*only if Auto Format is set to 'Normal' or 'Full')	▼ Off: 4:3/14:9 is selected ◄ On: Smart mode is selected automatically for 4:3/14:9 broadcasts
Sleep Timer	You can select a time after which the TV switches itself into standby mode. ▼ Off ▲ 90 min
Parental Lock	▼ Off: No parental lock. ◄ On: This feature disables the TV buttons when the set is in standby mode. It is only possible to switch the set back on by pressing a button on the remote control.
AV2 Output	▼ TV audio/video signal from the aerial ⅋ AV1 audio/video signal from scart 1 AV2 audio/video signal from scart 2 AV3 audio/video signal from scart 3 ◄ AV4 audio/video signal from connectors on front of the TV

Changing the screen size

ⓘ This feature allows you to change the size of the TV picture.

Press the ⬦ button on the remote control repeatedly or use the ▲ or ▼ buttons to select one of the following formats then press the OK button to confirm your selection:

Smart	imitation of wide screen effect for 4:3 broadcasts.
4:3	conventional 4:3 picture size, full picture information.
14:9	compromise between 4:3 and 16:9 picture size.
Zoom	widescreen format for letterbox movies
Wide	for 16:9 broadcasts.

In Smart, Zoom and 14:9 modes parts of the top and bottom of the screen are cut off. Press ▲ or ▼ to adjust the position of the image on screen (eg to read subtitles) then press the OK button to confirm.

17

Using the TV menu system:

Naming a channel

ⓘ Names for channels are usually taken automatically from Teletext if available. You can however name a channel or an input video source using up to five characters (letters or numbers).

1. Press the MENU button on the remote control to display the menu on the TV screen.

2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu.

3. Press the ▼ button to select 'Manual Set Up' then press ▲ to enter the 'Manual Set Up' menu.

4. Press the ▼ button to select 'Manual Programme Preset' then press ▲ to enter the 'Manual Programme Preset' menu.

5. Press the ◄ or ▼ buttons to select the channel you wish to name.

6. Press the ▲ button repeatedly until the first element of the 'LABEL' column is highlighted.

7. Press the ◄ or ▼ buttons to select a letter or number (select '-' for a blank) then press ▲ to confirm. Select the other four characters in the same way.

8. After selecting all the characters, press the OK button.

9. Repeat steps 5 to 8 if you wish to label other channels.

10. Press the MENU button to remove the menu from the TV screen.

Skipping programme positions

ⓘ This function enables you to skip unused programme positions when selecting them with the PROGR+/- buttons. However, by using the number buttons you can still select the skipped programme position.

1. Press the MENU button on the remote control to display the menu on the TV screen.

2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu.

3. Press the ▼ button to select 'Manual Set Up' then press ▲ to enter the 'Manual Set Up' menu.

4. Press the ▼ button to select 'Manual Programme Preset' then press ▲ to enter the 'Manual Programme Preset' menu.

5. Press the ◄ or ▼ buttons to select the programme position then press ▲ to highlight the 'SKIP' column.

6. Press the ◄ or ▼ buttons to select 'Off' or 'On' (if you wish to skip this programme position) then press the OK button to store.

7. Repeat steps 5 and 6 if you wish to skip or unskip further programme positions.

8. Press the MENU button to remove the menu from the TV screen.

Using the TV menu system:

Re-arranging the TV channels

ⓘ After tuning the TV, you can use this feature to change the order of the channels on the TV.

1. Press the MENU button on the remote control to display the menu on the TV screen.

2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu.

3. Press the ▼ button to select 'Programme Sorting' then press ▲ to enter the 'Programme Sorting' menu.

4. Press the ◄ or ▼ buttons to select the channel you want to move then press ▲ to confirm.

5. Press the ◄ or ▼ buttons to select the new programme position (eg PROG 4) for your selected channel then press the OK button to confirm. The selected channel now moves to its new programme position and the other channels move accordingly.

6. Repeat steps 4 and 5 if you wish to sort the other channels.

7. Press the MENU button to remove the menu from the TV screen.

Manually tuning the TV

ⓘ You have already tuned the TV automatically using the instructions at the start of this manual. You can however carry out this operation manually, adding channels to the TV, one at a time.

1. Press the MENU button on the remote control to display the menu on the TV screen.

2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu.

3. Press the ▼ button to select 'Manual Set Up' on the menu screen then press ▲ to enter the 'Manual Set Up' menu.

4. Press the ▼ button to select 'Manual Programme Preset' on the menu screen then press ▲ to enter the 'Manual Programme Preset' menu.

5. Press the ◄ or ▼ buttons to select a programme number for your channel (eg PROGR 1 for BBC1) then press ▲ to highlight the 'SKIP' column.

6. Press ▲ to select 'OFF' then press ▲ to highlight the 'SYS' column.

7. Press the ◄ or ▼ buttons to select the 'TV broadcast system or 'EXIT' for a video input source (AV1, AV2, ...) then press ▲ to confirm.

8. Press the ◄ or ▼ buttons to select 'C' for terrestrial channels, 'S' for cable channels, or 'F' for direct frequency inputs then press ▲ to confirm.

9. Select the first number digit of 'CH' (channel) then the second number digit of 'CH' with the number buttons on the remote control or
Press the ▼ button to search for the next available channel.

10. If you do not wish to store this channel on the programme number you selected, press the ◄ or ▼ buttons to continue searching for the desired channel.

11. If this is the channel you wish to store, press the OK button.

12. Repeat steps 5-11 if you wish to store more channels then press the MENU button to remove the menu from the TV screen.

16

13

Using the TV menu system:

Using the Further Programme Preset feature

With this feature you can a) adjust the attenuation of each channel, b) individually adjust the volume level of each channel, c) manually fine-tune the TV to obtain a better picture reception if the picture is distorted or d) preset the AV output for the programme positions of channels with scrambled signals (eg from a pay TV decoder). In this way a connected VCR records the unscrambled signal.

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu
3. Press the ▼ button to select 'Manual Set Up' then press ▲ to enter the 'Manual Set Up' menu.
4. Press the ▼ button to select 'Further Programme Preset' then press ▲ to enter the 'Further Programme Preset' menu.
5. Press the ▲ or ▼ buttons to select the relevant programme number then press the ▲ button repeatedly to select a) ATT b) VOL. c) AFT or d) DECODER. The selected item changes colour.

6. a)ATT - RF Attenuator
Press the ▲ or ▼ buttons to switch attenuator 'on' or 'off'. Press the OK button to confirm the selection. Repeat steps 5 and 6a if you wish to adjust the attenuation of the other channels.

b)VOL - Volume Offset
Press the ▲ or ▼ buttons to adjust the volume level (range -7 to +7) of the channel. Store by pressing the OK button. Repeat steps 5 and 6b if you wish to adjust the volume level of the other channels.

c) AFT - Automatic Fine Tuning
Press the ▲ or ▼ buttons to fine tune the channel frequency over a range of -15 to +15. Press the OK button to confirm. Repeat steps 5 and 6c if you wish to fine tune other channels.

d)DECODER
Press the ▲ or ▼ buttons to select AV1 or AV2 for the programme position then press the OK button to confirm. You can now attach a decoder to the AV1 or the AV2 socket on the back of the TV and the picture from that decoder will appear on this programme number. Repeat steps 5 and 6d to preset the AV output for other programme positions.

7. Press the MENU button to remove the menu from the TV screen.

Selecting the 'Demo' feature

This function provides an overview of some of the features available on the TV.

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu
3. Press the ▼ button to select 'Manual Set Up' then press ▲ to enter the 'Manual Set Up' menu.
4. Press the ▼ button to select 'Demo' then press ▲ to start the demonstration (which lasts for approximately 5 minutes).
5. Press the ◻ button to remove the demonstration from the TV screen.

Using the TV menu system:

Adjusting the picture rotation

Because of the earth's magnetism the picture might slant. In this case you can readjust the picture.

1. Press the MENU button on the remote control to display the menu on the TV screen.
2. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu
3. Press the ▼ button to select 'Manual Set Up' then press ▲ to enter the 'Manual Set Up' menu.
4. Press the ▼ button to select 'Picture Rotation' then press ▲ to enter the 'Picture Rotation' sub menu.
5. Press the ▲ or ▼ buttons to rotate the picture over a range of -5 to +5 then press the OK button to store.
6. Press the MENU button to remove the menu from the TV screen.

Adjusting the picture geometry for an RGB source

When connecting an RGB source such as a Sony Playstation you may need to readjust the geometry of the picture.

1. Press the ⊕ button on the remote control to select the connected RGB source ⊕1.
2. Press the MENU button to display the menu on the TV screen.
3. Press the ▼ button to select the ⊞ symbol on the menu screen then press ▲ to enter the 'Set Up' menu
4. Press the ▼ button to select 'Manual Set Up' on the menu screen then press ▲ to enter the 'Manual Set Up' menu
5. Press the ▼ button to select 'RGB Set Up' on the menu screen then press ▲ to enter the 'RGB Set Up' sub menu.
6. Press ▲ to select H Centre then press ▲ or ▼ to adjust the centre of the picture over a range of -10 to +10. Store the new range by pressing the OK button.
7. Press ▲ to select H Size then press ▲ or ▼ to adjust the horizontal coordinates over a range of -10 to +10. Store the new range by pressing the OK button.
8. Press the MENU button to remove the menu from the TV screen.

Specifications

TV system
I

Colour system
PAL, SECAM
NTSC 3.58, 4.43 (only Video In)

Channel coverage
See the 'Channel Display Table' below.

Picture tube
KV-28FQ75: FD Trinitron WIDE, Approx. 72cm (28 inches)
KV-32FQ75: FD Trinitron WIDE, Approx. 82cm (32 inches)

Rear Terminals
⊖-1/⊖1   21-pin Euro connector (CENELEC standard) including audio/
            video input, RGB input, TV audio/video output.
⊖-2/⊖2   21-pin Euro connector (CENELEC standard) including audio/
            video input, S-video input, Selectable audio/video output.
⊖-3/⊖3   21-pin Euro connector (CENELEC standard) including audio/
            video input, S-video input, Monitor audio/video output.
⊖   L/G/SR RCA connectors, variable output for audio signals
          R/D/D/D

Tᴛ   RF In

Front Terminals
⊖4   Video input - phono jacks
⊖4   Audio inputs - phono jacks
⊕⊖4   S video input - 4 pin DIN
⌒:   Headphones jack - minijack stereo

Sound output
Left/Right: 2x20W (Music Power)
              2x10W (RMS)
Sub woofer: 30W (Music Power)
              15W (RMS)

Power consumption
KV-28FQ75: 152W
KV-32FQ75: 160W

Dimensions (wxhxd)
KV-28FQ75: Approx. 788x571x563mm
KV-32FQ75: Approx. 886x620x592mm

Weight
KV-28FQ75: Approx. 46.0kg
KV-32FQ75: Approx. 74.0kg

Accessories supplied
RM-893 remote control (1)
IEC designated size AA batteries (2)

Optional accessory
TV Stand:
KV-28FQ75:   SU28FQ1
KV-32FQ75:   SU32FQ1

Other features
Flat display Trinitron tube, noise reduction, DRC 50Hz picture, DRC 100Hz picture, PAP, PAT, M-PIP, graphic equaliser, 2000 page TEXT memory, personal ID, sleep timer, NexTView, Digital Comb Filter, second tuner.

Design and specifications are subject to change without notice.

Channel Display Table

	Receivable Channels	Channel Displays
I	B21..B69	C21..C69

Troubleshooting

Here are some simple solutions to problems which may affect the picture and sound.

Problem	Suggested remedy
No picture (screen is dark), no sound	• Plug the TV in. • Press the ① button on the front of the TV. • If the ⏻ indicator is on press the I/⏻ button or a numbered button on the remote control. • Check the aerial connection. • Turn the TV off for 3 or 4 seconds and then turn it on again using the ① button on the front of the TV.
Poor or no picture (screen is dark), but good sound.	• Using the MENU system, select the Picture Adjustment display. Adjust the brightness, picture and colour balance levels. • From the Picture Adjustment display select RESET to return to the factory settings.
Good picture, no sound	• Press the ⊿ button on the remote control. • If ✕ is displayed on the screen, press the ✕ button on the remote control.
No colour on colour programmes	• Using the MENU system, select the Picture Adjustment display and adjust the colour setting. • From the Picture Adjustment display select RESET to return to the factory settings.
Distorted picture when changing programmes or selecting Teletext	• Turn off any equipment connected to the scart connectors on the rear of the TV.
Remote control does not function	• Replace the batteries.
The standby indicator ⏻ on the TV flashes	• Contact your nearest Sony service centre.
Interference on picture from external equipment	• Reduce sharpness level.

• **If you continue to have these problems, have your TV serviced by qualified personnel.**
• **NEVER open the casing yourself.**

2-1. Rear Cover Removal

Remove the rear cover fixing screws indicated. Take care when removing the rear cover not to damage the speaker cables [Disconnect the speaker connector] as speakers are fitted inside the rear cover.

2-2. Speaker Connector Disconnection

Before completely removing the rear cover disconnect the speaker connector which is located on the inside.

2-3. Chassis Removal and Refitting

To remove lift the main bracket rear slightly and slide the chassis away from the beznet. Ensure that the interconnecting leads are released from their purse locks to prevent damage being caused.

When refitting the chassis ensure that the main bracket is located in the beznet guide slots before sliding the chassis forwards. Refit the interconnecting leads in their respective purse locks.

2-4. Service Position

Position the PWB as indicated to access the solder side.
To gain access to the D Board follow the instructions on page 19. [Removal and Replacement of the main bracket bottom plates].

2-5. D1 Board Removal

To remove the D1 Board release the clip circled and gently remove the board in a vertical direction.

2-6. J Board Removal

— Clip

Release the two metal bracket support clips located on either side of the chassis. Tilt the bracket very slightly away from the shield case indicated. Release the J board board socket retaining clip and carefully lift the complete assembly vertically.

— Shield case

2-7. B3 Board Removal

Follow the steps indicated in removal of the J board. With the assembly removed access to the B3 board shield is possible. To remove the shield locate and remove the two screws positioned on either side and at opposite ends of the shield. Release the B3 board clip and remove in a vertical direction. Please ensure that the screws are refitted after service.

Screw —

Note :
Removal of the B3, E, and M1 printed circuit boards follows the same procedure of releasing the securing clips as indicated in the fig for D1 board removal.
Take care not to apply to great a pressure to the clips as this may cause damage.

17

2-8. Front Control Module Removal

Remove the two screws fixing the user control module to the front underside of the set. The control module drops down to allow access to the boards.

Screws

2-9. F3 and H6 Board Removal

To remove the F3 and H6 Boards release the clips circled and ease the boards gently away from the main support bracket.

Clips

2-10. H5 Board Removal

To remove the H5 Board, first remove the control door from bracket by releasing the clips circled and pushing them through the main support bracket.

Clips

Removal of H5 Board follows the same procedure as removal of the F3 and H6 Boards.

2-11. Service Connector for H5 Board

If there is a requirement to use the front video and audio sockets when the chassis is placed in its service position, it would be necessary to use an extender board and extension cable as indicated below.

From H5 Board

To CN 1703 on
A Board

Extender board assembly A-1647-037-A

The Extender board and extension cable are available as a service part by ordering the part number as indicated.

WARNING:
BEFORE REMOVING
THE ANODE CAP

High voltage remains in the CRT even after the power is disconnected. To avoid electric shock, discharge CRT *before* attempting to remove the anode cap. Short between anode and CRT coated earth ground strap.

Coated Earth
Ground Strap

1. Discharge the anode of the CRT and remove the anode cap.
2. Unplug all interconnecting leads from the Deflection yoke, neck assy, degaussing coils and CRT grounding strap.
3. Remove the C Board from the CRT.
4. Remove the chassis assembly.
5. Loosen the Neck assembly fixing screw and remove.
6. Loosen the Deflection yoke fixing screw and remove.
7. Place the set with the CRT face down on a cushion and remove the Degaussing Coil holders.
8. Remove the Degaussing Coils.
9. Remove the CRT grounding strap and spring tentioners.
10. Unscrew the four CRT fixing screws [located on each CRT corner] and remove the CRT.
   [Take care not to handle the CRT by the neck.]

Removal of the Anode-Cap

* REMOVING PROCEDURES.

① Turn up one side of the rubber cap in the direction indicated by the arrow ⓐ

② Using a thumb pull up the rubber cap firmly in the direction indicated by the arrow ⓑ

Anode button

③ When one side of the rubber cap is separated from the anode button, the anode-cap can be removed by turning up the rubber cap and pulling it up in the direction of the arrow ⓒ

How to handle the Anode-Cap

1. To prevent damaging the surface of the anode-cap do not use sharp materials.
2. Do not apply too great a pressure on the rubber, as this may cause damage to the anode connector.
3. A metal fitting called a shatter hook terminal is fitted inside the rubber cap.
4. Do not turn the rubber foot over excessively, this may cause damage if the shatter hook sticks out.

19

REMOVAL AND REPLACEMENT OF THE MAIN-BRACKET BOTTOM PLATES.

(1) REMOVING THE PLATES

In the event of servicing being required to the solder side of the D Board printed wiring board, the bottom plates fitted to the main chassis bracket require to be removed.

This is performed by cutting the gates with a sharp wire cutter at the locations indicated by the arrows.

Note : There are 3 plates fitted to the main bracket and secured by 3 gates.

Only remove the necessary plate to gain access to the printed wiring board.

⚠ **For safety reasons, on no account should the plates be removed and not refitted after servicing.**

(2) REFITTING THE PLATES

Because the plates differ in size it is important that the correct plates are refitted in their original location.

Please note that the plates need to be rotated 180 degrees from their cut position to allow the tabs to be fitted into their catch positions.

Catch

Tab

20

- When complete readjustment is necessary or a new picture tube is installed, carry out the following adjustments.
- Unless there are specific instructions to the contrary, carry out these adjustments with the rated power supply.
- Unless there are specific instructions to the contrary, set the controls and switches to the following settings :

  Contrast   .... normal

  Brightness .... normal

Carry out the adjustments in the following order :
3-1.   Beam Landing.
3-2.   Convergence.
3-3.   Focus.
3-4.   White Balance.

Note : Test equipment required.
1.   Color bar/pattern generator.
2.   Degausser.
3.   Oscilloscope.
4.   Digital multimeter.

3-1. Beam Landing

Preparation :

1. In order to reduce the influence of geomagnetism on the set's picture tube, face it in an easterly or westerly direction.
2. Switch on the TV set's power and degauss with a degausser.

(1) Adjustment of Neck Assembly and Y-Splitting Axis.

1. Position the neck assembly as indicated in Fig.3-2.
2. Loosen the deflection yoke fixing screw.
6. Position the Y-splitting axis correction magnets located on the neck assembly as indicated in Fig 3-1.

Fig.3-1

Y-splitting axis correction magnet

Caution :

High voltages are present on the Deflection yoke terminals - take care when handling the Deflection yoke whilst carrying out adjustments.

(2) Landing

Note : Before carrying out the following adjustments adjust the magnets as indicated below [See Fig.3-5].
1. Input a crosshatch signal from the signal generator.
2. Rough-adjust the focus and horizontal convergence.
3. Switch from the crosshatch pattern to an all-red pattern.

4. Move the deflection yoke backwards and adjust with the purity magnet so that the red is at the centre and it aligns symmetrically [See Fig.3-6].
5. Move the deflection yoke forward to the point where the entire screen just becomes red [Mark its position].
6. Move the deflection yoke further forward until the screen just changes colour at the edges. [Mark its position]
7. Position the deflection yoke between the two marks indicated above.
8. Input a crosshatch pattern from the pattern generator and rotate the deflection yoke so that the horizontal lines are parallel with the top and bottom of the screen.
9. When the position of the deflection yoke has been determined, fasten it with its fixing screw.
10. Adjust the upper and lower pin symmetrically by tilting the DY up and down then insert a DY wedge at the top. Use the Y- splitting axis magnets to finely adjust the pin balance. [Fig.3-3].
11. Adjust the H-trap by moving the DY left or right. Insert DY wedges at top and bottom left and top and bottom right. Finely adjust using the H-trap VR on the DY assembly. [See Fig.3-4].
12. Switch the pattern generator to green then blue and confirm the purity.
13. If the beam does not land correctly in all the corners of the screen, use disk magnets to correct it. [Confirm the corner landing for green and blue]

Fig.3-2   Neck assy

Align the edge
of the neck assy with
the edge of the G2 grid
on the G3 side.

Fig.3-3

Fig.3-4

DY Wedges

DY

Fig.3-5

Purity magnets

Align both Purity magnets to the vertical position

Align pips on each magnet

Purity control magnets

Fig.3-6

GREEN
RED
BLUE

Disk magnets or rotatable disk magnets correct these areas (a-d)

Purity control corrects this area

a   b

c   d

Deflection yoke positioning corrects these areas

Disk Magnets

3-2. Convergence

(1) Screen centre convergence [Static convergence]

1. Input a dot pattern signal from the pattern generator.
2. Normalize the picture setting.
3. [Moving vertically], adjust the V.STAT magnet so that the vertical red, green and blue dots coincide at the centre of the screen.

Center dot

R
G
B

R G B

H STAT convergence control

V.STAT Vertical Static Magnet

C Board

RV5375 (H STAT)
H STAT Convergence
(on mount side)

By opening or closing the V.STAT magnet, the red green and blue dots move in the direction indicated below.

B
G
R

B
G
R

Note: Do not adjust the H.STAT by rotating the V.STAT magnets as this can affect the focus setting.

22

4. Correction for HMC [Horizontal mis-convergence] and VMC [Vertical mis-convergence] by using the BMC [Hexapole] magnet.

a). HMC correction by BMC [Hexapole] magnet and movement of the electron beam.

HMC correction(A)   HMC correction(B)

A < B   R   G   B   A > B   R   G   B
        o   o   o   o   o   o

A = B   R   G   B   A = B   R   G   B
        o   o   o   o   o   o

b). VMC correction by BMC [Hexapole] magnet and movement of the electron beam.

VMC correction(A)   VMC correction(B)

C < D   C = D   C > D   C = D
    O R   O R   O R   O R
C   O G   C   O G   O G   O G
D   O B   D   O B   O B   O B

HAMP Adjustment

Adjust the HAMP using HAMPL and HAMPR registers in the Dynamic Convergence section of the service menu.

HTIL Adjustment

THL Correction assy

HTIL correction can be performed by adding a THL correction assembly to the Deflection yoke.

YCH Adjustment

YCH VR
Deflection Yoke

TLV Adjustment

TLV VR
Deflection Yoke

H-TRAP Adjustment

HTRAP VR
Deflection Yoke

The H-TRAP should not be adjusted unless absolutely necessary as it affects the TLV settings.

Layout of each control

Purity magnet
BMC (Hexaploe) magnet
V STAT convergence magnet
Y-splitting axis correction magnet

Note : If you are unable to adjust the corner convergence properly, this can be corrected with the use of permalloy magnets.

a   b

a-d: screen-corner convergence defect

c   d

Install the permalloy assembly for the area that needs correcting.

a

b

Permalloy Assy
X-4387-214-1

c

d   Convergence adjustment with permalloy

1. Receive a television broadcast signal.
2. Normalize the picture setting.
3. Adjust the focus control located on the flyback transformer to obtain the best focus at the centre of the screen.
   Bring only the centre area of the screen into focus, the magenta-ring appears on the screen. In this case, adjust the focus to optimize the screen uniformly.

Focus
Control

3-4. Screen (G2), White Balance

[Adjustment in the service mode using the remote commander]

G2 adjustment [RV5376]

1. Input a dot signal from the pattern generator.
2. Set the Picture, Brightness and Colour to minimum.
3. Apply 170V DC from an external power supply to the R, G and B cathodes of the CRT.
4. Whilst watching the picture, adjust the G2 control RV5376 [SCREEN] located on the C Board to the point just before the flyback return lines disappear.

White balance adjustment for TV mode

1. Input an all-white signal from the pattern generator.
2. Enter into the 'Service Mode' by pressing 'TEST', 'TEST' and 'MENU' 'MENU' on the Service Commander.
3. Select 'Backend' from the on screen menu display and press 'OK'.
4. The 'Backend' menu will appear on the screen.[See Page 26]
5. Set the 'Contrast' to MAX.
6. Set the 'R-Drive' to 41.
7. Adjust the 'G-Drive' and the 'B-Drive' so that the white balance becomes optimum.
8. Press the 'OK' button to write the data for each item.
9. Set the 'Contrast' to MIN.
10. Set the 'R-Cutoff' to 31.
11. Adjust the 'G-Cutoff', and the 'B-Cutoff' with the left and right buttons on the remote commander so that the white balance becomes optimum.
12. Press the 'OK' button to write the data for each item.

4-1. Electrical Adjustments

Service adjustments to this model can be performed using the supplied Remote Commander RM-893.

How to enter into the Service Mode

1. Turn on the main power switch of the set while pressing P + (plus) and P - (minus) buttons on the front drop down control panel.

2. 'TT' will appear in the upper right corner of the screen.
3. Press the 'MENU' button twice on the remote commander to obtain the service menu on the screen.


```
RESET DEVICES              SERVICE MENU                    INITIALISING

Backend                       Initialising                   Model Setting
Deflection                    Reset Devices                  Destination Setting
Ext Deflection                Monitoring                     Basic Setting
Dynamic Convergence           Device Register Setting        Feature Setting
Colour Decoder 1              Special Adjustment
Colour Decoder 2
Audio/Video Switch
Mid-X                       Select :   ▼▲      Next Menu  ►
External PLL Mid-X                                          MONITORING
Panorama Chip
Autowide                                                    Device Status monitor
Sound                                                       Error Monitor
                                                            Production Monitor
                                                            NVM Monitor
                                                            Format Monitor
                                                            CNI Monitor
```

4. Push the joystick up or down on the remote commander to select the adjustment item.
5. Push the right button to proceed to the next menu.
6. If the required adjustment item is 'Deflection', push the down button to move to 'Deflection'.
7. Push the joystick to the right to enter into 'Deflection'.
8. Change the data in order to comply with each standard.

Note :
• Before performing any adjustments ensure that the correct model has been selected in the 'Model Setting' menu.
• After carrying out the service adjustments, to prevent the customer accessing the 'Service Menu' switch the TV set OFF and then ON.

Initialising Menu

```
Initialising

          Model Setting
          Destination Setting
          Basic Setting
          Feature Setting
Select :              Next menu:
```

Model Setting

The menu contains a list with all the available models of this software to set up the TV set in an easy way. The selection of a model is setting data for its features and hardware resources which cannot be detected by the automatic power on H/W detection as well as a special *model byte* to get an unique model identification for models which cannot be differed by features and hardware resources (e.g. KV-28FC60 and KV-28FC60Z)

Before data is set, the user will be asked if he really wants to set a new model. If the user agrees, automatically the destination setting menu is shown.

```
Model Setting

1          KV-28FC60          Reset
2          KV-28FC60Z
3          KV-29FC60
4          KV-32FC60
5          KV-32FC60Z
6          KV-34FC60
7          KV-28FQ75
8          KV-29FQ75
9          KV-32FQ75
10         KV-34FQ75
11         KV-28FS70
12         KV-32FS70
13         KV-36FS70


BLACK          = No Conformity
GREEN          = Compatible Model
RED            = Conformity for all data
```

Table.4-1

Indication of Model Compatibility.

Black:
If any data does not match to specific model, the model name is displayed in black.
Green:
All data which is checked by model setting menu concurs to model except model byte.
Red:
All data which is checked by model setting menu concurs to model including model byte.

Note:
After selecting a model, it may be necessary to reset some devices to get the correct data. (Treble/Bass Offset of Sound, deflection adjustments, ...)

Basic Setting

No	Descr	Min	Max	Data
	Basic setting			
1	Sys.B/G	OFF	ON	ON
2	Sys.D/K	OFF	ON	ON
3	Sys.L	OFF	ON	OFF
4	Sys.I (UK)	OFF	ON	OFF
5	Sys.I (IRL)	OFF	ON	ON
6	TXTNat.option	1	4	3
7	16:9 CRT	OFF	ON	ON
8	Sub-woofer	OFF	ON	ON
9	Auto stand-by	OFF	ON	ON
10	Comb-filter	OFF	ON	ON
11	Auto YC det	OFF	ON	ON
12	Auto comb det	OFF	ON	ON
13	AV2 Available	OFF	ON	ON
14	AV3 Available	OFF	ON	ON
15	AV4 Available	OFF	ON	ON
16	AV3 Fr & rear	OFF	ON	OFF
17	SECAM Tape	OFF	ON	OFF
18	AV1 Sound Mute	OFF	ON	OFF

Table.4-2

Feature Setting

No	Descr	Min	Max	Data
	Feature setting			
1	PAP	OFF	ON	ON
2	PAT	OFF	ON	ON
3	INDEX	OFF	ON	ON
4	EPG	OFF	ON	ON
5	FULL EPG	OFF	ON	ON

Table.4-3

Device Register Setting

```
          Backend
          Deflection
          Ext Deflection
          Dynamic Convergence
          Colour Decoder 1
          Colour Decoder 2
          Audio / Video Switch
          Mid - X
          External PLL Mid - X
          Panorama Chip
          Autowide
          Sound
```

Table.4-4

Audio / Video Switch					
No	Descr	Def	Min	Max	Data
1	CVOUT1	0	0	9	0
2	CVOUT2	2	0	9	2
3	GD1 SW	ON	OFF	ON	ON
4	GD2 SW	ON	OFF	ON	ON
5	YCOUT 1	0	0	7	0
6	YCOUT 2	1	0	7	1
7	LO0CTRL	OFF	OFF	ON	OFF
8	LO1CTRL	OFF	OFF	ON	OFF
9	AOUT 1	3	0	7	3
10	AOUT 2	3	0	7	3
11	AOUT 3MUTE	OFF	OFF	ON	OFF
12	ZCD SW	ON	OFF	ON	ON
13	AOUT 3	3	0	7	3
14	GROUP DEL	15	0	31	15
15	AOUT3 L/R	0	0	3	0
16	AOUT3VOLF	0	0	7	0
17	AOUT3VOLC	3	0	7	3
18	SYNC1	1	0	1	1
19	SYNC2	1	0	1	1

Table.4-5

Special Adjustment				
No	Descr	Min	Max	Data
1	RGB level	0	7	0
2	RGB Gain	0	31	8
3	RGB PatLevel	0	7	0
4	RGB Patgain	0	31	15
5	Extra Fw	0	255	255
6	EPG Chks Check	OFF	ON	ON
7	Slicer High	OFF	ON	ON
8	FCW Wide	OFF	ON	ON
9	Mpeg NR	OFF	ON	OFF
10	Notch Filter	OFF	ON	OFF
11	NLD Step	-7	0	-1
12	PKD Step	-15	0	-5
13	CRD Step	0	15	7
14	SHP Step	-10	0	-3
15	COL Step	-10	0	-1
16	SHP gain Step	-5	0	0
17	VM level Step	-3	0	0
18	NTSC Auto YC AV2	OFF	ON	OFF
19	NTSC Auto YC AV3	OFF	ON	OFF

Table.4-6

Backend					
No	Descr	Def	Min	Max	Data
1	R-on	ON	OFF	ON	ON
2	G-on	ON	OFF	ON	ON
3	B-on	ON	OFF	ON	ON
4	D-col	OFF	OFF	ON	OFF
5	Color-axis	2	0	3	2
6	Contrast	40	0	63	40
7	Limit-Lvl	3	0	3	3
8	Hue	32	0	63	32
9	Colour	31	0	63	31
10	CTI-Level	2	0	3	2
11	Brightness	31	0	63	31
12	Gamma	3	0	3	3
13	Sharpness	30	0	63	28
14	R-Drive	41	0	63	41
15	G-Drive	41	0	63	37
16	B-Drive	41	0	63	25
17	ABL-Mode	0	0	3	2
18	Sub Bright	31	0	63	21
19	VM-Level	2	0	3	1
20	R-Cutoff	31	0	63	31
21	Preover	2	0	3	2
22	G-Cutoff	31	0	63	20
23	DPIC-Level	1	0	3	2
24	B-Cutoff	31	0	63	12
25	DC-Tran	0	0	3	1
26	Sub-Cont	7	0	15	8
27	LRGB2-Lvl	8	0	15	8
28	P-Abl	15	0	15	15
29	Sharp.Fo	ON	OFF	ON	ON
30	Aging-W	OFF	OFF	ON	OFF
31	Aging-B	OFF	OFF	ON	OFF
32	CB-offset1	11	0	15	11
33	CR-offset1	11	0	15	11
34	CB-offset2	7	0	15	7
35	CR-offset2	7	0	15	7
36	Sub Color	0	-8	8	-5

Table.4-7

Colour Decoder 1					
No	Descr	Def	Min	Max	Data
1	Tint	31	0	63	31
2	P/N Gw	OFF	OFF	ON	OFF
3	P/N ID	OFF	OFF	ON	OFF
4	Sub Colour	7	0	15	7
5	Sub Contr	8	0	15	8
6	Sharp FO	1	0	3	1
7	Sharp EQ	2	0	3	2
8	Sharp Gain	8	0	15	8
9	Y-Out Lev	35	0	63	35
10	BS Point	0	0	3	0
11	C-Out Lev	45	0	63	45
12	DC Rest	0	0	3	0
13	BPF FO	2	0	3	2
14	BPF Q	1	0	3	1
15	Filter Sw	OFF	OFF	ON	OFF

Table.4-8

	Colour Decoder 1 (cont)				
No	Descr	Def	Min	Max	Data
16	C-Trap Sw	0	0	1	0
17	S-D Trap	ON	OFF	ON	ON
18	LPF	ON	OFF	ON	ON
19	Y-DL	8	0	10	8
20	N-Comb	ON	OFF	ON	ON
21	Video Sel	0	0	15	0
22	RGB Sel	0	0	3	0
23	Halftone	OFF	OFF	ON	OFF
24	CrOFF.1	7	0	15	11
25	CbOFF.1	7	0	15	11
26	CrOFF.2	7	0	15	7
27	CbOFF.2	7	0	15	7
28	VCD Freq	3	0	7	3
29	VCD Mode	0	0	3	0
30	AFC SENS	1	0	3	1
31	MVM	OFF	OFF	ON	OFF
32	S-R-Y Adj	4	0	15	6
33	S-B-Y Adj	6	0	15	4
34	BELL/HPF	2	0	3	2
35	BELL FO	OFF	OFF	ON	OFF
36	S-GP	0	0	3	0
37	S ID	OFF	OFF	ON	OFF
38	RGB1 ENB	OFF	OFF	ON	OFF
39	HS-PH	1	0	1	0
40	Auto SW	1	0	1	1
41	VP_PH	0	0	1	0
42	S/N RATIO	3	0	3	3

Table.4-9

	Dynamic Convergence				
No	Descr	Def	Min	Max	Data
1	Range	63	0	63	63
2	V Stat	32	0	63	14
3	H Stat	33	0	63	43
4	H amp L	37	0	63	33
5	H amp R	36	0	63	33
6	Up Y	31	0	63	57
7	Low Y	33	0	63	31
8	Y up L	30	0	63	56
9	Y up R	30	0	63	31
10	Y low L	31	0	63	58
11	Y low R	30	0	63	45
12	Mbow Up L	31	0	63	31
13	Mbow Up R	32	0	63	31
14	Mbow Low L	32	0	63	31
15	Mbow Low R	32	0	63	31
16	T Cor PCtrl	OFF	OFF	ON	OFF
17	Top Cor Pin	31	0	63	31
18	B Cor PCtrl	OFF	OFF	ON	OFF
19	Bot Cor Pin	43	0	63	31

Table.4-10

	Sound				
No	Descr	Def	Min	Max	Data
1	Ref.Level	40	0	20	40
2	Auto-gain	ON	OFF	ON	ON
3	Ana-in	0	0	1	0
4	Carr-mute	ON	OFF	ON	ON
5	Clock out	ON	OFF	ON	ON
6	AM-gain	ON	OFF	ON	ON
7	Clip mode	0	0	2	0
8	SCART1 Vol	79	0	127	79
9	SCART2 Vol	79	0	127	79
10	SCART Pr	27	0	127	27
11	I2S1-pr	16	0	127	16
12	I2S2-pr	16	0	127	16
13	FM pr	27	0	127	27
14	BG Nic-pr	53	0	127	53
15	L Nic-pr	59	0	127	59
16	DK Nic-pr	53	0	127	53
17	I Nic-pr	97	0	127	97
18	Irl Nic-pr	97	0	127	97
19	AVC-Decay	2	0	8	2
20	SubW-vol	-4	-127	0	-4
21	SubW-freq	20	5	40	20
22	SubW-HPass	OFF	OFF	ON	OFF
23	Spat-stre	+127	0	-1	127
24	Spat-Coeff	0	0	8	0
25	Bass offs	0	-3	+3	0
26	Treble offs	-1	-3	+3	-1
27	Loudn offs	0	0	9	0
28	Hp-Voloffs	-2	-5	+5	-2
29	M-S Limit	+30	-128	+127	30
30	M-B Limit	-30	-128	+127	-30
31	S-M Limit	+12	-128	+127	12
32	S-B Limit	-20	-128	+127	-20
33	B-M Limit	-12	-128	+127	-12
34	B-S Limit	+20	-128	+127	20
35	Err.Max	40	0	255	40
36	Err.Min	14	0	255	18
37	Vol.Offset	-4	-6	0	-4

Table.4-11

	Ext. Deflection				
No	Descr	Def	Min	Max	Data
1	Linearity	127	0	255	127
2	H Centre	31	0	63	31
3	H Trap	31	0	63	31
4	Rotation	0	0	255	0
5	FocusPhase	127	0	255	127

Table.4-12

No	Descr	Def	Min	Max	Data
	Deflection				
1	V-Size	31	0	63	39
2	V-Position	31	0	63	38
3	V-Comp	0	0	3	0
4	V-Linear	7	0	15	8
5	S-Corr	7	0	15	8
6	H-Size	31	0	63	48
7	EW-DC	OFF	OFF	ON	OFF
8	Akb Tim2	OFF	OFF	ON	OFF
9	Pin-Amp	31	0	63	36
10	H-Comp	0	0	3	0
11	Up-Cpin	31	0	63	30
12	M-Pin	2	0	3	2
13	Lo-CPin	31	0	63	33
14	Trapezium	7	0	15	6
15	H-Position	22	0	63	31
16	VblKw	0	0	3	0
17	AFC-Bow	7	0	15	8
18	AFC-Angle	7	0	15	8
19	Left-Blk	52	0	63	52
20	Right-Blk	11	0	63	11
21	V-Freerun	0	0	3	0
22	V-Aspect	0	0	63	0
23	Zoom-Sw	OFF	OFF	ON	OFF
24	U-Scan	OFF	OFF	ON	OFF
25	V-Scroll	31	0	63	31
26	Akb-Tim	2	0	3	2
27	Up-Vlin	0	0	15	0
28	Lo-Vlin	0	0	15	0

Table.4-13

Deflection System Adjustment

1. Enter into the service mode and select 'Deflection' from the menu. The 'Deflection' adjustment menu will be displayed.
2. Select and adjust each item to obtain the optimum image.

4-2. Volume Electrical Adjustments

Sub Colour Adjustment

1. Input a PAL colour bar signal.
2. Connect an oscilloscope to CN5400 pin 5 located on the C Board.
3. Enter into the 'Service Mode'.
4. Choose 'Backend' from the menu.
5. Adjust 'Sub Colour' data so that the right sides of the waveform are of equal height.

Same Level

B-Out Waveform

4-3. TEST MODE 2:

Is available by pressing the 'TEST' button twice, OSD 'TT' appears. The functions described below are available by selecting the two numbers. To release the 'Test mode 2', press 0, 10, 20 ... twice or switch the TV set into Stand-by mode. Pressing the two Local Control buttons (+ and -) during power ON will also switch into 'TT' mode.

In 'TT' mode, it is possible to remove the Menu from the screen by pressing the Speaker Off button once. Pressing the Speaker OFF button a second time will cause the Menu to reappear. The function is kept even when the menu is not displayed on screen !!.

00	'TT' mode off		54	Dolby on left centre only
01	Picture maximum		55	Dolby on surround speaker only
02	Picture minimum		60	No function
03	Set speaker/headphone Volume to 30%		61	Service mode
04	Set speaker/headphone Volume to 50%		62	Production mode
05	Set speaker/headphone Volume to 65%		63	Copy the picture reset data from ROM into the picture reset location of NVM
06	Set speaker/headphone Volume to 80%		64	Copy the actual adj picture data from NVM to reset location of NVM
07	Ageing mode		65	Reset error codes
08	Shipping Condition		68	Ignore error on
10	No function		69	Ignore errors off
11	Sub picture adjustment		70	No function
12	Sub colour adjustment		71	Copy default dates of PANORAMA chip and external PLL from ROM into NVM
13	Display software version and TV set configeration		72	No function
14	Production Info Display		73	Clear all programmes except 1-5 and all station labels
15	Picture Rotation		74	Adjustment for PIN Amp/Upper Corner Pin for MID, EPG and 12501 mode
16	Picture level 50%		75	Adjustment for Lower Corner Pin/ Trapezoid for MID, EPG and 12501 mode
17	Audio mute on		76	Adjustment for M Pin for 12501 mode
18	No function		77	Picture Booster check
19	Sub brightness adjustment		78	No video blanking
20	No function		79	No function
21	Destination A includes text settings, display TV status		80	No function
22	Destination L includes text settings, display TV status		81	Horizontal adjustment for left picture in PAP mode, text picture in PAT mode and centre picture in INDEX mode. Adjustment is done with left and right joystick button, released by "TV" or "OK" buttons. The corresponding mode must be set before adjustment.
23	Destination E includes text settings, display TV status			
24	Destination U includes text settings, display TV status			
25	Destination D includes text settings, display TV status			
26	Destination B includes text settings, display TV status		82	Horizontal adjustment for right picture in PAP mode and live picture in PAT mode. Adjustment is done with left and right joystick button, released by "TV" or "OK" buttons. The corresponding mode must be set before adjustment.
27	Destination K includes text settings, display TV status			
28	Destination R includes text settings, display TV status			
30	No function			
31	Geometry Adjustment 1			
32	Geometry Adjustment 2		83 - 86	No function
33	Error monitor			
34	No function		87	Personal ID reset
35	CRT 4:3 <> 16:9 ; Display TV status		88	Parental Lock off
36	Line 23 detection switch		89	OSD mute on/off
37	Velocity Modulation (VM) test		90	No function
38	No function		91	Focus adjustment (Focus Phase/Ext. Deflection) with left and right joystick button.
39	No function			
40	No function		92	Focus adjustment (DC Level/Ext. Deflection) with left and right joystick button.
41	Screen mode check			
42	Re-initialise geometry		93	Reserved for software group only
43	No function		94	INDEX mode test command, released by OK or 00
44	No function		95	Dolby Low Pass Filter ON in surround channel
45	No function		96	Dolby Low Pass Filter OFF in surround channel
46	Reserved for dealer commander		97	No action
47	Re-initialise NVM		98	No action
48	Set NVM as non virgin		99	Speaker check, released by OK or 00
49	Set NVM as virgin			
50	No function			
51	Set Dolby volume to 90%			
52	Dolby on left speaker only			
53	Dolby on right speaker only			

5-1. BLOCK DIAGRAMS (1)

5-1. BLOCK DIAGRAMS (2)

5-1. BLOCK DIAGRAMS (3)

D1 (DEFLECTION)

B3 (SIGNAL PROCESSING)

39 40 41 42

5-1. BLOCK DIAGRAMS (4)

M1 (MICRO TEXT)

E (RGB OUT / CHROMA)

C (CRT DRIVE)

VM (VELOCITY MODULATION)

NECK ASSY

5-2. CIRCUIT BOARD LOCATION

5-3. SCHEMATIC DIAGRAMS AND PRINTED WIRING BOARDS

Note :
- All capacitors are in μF unless otherwise noted.
- pF : μμF 50WV or less are not indicated except for electrolytic types.
- Indication of resistance, which does not have one for rating electrical power, is as follows.

Pitch : 5mm
Electrical power rating : 1/4W

- Chip resistors are 1/10W
- All resistors are in ohms.
- k = 1000 ohms, M = 1000,000 ohms.

- : nonflammable resistor.
- : fusible resistor.
- : internal component.
- : pane designation or adjustment for repair.

- All variable and adjustable resistors have characteristic curve B, unless otherwise noted.
- All voltages are in Volts.
- Readings are taken with a 10Mohm digital multimeter.
- Readings are taken with a color bar input signal.
- Voltage variations may be noted due to normal production tolerances.

- : B + bus.
- : B - bus.
- : RF signal path.
- : earth - ground.
- : earth - chassis.

Reference Information

RESISTOR	RN	: METAL FILM
	RC	: SOLID
	FPR0	: NON FLAMMABLE CARBON
	FUSE	: NON FLAMMABLE FUSIBLE
	RS	: NON FLAMMABLE METAL OXIDE
	RB	: NON FLAMMABLE CEMENT
	RW	: NON FLAMMABLE WIREWOUND
		: ADJUSTMENT RESISTOR
COIL	LF-8L	: MICRO INDUCTOR
CAPACITOR	TA	: TANTALUM
	PS	: STYROL
	PP	: POLYPROPYLENE
	PT	: MYLAR
	MPS	: METALIZED POLYESTER
	MPP	: METALIZED POLYPROPYLENE
	ALB	: BIPOLAR
	ALT	: HIGH TEMPERATURE
	ALR	: HIGH RIPPLE

Note : The components identified by shading and marked △ are critical for safety. Replace only with the part numbers specified in the parts list.

Note : Les composants identifiés par une trame et par une marque △ sont d'une importance critique pour la sécurité. Ne les remplacer que par des pièces de numéro spécifié.

43   44   45   46

H5 [FRONT AV, S-VIDEO]

H5.-28-32FQ75

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

CN7103
11P
*S-MICRO
WHT-L

TO A BOARD
CN1703

HEADPHONE R IN	1
GND [HP]	2
HEADPHONE L IN	3
GND [HP]	4
AV3 CHROMA OUT	5
GND	6
AV3 LUMINANCE OUT	7
GND	8
AV3 LEFT OUT	9
GND	10
AV3 RIGHT OUT	11

D7900 XX R7904 JW 5MM D7901 XX D7902 XX D7903 XX

C7926 0.022 C7926 0.022

L7925 10UH L7926 10UH

R7900 JW 5MM R7906 JW 5MM

C7900 100P 500V

J7925 7P

R7901 1K R7902 470K R7903 470K C7901 100P 500V R7907 XX

R7905 1K R7908 XX

R L V

J7900

CN7102
3P
*S-MICRO
WHT-L

TO A BOARD
CN1702

KEY 2	1
KEY [GND]	2
KEY 1	3

R7100 4.7K S7100 AV-SOURCE
R7101 10K CONTROL
R7102 2.2K S7101 VOL -
R7103 10K Vol +
R7104 4.7K S7102 PROG -
R7105 2.2K PROG +

H5 FRONT AV, S-VHS HEADPHONE CONNECTIONS

H5 [PRINTED WIRING BOARD]

32/28/29 FQ75
(CONF-TRIAL)
SONY
H5

CN7103 CN7102

C7925 L7925 C7926 L7926 R7907 R7906 R7908 D7903 D7902 R7904 D7901 D7900 R7900 R7905 C7901 C7900 R7903 R7902 R7901 R7100 R7103 R7102 R7105 R7104 R7101

J7925 J7900 S7100 S7101 S7102

(171852411)
1-678-084-11

H6 [IR RECEIVER FOR SIRCS AND LED]

H6.-28-32FQ75

H6 IR RECEIVER FOR SIRCS. & LED

IC7150
TSOP1740KS1

C7150 220 50V R7151 330

D7150 SLA-570KT3F

R7150 220

VCC OUT GND

CN7100
4P

1	GND
2	STBY +5V
3	SIRCS
4	RESP LED

TO A BOARD
CN1700

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

RESP LED SIRCS STBY5V GND

CN7100
D7150
R7150 R7151
C7150
IC7150

32/28/29 FQ75
(CONF-TRIAL)
SONY
H6
B

H6 [PRINTED WIRING BOARD]

F1 [AC FILTER, FUSE]

F1.-28-32FQ75

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

F1 AC FILTER FUSE

CN7611
*BTOB-L

AC IN	1
AC IN	2

TO POWER-CORD

F7626 H.B.C
VD7526 ERZV14D471

C7626 0.47 300V *AC

R7626 17PF 20% *AC

LF7626 LF1

JW7626 JW7627

JW7628 JW7629

LF7627 LF1

R7627 0.47 10W

CN7633
*BTOB-S
2P

2	AC OUT
1	AC OUT

TO F3 BOARD
CN7633

CN7655
JP
*TAB GND

CN7622
JP
*TAB GND

F1 [PRINTED WIRING BOARD]

CN7611 CN7655 SONY F1

28/29/32 INCH
T5.0AH250V
34/36 INCH
T6.3AH250V

F7626

AC IN AC OUT

EY7077 R7627 EY7078
EY7093 JW7629 EY7076
EY7088 JW7628 LF7626 EY7086 EY7084 EY7082
EY7096 EY7095 C7626 EY7080
R7626 VD7526 EY7087 LF7627 CN7622
EY7089 JW7626 EY7074 EY7081
EY7092 EY7094 EY7075 EY7085 EY7083

F3 [POWER SWITCH]

F3.-28-32FQ75

F3 POWER SWITCH

CN7733
2P

AC IN	1
AC IN	2

TO F1 BOARD
CN7633

S7751

CN7700
2P

2	AC OUT
1	AC OUT

TO D BOARD
CN6700

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

F3 [PRINTED WIRING BOARD]

F3 SONY 32/28/29 FQ75 (CONF-TRIAL)

B CN7700
CN7733
EY7780 EY7778 EY7787 EY7786
EY7785 EY7784
S7751
EY7783 EY7782

E [R,G,B OUT CHROMA]

E [PRINTED WIRING BOARD (B side)]

M1 [PRINTED WIRING BOARD (A side)]

M1 [PRINTED WIRING BOARD (B side)]

52

M1 MICROPROCESSOR & TEXT DECODER

M1 [MICRO PROCESSOR AND TEXT DECODER]

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

TO A BOARD
CN1901

D1 [DEFLECTION]

IC		IC		TRANSISTOR						DIODE		
IC6100	G-2	IC5351	B-5	Q6102	H-3	Q6113	H-4	Q6128	H-4	Q6352	C-3	Q6405	C-1	D6127	D-3	D6354	A-3
IC6101	H-2	IC5352	A-5	Q6103	G-3	Q6118	G-5	Q6129	G-3	Q6353	B-3	Q6455	F-3	D6128	D-3	D6355	C-4
IC6102	G-3	IC5353	D-4	Q6104	F-3	Q6119	G-4	Q6201	G-4	Q6354	B-2	Q6465	D-2	D6129	F-3	D6358	B-2
IC6103	H-5	IC5354	D-2	Q6105	G-2	Q6120	G-4	Q6202	G-4	Q6356	B-5	DIODE		D6253	F-2	D6359	C-1
IC6250	F-3	IC5355	D-1	Q6106	F-2	Q6122	G-4	Q6250	F-4	Q6358	B-2	D6102	G-3	D6255	D-2	D6401	E-4
IC6251	D-2	IC5356	E-1	Q6107	H-2	Q6123	H-3	Q6251	E-4	Q6401	D-5	D6104	G-4	D6350	C-4	D6402	E-4
IC6302	D-3	TRANSISTOR		Q6108	G-2	Q6125	H-5	Q6252	E-2	Q6402	E-5	D6105	G-3	D6351	C-5	D6403	D-1
IC6350	B-3	Q6100	G-3	Q6110	F-2	Q6126	H-5	Q6350	C-4	Q6403	D-4	D6107	H-4	D6352	A-3	D6404	C-1
		Q6101	G-2	Q6112	H-3	Q6127	D-3	Q6351	B-5	Q6404	D-5	D6108	H-4	D6353	B-2	D6405	D-1

D1 [PRINTED WIRING BOARD]

D board Waveforms

TP1 — 570 mVp-p (V)	TP2 — 58 Vp-p (V)
TP3 — 2.28 Vp-p (H)	TP4 — 131 Vp-p (H)
TP7 — 2.14 Vp-p (H)	TP8 — 150 Vp-p (H)
TP5 — 1.07 kVp-p (H)	TP6 — 2.3 Vp-p (H)
TP9 — 1.72 kVp-p (H)	TP10 — 265 Vp-p (H)
TP11 — 1.98 Vp-p (V)	TP12 — 116 Vp-p (V)

IC Voltage Table

Ref No	Pin No	Voltage (V)
IC6600	1	134.7
	2	2.5
	3	9.1
	4	0
IC6700	1	1.4
	3	-12.2
	5	-0.8
	6	15.0
	7	1.4
IC6801	1	0
	2	0
	3	0
	5	2.2
	6	6.7
	7	0.1

Semiconductor Voltage Table

Ref	(e)	(b)	(c)	Ref	(e)	(b)	(c)
Q6676	1.8	2.5	5	Q6503	0	0	11.8
Q6677	1.8	2.1	5	Q6605	0	0.7	0
Q6678	1.8	1.6	5	Q6608	0	0	3.5
Q6807	0	6.4	0	Q6681	0	11.4	0
Q6801	0	0.3	61	Q6851	0	-1	84.6
Q6802	0	-0.4	73.7	Ref	(s)	(g)	(d)
Q6803	0	135.2	0				
Q6804	0	0	135.6	Q6805	0	2	22
Q6602	9.1	11.8	0	Q6806	0	1.4	135.7

D [PRINTED WIRING BOARD]

NOTE:
Portions of the circuit marked as shown are high voltage areas. Use care to prevent electric shock during inspection or repair.

IC				TRANSISTORS														
IC6600	I - 6	IC6654	L - 5			Q6607	I - 5	Q6676	M - 4	Q6700	G - 3	Q6806	C - 4	D6602	F - 10	D6615	M - 3	D6621	L - 2
IC6604	K - 8	IC6667	N - 5	Q6600	G - 10	Q6608	L - 2	Q6677	N - 4	Q6801	B - 8	Q6807	M - 2	D6603	B - 8	D6616	I - 4	D6623	H - 5
IC6651	M - 7	IC6676	M - 5	Q6602	I - 7	Q6611	M - 1	Q6678	M - 4	Q6302	F - 5	Q6851	B - 9	D6604	K - 9	D6617	H - 4	D6624	I - 4
IC6652	G - 1	IC6700	F - 4	Q6603	M - 5	Q6651	N - 5	Q6679	M - 3	Q6303	B - 6	DIODE		D6605	M - 5	D6618	K - 2	D6625	J - 4
IC6653	I - 1	IC6801	C - 1	Q6605	L - 4	Q6652	N - 5	Q6680	M - 3	Q6304	E - 4	D6600	G - 10	D6610	M - 3	D6619	K - 2	D6626	M - 3
				Q6606	M - 1	Q6667	M - 5	Q6681	M - 4	Q6305	D - 4	D6601	G - 10	D6613	M - 4	D6620	I - 3		

D6627	J - 1	D6652	M - 8	D6659	M - 6	D6701	G - 3	D6810	D - 4
D6628	N - 1	D6653	M - 7	D6676	M - 3	D6805	C - 8	D6811	B - 8
D6629	L - 3	D6654	M - 7	D6677	M - 3	D6806	C - 8	D6851	B - 8
D6630	L - 4	D6655	M - 7	D6678	M - 4	D6807	H - 7	D6852	B - 8
D6631	F - 10	D6656	M - 7	D6679	M - 4	D6808	H - 7		
D6651	M - 8	D6658	M - 8	D6681	M - 5	D6809	M - 2		

D [POWER SUPPLY AND DEFLECTION]

A [SIGNAL AND AUDIO AMPLIFIER]

IC Voltage Table

Ref No	Pin No	Voltage (V)
IC1126	1	0
	2	-11
	3	10
	6	-19
	9	0
	10	4.1
	12	-11
IC1151	1	0
	2	-11
	3	10
	6	-18
	9	0
	10	4.1
	12	-11
IC1400	1	0
	3	4.6
	5	4.6
	6	4.0
	9	0
	10	0
	14	4.5
	15	4.5
IC1176	1	0
	3	3
	6	3
	7	0
	8	0
	9	0
	11	3
	12	0
	13	0
	14	0

Semiconductor Location Table

IC		IC	
IC1126	G - 7	Q1403	L - 9
IC1151	H - 7	Q1404	L - 9
IC1176	C - 7	Q1405	M - 3
IC1400	E - 10	Q1406	M - 9
IC1601	L - 4	Q1601	B - 11
IC1604	L - 5	Q1602	C - 9
IC1605	L - 7	Q1626	F - 9
IC1630	I - 2	**DIODE**	
IC1631	L - 2	D1101	B - 9
TRANSISTOR		D1101	B - 9
Q1100	B - 9	D1102	B - 9
Q1101	C - 9	D1103	D - 10
Q1201	F - 12	D1104	E - 14
Q1202	F - 12	D1201	K - 13
Q1204	F - 12	D1401	E - 2
Q1226	J - 15	D1402	E - 2
Q1227	J - 15	D1405	L - 11
Q1229	I - 14	D1406	L - 11
Q1300	G - 13	D1407	L - 11
Q1326	L - 12	D1408	L - 11
Q1327	L - 12	D1601	C - 9
Q1328	K - 13	D1602	C - 9
Q1329	K - 13	D1626	B - 12
Q1401	L - 9	D1627	F - 10
Q1402	L - 9	D1630	H - 1
		D1631	L - 3

Semiconductor Voltage Table

Ref	(e)	(b)	(c)	Ref	(e)	(b)	(c)
Q1100	10.5	10.6	0	Q1229	5	4.9	0
Q1101	0	0	2.2	Q1326	1.2	1.8	4.4
Q1201	0	0.6	0	Q1327	5	4.4	1.7
Q1202	0	0.1	2.1	Q1328	2.6	3.2	8.3
Q1300	0	4.6	0	Q1329	5	8.3	4.5
Q1226	0	0	4.9	Q1601	0	0	5
Q1227	0	0	4.9	Q1602	3.9	3.3	0

A [PRINTED WIRING BOARD]

Semiconductor Location Table

IC		Q8150	A - 5	Q8405	G - 3	D8810	G - 4
IC8101	B - 5	Q8151	A - 5	Q8406	G - 2	D8811	D - 9
IC8150	B - 5	Q8152	A - 5	Q8501	F - 6	D8812	D - 8
IC8151	A - 4	Q8153	A - 5	Q8901	D - 1	D8813	G - 4
IC8200	J - 3	Q8154	A - 4	DIODE		D8814	G - 4
IC8201	J - 4	Q8156	B - 4	D8150	A - 5	D8900	A - 3
IC8202	I - 3	Q8157	C - 4	D8151	A - 5	D8901	J - 8
IC8301	F - 2	Q8200	J - 5	D8152	A - 5	D8902	A - 3
IC8302	F - 1	Q8201	J - 4	D8153	I - 4	D8903	A - 3
IC8401	I - 2	Q8202	I - 4	D8200	B - 8	D8904	J - 7
IC8402	H - 2	Q8300	D - I	D8201	B - 8	D8905	J - 7
IC8500	E - 2	Q8302	E - I	D8202	H - 9	D8906	I - 8
IC8550	G - 1	Q8303	F - 2	D8203	H - 8	D8907	I - 8
IC8601	I - 4	Q8305	E - I	D8801	E - 8	D8908	I - 8
IC8602	H - 1	Q8306	E - I	D8802	F - 4	D8909	I - 7
IC8603	I - 1	Q8308	E - 3	D8803	G - 3	D8910	I - 7
IC8604	I - 7	Q8309	J - 5	D8804	D - 9	D8911	I - 7
IC8700	C - 1	Q8310	E - 2	D8805	D - 8	D8912	D - 3
IC8801	F - 4	Q8401	F - 4	D8806	D - 8	D8913	H - 7
TRANSISTOR		Q8402	C - 7	D8807	D - 8	D8914	H - 7
Q8100	G - 9	Q8403	H - 3	D8808	D - 8	D8915	H - 7
Q8101	F - 9	Q8404	G - 2	D8809	G - 3		

Semiconductor Voltage Table

Ref	(e)	(b)	(c)	Ref	(e)	(b)	(c)
Q8150	2.9	3.6	5.0	Q8302	1.0	1.6	9.0
Q8151	0	0.4	4.8	Q8303	1.3	1.9	7.7
Q8152	0	4.6	0	Q8305	1.3	1.9	7.3
Q8153	0	0.4	4.8	Q8306	0.1	0.1	5.0
Q8154	0	4.6	0	Q8401	0.1	0.1	5.0
Q8156	3.9	4.6	9.0	Q8404	1.2	1.9	7.4
Q8157	3.9	4.6	9.0	Q8809	2.7	2.1	0
Q8200	1.9	2.5	5.0	Q8817	3.9	4.6	9.0
Q8201	1.2	1.9	5.0	Q8901	1.9	2.5	9.0
Q8202	5.1	5.8	9.0	Ref	(s)	(g)	(d)
Q8300	1.6	1.0	0	Q8815	1.8	0	0.6

IC Voltage Table

Ref No	Pin No	Voltage (V)	Ref No	Pin No	Voltage (V)
IC8200	2-3	4.7	IC8100	1-2	1.5
	4-6	2.5		3	0.5
	7	0.6		6	2.6
	17	0.7		7	0.9
	21	5.0		9	1.0
	36	3.8		11	2.8
	37	3.7		12-13	1.8
	38	7.0		14	1.0
	40	7.0		22-23	5.0
	45	3.7		26	5.0
	56-57	3.8		30	5.0
	58	2.6		37	2.4
	60	3.8		40-42	1.9
	67	0.4		44	1.9
	68-69	1.5	IC8101	1	1.2
	71	2.4		3	4.1
	72	2.2		5	0.6
IC8201	1-3	5.0		8	0.5
	5-10	5.0		1	1.8
	12-14	5.0		2-4	4.5
IC8301	1	2.4		5	0
	2	1.9		6-7	4.6
	3	1.5		8	0
	4	0.1		9	4.6
	5	2.4		10	3.4
	7	2.6		11	3.8
	9	0.3	IC8901	13	4.5
	10	0.8		22-30	4.5
	11	2.5		32-41	4.5
	13-14	4.5		43	4.6
	20	2.4		45	3.7
	21	1.8		46	3.5
	22-23	1.9		47	4.5
	24	0.1		49	4.5
	25-27	2.5		51-80	4.5
	29	2.8	IC8151	2	2.4
	37	1.1		3	4.6
	38	4.0		4	4.6
IC8401	1	2.3		5	0.4
	2	1.9		6	4.6
	4	0.1		7	0.4
	9	0.3		9	0
	10	4.0		10	2.6
	11	2.4	IC8150	1	3.0
	20	2.4		2	2.5
	21	1.7		3	1.7
	22-23	1.9		6	4.3
	37	1.1		12	2.4
	38	4.0		13	4.6
	40	3.3		14	2.5
	47	3.8			
	48	1.8			

J [PRINTED WIRING BOARD]

Digital Comb Filter

AUTO WIDE

SUB & B

PIP

COMPONENTS MARKED AS xx ARE NOT FITTED ON THIS MODEL

TO A BOARD
CN1801

J (1/2) INTERFACE/AUDIO/CHROMA/G COMB FILTER

J [INTERFACE, AUDIO, CHROMA, G COMB FILTER (Page 2/2)]

C . . 28-32FQ75

C R, G, B OUT

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

Semiconductor Voltages

Ref	(e)	(b)	(c)	Ref	(e)	(b)	(c)
Q5301	3.5	2.8	0	Q5300	3.7	4.4	3.8
Q5326	3.6	3	0	Q5325	3.7	4.4	3.8
Q5352	3.7	3	0	Q5351	3.8	4.4	3.9
Q5375	10.3	10.9	11	Q5350	11	10.9	3.9
Q5376	11	10.3	10.9				

KV-28FQ75 – W66LLX060X
KV-32FQ75 – W76LLZ060X

IC Voltage Table

Ref No	Pin No	Voltage (V)
IC5300	1	3.9
	3	3.8
	5	8.4
	7	153.0
	8	157.0
	9	152.0
IC5325	1	3.9
	3	3.8
	5	8.7
	7	150.0
	8	155.0
	9	150.0
IC5350	1	3.9
	3	3.8
	5	8.4
	7	150.0
	8	156.0
	9	149.0

C board Waveforms

TP1	TP2
117 Vp-p (H)	109 Vp-p (H)
TP3	TP4
109 Vp-p (H)	2.5 Vp-p (H)
TP5	TP6
2.5 Vp-p (H)	2.5 Vp-p (H)
TP7	
3.64 Vp-p (H)	

1-678-180-11
(171852411)

SONY

C [PRINTED WIRING BOARD]

BL [PRINTED WIRING BOARD (A) SIDE]

IC			
IC2301	E - 9	Q2504	G - 13
IC2501	E - 6	Q2506	G - 13
IC2502	E - 6	Q2507	H - 11
IC2503	F - 6	Q2508	H - 12
IC2504	C - 9	Q2509	G - 12
IC2505	C - 8	Q2510	I - 12
TRANSISTOR		Q2511	J - 12
Q2300	G - 10	Q2512	J - 11
Q2301	F - 8	Q2513	J - 11
Q2302	G - 8	Q2514	J - 11
Q2306	D - 10	Q2515	I - 11
Q2307	F - 10	Q2516	I - 10
Q2308	F - 9	Q2517	E - 8
Q2309	E - 9	Q2518	I - 10
Q2316	C - 9	Q2519	C - 9
Q2318	D - 9	Q2520	D - 10
Q2319	G - 8	Q2521	H - 9
Q2320	G - 9	Q2522	H - 9
Q2322	F - 8	Q2523	I - 9
Q2323	F - 10	Q2524	E - 8
Q2324	A - 7	Q2525	H - 10
Q2325	A - 7	Q2526	H - 10
Q2326	A - 7	Q2527	E - 8
Q2327	A - 6	Q2528	F - 11
Q2331	B - 8	Q2529	G - 11
Q2332	B - 9	Q2530	G - 10
Q2333	B - 9	Q2531	D - 6
Q2334	A - 8	Q2532	F - 8
Q2335	B - 9	Q2533	F - 8
Q2336	B - 9	Q2534	D - 6
Q2337	B - 9	Q2555	C - 9
Q2338	B - 9	Q2566	C - 10
Q2339	G - 9	Q2568	B - 10
Q2340	G - 9	Q2571	E - 10
Q2341	C - 9	**DIODE**	
Q2342	D - 9	D2502	G - 9
Q2344	A - 8	D2503	H - 10
Q2345	A - 9	D2504	G - 9

BL [PRINTED WIRING BOARD (B) SIDE]

BL ANALOGUE NOISE REDUCTION

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

BL [ANALOGUE NOISE REDUCTION]

B3 [100Hz PROCESSING (Page 1/6)]

B3 [PRINTED WIRING BOARD [A] SIDE]

B3 [PRINTED WIRING BOARD [B] SIDE]

B3 (2/6)

B3 [100Hz PROCESSING (Page 2/6)]

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

B3 (3/6)

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

B3 [100Hz PROCESSOR (3/6)]

B3 (4/6)

B3 [100Hz PROCESSING (Page 4/6)]

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

B3 (5/6)

B3[100Hz PROCESSOR (5/6)]

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

B-#AE5A<...>-B3.-28-32FQ75

B3 (6/6)

B-RAE5A<...>-B3.-28-32FQ75

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL

B3 [100Hz PROCESSING (Page 6/6)]

VM.-29FQ75

+135V
+9V

VM VELOCITY MODULATION

COMPONENTS MARKED AS XX ARE NOT FITTED ON THIS MODEL.

TO E BOARD CN4502
TO D1 BOARD CN5502
TO NECK ASS'Y

1-678-178-11
(1718524111)

VM board Waveforms

TP1	TP2	TP3
117 Vp-p (V)	109 Vp-p (V)	109 Vp-p (V)

Semiconductor Voltage Table

Ref	(e)	(b)	(c)
Q5400	0.9	1.5	9.0
Q5401	1.0	1.6	5.2
Q5402	6.0	6.6	9.0
Q5403	5.9	6.0	9.0
Q5404	5.2	5.9	0
Q5405	5.9	5.8	0
Q5406	135.1	134.6	68.2
Q5407	0.8	1.4	68.2
Q5408	7.6	6.9	1.4
Q5409	6.9	7.5	9.0

5-5. IC BLOCK DIAGRAMS

D BOARD IC6700 STV 9379

FLYBACK GENERATOR
POWER AMPLIFIER
THERMAL PROTECTION

J BOARD IC8101 TDA2822D

E BOARD IC4301 CXA2100Q-TL

J BOARD IC8200 MSP3410D-QA-B4

5-4 SEMICONDUCTORS

BA7046F
BA7046F-T1
LM393PS-E20
MB3793-42NF
MB3793-42NF-ER
NJM2240M
NJM2240M(TE2)
NJM3404AD

CXA1855Q-T6

CXA1875AM-T4
HE4094BT
MC14052BDR2
MC74F157ADR2
SN74LS221D
74HCT4046AD/S470

CXD2053S
TDA4780/V3

KA78R05TU
KA78R09TU
KA78R33TU

1 : V IN
2 : V OUT
3 : GND
4 : ON/OFF CONTROL

CAD005AD
LM358
LM393N
M5216P
M24C32-BN6
ST24C16FB6
TDA2822M
UPC393C

LM78L05ACZ
LM78L12ACZ
L78L05ACZ-AP
L78L12ACZ-AP

MB3793-42PNF-ER

MB88141PF-ER

MSP3410D-QA-B4
SAA7185WP
SDA5273P-C134-GEG
SDA5275

M27C80C-100K1

MSM65355GS
SAB-C161R1-LM

SBX1981-51

SDA936I

SDA9288X-B121
TDA9143/N2
TDA9144/N2
TDA9170T
MSM534031E3Y-Z

STV9379

TC4S69F

TC55257DFTL-70V-EL

TDA6111Q/N4

TDA7309D013TR

TDA9320H-N1-518

TEA6422DT
LM393N

TLC2933

TLC5733A

TOP209P

U2860B-BFPG3
74LVC08D

BC546B
BC556B

BF199
BF199-AMMO

BF421-AMMO

BF87-127

IMZ1A-T109

IRF614
IRF620

DTA144EK
DTA144EK-T146
DTC114EK
DTC114YKA-T146
DTC123EK
DTC123EK-T146
DTC124EKA-T146

DTC144EK
DTC144EK-T146
2SA1037K-T-146-R
2SA1162-G
2SC2412K-QR
2SC2412K-T-146-R

DTA144ESA
DTA144ESA-TP
DTC114ESA-TP
DTC144ESA-TP
2SA1175-HFE
2SA733-K

2SC2500-B
2SC2551-O
2SC2551O-TPE2

2SC2688-LK
2SC3840K

2SC3997CA

MARKING SIDE VIEW

2SA933AS-RT
2SA933AS-QRT
2SA933S-RT
2SC1740S-RT
2SC2785-HFE

2SC4793

2SA1837

2SD2396-I

DAN202K
DAN202K-T-146

DAP202K
DAP202K-T-146

DA204K
DA204K-T-146

D1NL20-TA   RGP02-20EG23
D1NL20U-TR   RGP10GPKG23
D1NS4-TR   RGP15GPKG23
EGP20G   S2LA20F
EL1Z   1SS133T-77
GP08D   1SS83
GP08DPKG23   1SS83TD
R2K-V1

CATHODE

ANODE

D10SC4M-F
D10SC6M

D4SB60L
D4SB60L-F
RBA-402L

+   ~   ~   −

+   ~   ~   −

ERA38-06TP1   MTZJ-T-77-9.1
ERA82-004TP1   MTZJ-T-77-12
GP08DPKG23   MTZJ-T-77-22
MTZJ-T-77-12   MTZJ-T-77-18B
MTZJ-T-77-15   MTZJ-33C
MTZJ-T-77-2.2A   RD5.6ESB2
MTZJ-T-77-3-3B   RD9.1ESB2
MTZJ-T-77-3.6A   PGKE200AG23
MTZJ-T-77-4.7B   1SS119-25
MTZJ-T-77-5.6B   1SS119-25TD
MTZJ-T-77-6.8
MTZJ-T-77-7.5B

CATHODE

ANODE

ERC04-06SE

CATHODE

ANODE

ERD08M-15

CATHODE

ANODE

ESAC39M-06C
ESAC39M-06CF38

1   2   3

MA3033-L
MA3033L-TX
MA3056M-TX
MA3062M-TX
MA3030-H-(TX)

NC

MA3051L-TX

CATHODE

ANODE

MA73-TX

1SS355TE-17
RD12SB2
UDZ-TE-17-3.9B
UDZ-TE-17-4.7B
UDZ-TE-17-6.2B
UDZ-TE-17-6.8B
UDZ-TE-12B

ANODE

CATHODE

UF4005PKG23

ANODE

CATHODE

109

Note : Les composants indentifies par une trame et par une marque ⚠ sonte d'une importance critique pour la securite. Ne les remplacer que par des pieces du numero specifie.

Note : The components identified by shading and marked ⚠ are critical for safety. Replace only with the part numbers specified in the parts list.

NOTE :

- Items with no part number and no description are not stocked because they are seldom required for routine service.
- The construction parts of an assembled part are indicated with a collation number in the remarks column.

- Items marked " * " are not stocked since they are seldom required for routine service. Some delay should be anticipated when ordering these items.

6-1. CHASSIS

UK models only

REF. NO.		PART.NO	DESCRIPTION	REMARK
1	⚠	1-571-433-31	SWITCH, PUSH (AC POWER)	
2		*A-1624-085-A	F3 BOARD, COMPLETE	
3		*4-205-196-12	MAIN BRACKET (AE-5A)	
4		*A-1640-328-A	D BOARD, COMPLETE (KV-28FQ75)	
		*A-1640-323-A	D BOARD, COMPLETE (KV-32FQ75)	
5	⚠	1-453-340-11	TRANSFORMER ASSY, FLYBACK	
				(NX-4522//U214)
6		*4-204-476-03	BRACKET, J1	
7		*A-1651-133-A	J BOARD, COMPLETE	
8		*A-1640-382-A	D1 BOARD, COMPLETE (KV-28FQ75)	
		*A-1640-385-A	D1 BOARD, COMPLETE (KV-32FQ75)	
9		*A-1640-383-A	E BOARD, COMPLETE (KV-28FQ75)	
		*A-1640-384-A	E BOARD, COMPLETE (KV-32FQ75)	
10		*A-1620-130-A	B3 BOARD, COMPLETE	

REF. NO.		PART.NO	DESCRIPTION	REMARK
11		*4-204-477-03	BRACKET, J2	
12		1-790-082-11	CABLE, RF	
13		*A-1620-128-A	BL BOARD, COMPLETE	
14		*1-555-716-51	CABLE, PIN	
15	⚠	1-792-389-11	CORD, POWER (WITH CONNECTOR)	
			(KV-28FQ75A/28FQ75B/28FQ75D/28FQ75E/	
			KV-32FQ75A/32FQ75B/32FQ75D/32FQ75E)	
	⚠	1-792-592-11	CORD POWER (WITH PLUG)	
			(KV-28FQ75U/32FG75U)	
16		1-693-338-21	MAIN TUNER/VIF(AEP)	
			(KV-28FQ75A/28FQ75D/28FQ75E/	
			KV-32FQ75A/32FQ75D/32FQ75E)	

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.	PART.NO	DESCRIPTION	REMARK
	1-693-340-21	MAIN TUNER/VIF(FR) (KV-28FQ75B/32FQ75B)		24	1-542-436-11	SPEAKER (24X4.2CM)	
	1-693-339-21	MAIN TUNER/VIF(UK) (KV-28FQ75U/32FQ75U)		25	*A-1678-192-A	WOOFER ASSY (SP) 26-29	
17	1-693-338-21	SUB TUNER/VIF(AEP)		26	4-204-775-21	BAFFLE, WOOFER	
		(KV-28FQ75A/28FQ75D/28FQ75E/		27	4-039-358-01	SCREW (4X16), (+) BV TAPPING	
		KV-32FQ75A/32FQ75D/32FQ75E)		28	1-529-417-11	SPEAKER (8CM)	
	1-693-340-21	SUB TUNER/VIF(FR) (KV-28FQ75B/32FQ75B)		29	4-204-776-21	BOX, WOOFER	
	1-693-339-21	SUB TUNER/VIF(UK) (KV-28FQ75U/32FQ75U)		30	4-205-544-01	COVER, REAR (KV-28FQ75)	
18	*A-1624-086-A	F1 BOARD, COMPLETE			4-205-272-01	REAR COVER (KV-32FQ75)	
19	*A-1634-054-A	M1 BOARD, COMPLETE					
20	*A-1631-094-A	A BOARD, COMPLETE					
		(KV-28FQ75A/28FQ75D/28FQ75E/					
		KV-32FQ75A/32FQ75D/32FQ75E)					
	*A-1631-098-A	A BOARD, COMPLETE (KV-28FQ75B/32FQ75B)					
	*A-1631-102-A	A BOARD, COMPLETE (KV-28FQ75U/32FQ75U)					
21	*A-1646-210-A	H5 BOARD, COMPLETE					
22	*A-1646-211-A	H6 BOARD, COMPLETE					
23	1-542-437-11	TWEETER (2CM)					

6-2. PICTURE TUBE

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.		PART.NO	DESCRIPTION	REMARK
51	X-4200-609-1	BEZNET ASSY (KV-28FQ75)		64		1-419-363-11	COIL, NA ROTATION	
	X-4200-576-1	BEZNET ASSY (KV-32FQ75)		65	⚠	8-453-011-11	NECK ASSY, (NA299-M)	
52	A-1610-072-A	FRONT CONTROL ASSY	53-61	66		*A-1644-108-A	VM BOARD, COMPLETE	
53	*4-205-558-11	BRACKET, CONTROL		67		*A-1638-139-A	C BOARD, COMPLETE	
54	4-205-561-11	WINDOW, ORNAMENTAL		68		4-200-433-01	SPRING, EXTENSION	
55	4-047-464-01	CATCHER, PUSH		69	⚠	1-416-466-11	COIL, DEMAGNETIC (KV-28FQ75)	
56	*4-205-559-11	BRACKET DOOR			⚠	1-416-769-11	COIL, DEMAGNETIC (KV-32FQ75)	
57	3-022-410-01	DAMPER		70		4-203-390-41	CUSHION, DGC	
58	3-703-035-11	SHAFT, LID		71		*4-057-308-01	HOLDER, DGC (KV-28FQ75)	
59	4-205-560-11	BUTTON, POWER				*4-059-569-01	HOLDER, DGC (KV-32FQ75)	
60	4-202-964-11	SPRING		72	⚠	1-251-807-22	CAP ASSY, HIGH-VOLTAGE	
61	4-205-562-11	GUIDE, LIGHT		73		4-203-658-01	SPACER, DY	
62	4-204-636-01	SHEET, BLOTTING		74	⚠	8-737-786-05	PICTURE TUBE (W66LLX060X) (KV-28FQ75)	
63	⚠ 1-451-481-11	DEFLECTION YOKE (Y28RVC2) (KV-28FQ75)			⚠	8-735-054-05	PICTURE TUBE (W76LLX060X) (KV-32FQ75)	
	⚠ 1-451-480-11	DEFLECTION YOKE (Y32RVC2) (KV-32FQ75)						

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.	PART.NO	DESCRIPTION	REMARK
75	4-036-188-12	SCREW, TAPPING (KV-28FQ75)		78	1-452-032-00	MAGNET, DISK; 10MM	
	4-204-225-01	PT-SCREW (KV-32FQ75)		79	X-4387-214-1	PERMALLOY ASSY, CORRECTION	
76	4-308-870-00	CLIP, LEAD WIRE		80	3-701-007-00	BAND, BINDING	
77	1-452-094-00	MAGNET, ROTATABLE DISK; 15MM					

SECTION 7
ELECTRICAL PARTS LIST

Note : Refer to the designated variant parts list when seeking a part indicated by an asterisk (*)

      Parts indicated (#) on the Schematic Diagram are not used in this model and
      therefore do not appear in the Parts List.

F3 H5 H6 BL

REF. NO.	PART.NO	DESCRIPTION			REMARK

*A-1624-085-A   F3 Board, Complete

< CONNECTOR >

REF. NO.	PART.NO	DESCRIPTION
CN7700	⚠ *1-695-292-11	PIN, CONNECTOR (POWER)
CN7733	⚠ *1-580-844-11	PIN, CONNECTOR (POWER)

< SWITCH >

REF. NO.	PART.NO	DESCRIPTION
S7751	⚠ 1-571-433-31	SWITCH, PUSH (AC POWER)

*A-1646-210-A   H5 Board, Complete

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION			
C7900	1-101-810-00	CERAMIC	100PF	5.00%	500V
C7901	1-101-810-00	CERAMIC	100PF	5.00%	500V
C7925	1-137-372-11	MYLAR	0.022UF	5.00%	50V
C7926	1-137-372-11	MYLAR	0.022UF	5.00%	50V

< CONNECTOR >

REF. NO.	PART.NO	DESCRIPTION
CN7102	*1-564-518-11	PLUG, CONNECTOR 3P
CN7103	*1-564-526-11	PLUG, CONNECTOR 11P

< SOCKET >

REF. NO.	PART.NO	DESCRIPTION
J7900	1-794-442-11	TERMINAL BLOCK (LIGHT ANGLE),S
J7925	1-785-448-11	JACK

< COIL >

REF. NO.	PART.NO	DESCRIPTION	
L7925	1-414-183-41	INDUCTOR	10UH
L7926	1-414-183-41	INDUCTOR	10UH

< RESISTOR >

REF. NO.	PART.NO	DESCRIPTION			
R7100	1-249-425-11	CARBON	4.7K	5%	1/4W
R7101	1-249-429-11	CARBON	10K	5%	1/4W
R7102	1-249-421-11	CARBON	2.2K	5%	1/4W
R7103	1-249-429-11	CARBON	10K	5%	1/4W
R7104	1-249-425-11	CARBON	4.7K	5%	1/4W
R7105	1-249-421-11	CARBON	2.2K	5%	1/4W
R7900	1-535-303-00	LEAD, JUMPER (5.0MM)			
R7901	1-249-417-11	CARBON	1K	5%	1/4W
R7902	1-247-895-91	CARBON	470K	5%	1/4W
R7903	1-247-895-91	CARBON	470K	5%	1/4W
R7904	1-535-303-00	LEAD, JUMPER (5.0MM)			
R7905	1-249-417-11	CARBON	1K	5%	1/4W
R7906	1-535-303-00	LEAD, JUMPER (5.0MM)			

< SWITCH >

REF. NO.	PART.NO	DESCRIPTION
S7100	1-771-947-11	SWITCH, TACTILE
S7101	1-771-947-11	SWITCH, TACTILE
S7102	1-771-947-11	SWITCH, TACTILE

*A-1646-211-A   H6 Board, Complete

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION			
C7150	1-126-969-11	ELECT	220UF	20.00%	50V

< CONNECTOR >

REF. NO.	PART.NO	DESCRIPTION
CN7100	*1-564-519-11	PLUG, CONNECTOR 4P

< DIODE >

REF. NO.	PART.NO	DESCRIPTION
D7125	*4-203-258-11	HOLDER, LED
D7150	8-719-030-11	DIODE SLA-570KT3F

< IC >

REF. NO.	PART.NO	DESCRIPTION
IC7150	8-749-014-59	IC TSOP1740KS1

< RESISTOR >

REF. NO.	PART.NO	DESCRIPTION			
R7150	1-247-815-91	CARBON	220	5%	1/4W
R7151	1-249-411-11	CARBON	330	5%	1/4W

*A-1620-128-A   BL Board, Complete

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION			
C2300	1-164-222-11	CERAMIC CHIP 0.22UF			25V
C2301	1-164-222-11	CERAMIC CHIP 0.22UF			25V
C2302	1-164-222-11	CERAMIC CHIP 0.22UF			25V
C2303	1-164-222-11	CERAMIC CHIP 0.22UF			25V
C2304	1-164-222-11	CERAMIC CHIP 0.22UF			25V
C2305	1-104-664-11	ELECT	47UF	20.00%	16V
C2306	1-104-664-11	ELECT	47UF	20.00%	16V
C2307	1-104-664-11	ELECT	47UF	20.00%	16V
C2308	1-126-933-11	ELECT	100UF	20.00%	16V
C2309	1-163-038-91	CERAMIC CHIP 0.1UF			25V
C2310	1-163-038-91	CERAMIC CHIP 0.1UF			25V
C2311	1-163-259-91	CERAMIC CHIP 220PF		5.00%	50V
C2312	1-163-259-91	CERAMIC CHIP 220PF		5.00%	50V
C2313	1-163-259-91	CERAMIC CHIP 220PF		5.00%	50V
C2314	1-163-259-91	CERAMIC CHIP 220PF		5.00%	50V
C2317	1-163-038-91	CERAMIC CHIP 0.1UF			25V
C2320	1-104-664-11	ELECT	47UF	20.00%	16V
C2321	1-104-664-11	ELECT	47UF	20.00%	16V
C2322	1-104-664-11	ELECT	47UF	20.00%	16V
C2323	1-163-038-91	CERAMIC CHIP 0.1UF			25V
C2324	1-163-038-91	CERAMIC CHIP 0.1UF			25V

REF.NO.	PART.NO	DESCRIPTION	REMARK	REF.NO.	PART.NO	DESCRIPTION	REMARK
C2325	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C2536	1-104-664-11	ELECT 47UF	20.00% 16V
C2326	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V	C2537	1-104-664-11	ELECT 47UF	20.00% 16V
C2327	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V	C2538	1-165-319-11	CERAMIC CHIP 0.1UF	50V
C2328	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V	C2539	1-165-319-11	CERAMIC CHIP 0.1UF	50V
C2329	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C2540	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V
C2330	1-104-664-11	ELECT 47UF	20.00% 16V	C2541	1-163-135-00	CERAMIC CHIP 560PF	5.00% 50V
C2331	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C2542	1-163-255-11	CERAMIC CHIP 150PF	5.00% 50V
C2332	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C2543	1-163-133-00	CERAMIC CHIP 470PF	5.00% 50V
C2338	1-104-664-11	ELECT 47UF	20.00% 16V	C2544	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V
C2342	1-104-664-11	ELECT 47UF	20.00% 16V	C2545	1-163-113-00	CERAMIC CHIP 68PF	5.00% 50V
C2344	1-104-664-11	ELECT 47UF	20.00% 16V	C2546	1-165-319-11	CERAMIC CHIP 0.1UF	50V
C2347	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C2547	1-165-319-11	CERAMIC CHIP 0.1UF	50V
C2348	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C2548	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V
C2349	1-104-664-11	ELECT 47UF	20.00% 16V	C2550	1-163-229-11	CERAMIC CHIP 12PF	5.00% 50V
C2350	1-104-664-11	ELECT 47UF	20.00% 16V	C2567	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C2351	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C2572	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C2352	1-104-664-11	ELECT 47UF	20.00% 16V				
C2353	1-163-237-11	CERAMIC CHIP 27PF	5.00% 50V			< CONNECTOR >	
C2355	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				
C2501	1-126-964-11	ELECT 10UF	20.00% 50V	CN2301	1-695-301-11	CONNECTOR, BOARD TO BOARD 40P	
C2502	1-126-964-11	ELECT 10UF	20.00% 50V			< DIODE >	
C2504	1-163-255-11	CERAMIC CHIP 150PF	5.00% 50V				
C2505	1-163-255-11	CERAMIC CHIP 150PF	5.00% 50V	D2502	8-719-914-43	DIODE DAN202K-T-146	
C2506	1-163-253-11	CERAMIC CHIP 120PF	5.00% 50V	D2503	8-719-914-43	DIODE DAN202K-T-146	
C2507	1-163-253-11	CERAMIC CHIP 120PF	5.00% 50V	D2504	8-719-914-43	DIODE DAN202K-T-146	
C2508	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V			< DELAY LINE >	
C2509	1-126-933-91	ELECT 100UF	20.00% 16V				
C2510	1-126-933-91	ELECT 100UF	20.00% 16V	DL2501	1-234-515-11	FILTER, LOW PASS	
C2511	1-165-319-11	CERAMIC CHIP 0.1UF	50V	DL2502	1-234-515-11	FILTER, LOW PASS	
C2512	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V				
						< FILTER >	
C2513	1-165-319-11	CERAMIC CHIP 0.1UF	50V				
C2515	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V	FL2300	1-234-479-11	FILTER, LOW PASS	
C2516	1-126-964-11	ELECT 10UF	20.00% 50V	FL2301	1-236-071-11	ENCAPSULATED COMPONENT	
C2518	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V	FL2501	1-234-515-11	FILTER, LOW PASS	
C2519	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V				
						< IC >	
C2521	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V				
C2522	1-126-967-11	ELECT 47UF	20.00% 50V	IC2301	8-752-067-36	IC CXA1815S	
C2523	1-165-319-11	CERAMIC CHIP 0.1UF	50V	IC2501	8-759-710-86	IC NJM2233BM(TE2)	
C2524	1-126-964-11	ELECT 10UF	20.00% 50V	IC2502	8-759-190-29	IC BA7655AF-E1	
C2525	1-126-964-11	ELECT 10UF	20.00% 50V	IC2503	8-759-710-24	IC NJM319M-TE2	
				IC2504	8-759-708-05	IC TA78L005AP-TPE6	
C2526	1-126-964-11	ELECT 10UF	20.00% 50V				
C2528	1-165-319-11	CERAMIC CHIP 0.1UF	50V	IC2505	8-752-072-94	IC CXA1875AM-T4	
C2529	1-163-259-91	CERAMIC CHIP 220PF	5.00% 50V				
C2530	1-163-087-00	CERAMIC CHIP 4PF	0.25PF 50V			< COIL >	
C2531	1-165-319-11	CERAMIC CHIP 0.1UF	50V				
				L2300	1-414-183-41	INDUCTOR 10UH	
C2533	1-126-964-11	ELECT 10UF	20.00% 50V	L2301	1-410-435-21	INDUCTOR 220UH	
C2535	1-104-664-11	ELECT 47UF	20.00% 16V	L2302	1-410-435-21	INDUCTOR 220UH	

REF. NO.	PART. NO	DESCRIPTION	REMARK	REF. NO.	PART. NO	DESCRIPTION	REMARK
L2303	1-410-427-11	INDUCTOR 47UH		Q2345	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2321	1-216-295-91	SHORT 0		Q2504	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2322	1-216-295-91	SHORT 0		Q2506	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2323	1-216-295-91	SHORT 0		Q2507	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2501	1-535-303-00	LEAD, JUMPER (5.0MM)		Q2508	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2502	1-535-303-00	LEAD, JUMPER (5.0MM)		Q2509	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
L2503	1-410-426-11	INDUCTOR 39UH		Q2510	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
L2504	1-410-431-11	INDUCTOR 100UH		Q2511	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2505	1-410-431-11	INDUCTOR 100UH		Q2512	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2506	1-408-615-31	INDUCTOR 100UH		Q2513	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2507	1-408-615-31	INDUCTOR 100UH		Q2514	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2508	1-408-605-31	INDUCTOR 15UH		Q2515	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2509	1-410-419-21	INDUCTOR 10UH		Q2516	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2510	1-535-303-00	LEAD, JUMPER (5.0MM)		Q2517	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
L2512	1-535-303-00	LEAD, JUMPER (5.0MM)		Q2518	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
		< TRANSISTOR >		Q2519	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
				Q2520	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2300	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2521	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q2301	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2522	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2302	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2523	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2306	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R					
Q2307	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2524	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
				Q2525	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2308	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2526	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2309	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2527	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2316	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		Q2528	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2318	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R					
Q2319	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		Q2529	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
				Q2530	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q2320	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2531	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2322	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2532	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2323	1-801-806-11	TRANSISTOR DTC144EKA-T146		Q2533	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2324	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R					
Q2325	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2534	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
				Q2555	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q2326	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		Q2566	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q2327	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2568	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR	
Q2331	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		Q2571	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q2332	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR					
Q2333	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR				< RESISTOR >	
Q2334	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2301	1-216-017-91	RES-CHIP 47 5% 1/10W	
Q2335	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2302	1-216-043-91	RES-CHIP 560 5% 1/10W	
Q2336	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		R2303	1-216-045-00	RES-CHIP 680 5% 1/10W	
Q2337	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2304	1-216-045-00	RES-CHIP 680 5% 1/10W	
Q2338	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		R2305	1-216-047-91	RES-CHIP 820 5% 1/10W	
Q2339	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2306	1-216-037-00	RES-CHIP 330 5% 1/10W	
Q2340	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		R2307	1-216-037-00	RES-CHIP 330 5% 1/10W	
Q2341	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R		R2308	1-535-143-21	LEAD, JUMPER (12.5MM)	
Q2342	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2309	1-535-143-11	LEAD, JUMPER (12.5MM)	
Q2344	8-729-120-28	TRANSISTOR 2SC2412K-T-146-QR		R2310	1-216-671-11	METAL CHIP 6.8K 0.5% 1/10W	

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R2311	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2370	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R2312	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W	R2371	1-216-662-11	METAL CHIP	3K	0.5%	1/10W
R2315	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2372	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R2316	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R2373	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R2317	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2374	1-216-662-11	METAL CHIP	3K	0.5%	1/10W
R2318	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2375	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R2321	1-216-041-00	RES-CHIP	470	5%	1/10W	R2383	1-216-295-91	SHORT	0		
R2322	1-216-041-00	RES-CHIP	470	5%	1/10W	R2385	1-216-025-91	RES-CHIP	100	5%	1/10W
R2323	1-216-041-00	RES-CHIP	470	5%	1/10W	R2386	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R2325	1-216-025-91	RES-CHIP	100	5%	1/10W	R2387	1-216-649-11	METAL CHIP	820	0.5%	1/10W
R2329	1-216-025-91	RES-CHIP	100	5%	1/10W	R2389	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2330	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2390	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2331	1-216-025-91	RES-CHIP	100	5%	1/10W	R2391	1-216-041-00	RES-CHIP	470	5%	1/10W
R2332	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2392	1-216-025-91	RES-CHIP	100	5%	1/10W
R2333	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2393	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R2334	1-216-017-91	RES-CHIP	47	5%	1/10W	R2394	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R2335	1-216-017-91	RES-CHIP	47	5%	1/10W	R2397	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2336	1-216-017-91	RES-CHIP	47	5%	1/10W	R2398	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2337	1-216-017-91	RES-CHIP	47	5%	1/10W	R2399	1-216-041-00	RES-CHIP	470	5%	1/10W
R2338	1-216-017-91	RES-CHIP	47	5%	1/10W	R2400	1-216-025-91	RES-CHIP	100	5%	1/10W
R2339	1-216-017-91	RES-CHIP	47	5%	1/10W	R2401	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2340	1-216-017-91	RES-CHIP	47	5%	1/10W	R2402	1-216-089-91	RES-CHIP	47K	5%	1/10W
R2341	1-216-017-91	RES-CHIP	47	5%	1/10W	R2403	1-216-041-00	RES-CHIP	470	5%	1/10W
R2342	1-216-025-91	RES-CHIP	100	5%	1/10W	R2404	1-216-041-00	RES-CHIP	470	5%	1/10W
R2343	1-216-025-91	RES-CHIP	100	5%	1/10W	R2407	1-216-041-00	RES-CHIP	470	5%	1/10W
R2344	1-216-017-91	RES-CHIP	47	5%	1/10W	R2408	1-216-295-91	SHORT	0		
R2345	1-216-017-91	RES-CHIP	47	5%	1/10W	R2411	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2346	1-216-017-91	RES-CHIP	47	5%	1/10W	R2413	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2347	1-216-017-91	RES-CHIP	47	5%	1/10W	R2414	1-216-295-91	SHORT	0		
R2348	1-216-017-91	RES-CHIP	47	5%	1/10W	R2415	1-216-647-11	METAL CHIP	680	0.5%	1/10W
R2351	1-216-025-91	RES-CHIP	100	5%	1/10W	R2418	1-216-025-91	RES-CHIP	100	5%	1/10W
R2352	1-216-025-91	RES-CHIP	100	5%	1/10W	R2421	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2353	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2422	1-216-295-91	SHORT	0		
R2354	1-216-017-91	RES-CHIP	47	5%	1/10W	R2423	1-216-029-00	RES-CHIP	150	5%	1/10W
R2355	1-216-017-91	RES-CHIP	47	5%	1/10W	R2424	1-216-039-00	RES-CHIP	390	5%	1/10W
R2356	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2425	1-216-041-00	RES-CHIP	470	5%	1/10W
R2357	1-216-017-91	RES-CHIP	47	5%	1/10W	R2426	1-216-035-00	RES-CHIP	270	5%	1/10W
R2358	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2427	1-216-035-00	RES-CHIP	270	5%	1/10W
R2359	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2428	1-216-045-00	RES-CHIP	680	5%	1/10W
R2360	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2432	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
R2361	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2436	1-216-025-91	RES-CHIP	100	5%	1/10W
R2362	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2437	1-216-051-00	RES-CHIP	1.2K	5%	1/10W
R2364	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2502	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W
R2366	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2503	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R2367	1-216-041-00	RES-CHIP	470	5%	1/10W	R2505	1-216-649-11	METAL CHIP	820	0.5%	1/10W
R2368	1-216-039-00	RES-CHIP	390	5%	1/10W	R2506	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R2369	1-216-037-00	RES-CHIP	330	5%	1/10W	R2511	1-216-053-00	RES-CHIP	1.5K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R2513	1-216-637-11	METAL CHIP	270	0.5%	1/10W	R2565	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R2514	1-216-059-00	RES-CHIP	2.7K	5%	1/10W	R2566	1-216-648-11	METAL CHIP	750	0.5%	1/10W
R2515	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R2567	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2516	1-216-649-11	METAL CHIP	820	0.5%	1/10W	R2568	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R2517	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R2569	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R2518	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R2570	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2519	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R2571	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W
R2521	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R2572	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W
R2522	1-216-025-91	RES-CHIP	100	5%	1/10W	R2573	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R2523	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R2574	1-216-295-91	SHORT	0		
R2525	1-216-055-00	RES-CHIP	1.8K	5%	1/10W	R2575	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2526	1-216-033-00	RES-CHIP	220	5%	1/10W	R2576	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R2528	1-216-033-00	RES-CHIP	220	5%	1/10W	R2577	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R2529	1-216-055-00	RES-CHIP	1.8K	5%	1/10W	R2578	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R2530	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2579	1-216-053-00	RES-CHIP	1.5K	5%	1/10W
R2531	1-216-631-11	METAL CHIP	150	0.5%	1/10W	R2580	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R2532	1-216-073-00	RES-CHIP	10K	5%	1/10W	R2581	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R2534	1-216-049-91	RES-CHIP	1K	5%	1/10W	R2582	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R2535	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2583	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R2536	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	R2584	1-216-049-91	RES-CHIP	1K	5%	1/10W
R2537	1-216-059-00	RES-CHIP	2.7K	5%	1/10W	R2585	1-216-081-00	RES-CHIP	22K	5%	1/10W
R2538	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R2586	1-216-073-00	RES-CHIP	10K	5%	1/10W
R2539	1-216-059-00	RES-CHIP	2.7K	5%	1/10W	R2587	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R2540	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R2588	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R2541	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	R2589	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R2542	1-216-647-11	METAL CHIP	680	0.5%	1/10W	R2590	1-216-647-11	METAL CHIP	680	0.5%	1/10W
R2543	1-216-647-11	METAL CHIP	680	0.5%	1/10W	R2591	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R2544	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R2592	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R2545	1-216-623-11	METAL CHIP	68	0.5%	1/10W	R2593	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R2546	1-216-655-11	METAL CHIP	1.5K	0.5%	1/10W	R2594	1-216-643-11	METAL CHIP	470	0.5%	1/10W
R2547	1-216-641-11	METAL CHIP	390	0.5%	1/10W	R2611	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2548	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R2614	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R2549	1-216-623-11	METAL CHIP	68	0.5%	1/10W	R2615	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R2551	1-216-655-11	METAL CHIP	1.5K	0.5%	1/10W	R2617	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2552	1-216-615-91	METAL CHIP	33	0.5%	1/10W	R2640	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2553	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R2644	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R2554	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R2649	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2555	1-216-073-00	RES-CHIP	10K	5%	1/10W	R2661	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R2556	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R2662	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R2557	1-216-063-91	RES-CHIP	3.9K	5%	1/10W	R2664	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R2558	1-216-073-00	RES-CHIP	10K	5%	1/10W	R2666	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R2559	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W	R2676	1-216-295-91	SHORT	0		
R2560	1-216-643-11	METAL CHIP	470	0.5%	1/10W	R2678	1-216-295-91	SHORT	0		
R2561	1-216-653-11	METAL CHIP	1.2K	0.5%	1/10W	R2680	1-216-665-11	METAL CHIP	3.9K	0.5%	1/10W
R2562	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R2681	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R2563	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R2684	1-216-639-11	METAL CHIP	330	0.5%	1/10W
R2564	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R2687	1-216-049-91	RES-CHIP	1K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.	PART.NO	DESCRIPTION	REMARK
R2688	1-216-295-91	SHORT 0		C361	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
R2691	1-216-295-91	SHORT 0		C362	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
R2692	1-216-295-91	SHORT 0		C363	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
R2698	1-216-295-91	SHORT 0		C501	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
R2699	1-216-295-91	SHORT 0		C502	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
				C503	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
*A-1620-130-A		**B3 Board, Complete**		C505	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
				C507	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
		< CAPACITOR >		C509	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
				C510	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C302	1-104-601-11	ELECT CHIP 10UF	20.00% 10V				
C305	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C511	1-163-038-91	CERAMIC CHIP 0.1UF	25V
C306	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C512	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C309	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C514	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C310	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C515	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
				C516	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C312	1-163-275-11	CERAMIC CHIP 0.001UF	5.00% 50V				
C313	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C517	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C314	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C518	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
C315	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V	C519	1-163-038-91	CERAMIC CHIP 0.1UF	25V
C316	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C520	1-163-038-91	CERAMIC CHIP 0.1UF	25V
				C521	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C317	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				
C318	1-124-779-00	ELECT CHIP 10UF	20.00% 16V	C522	1-163-038-91	CERAMIC CHIP 0.1UF	25V
C319	1-124-779-00	ELECT CHIP 10UF	20.00% 16V	C523	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C320	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C524	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
C321	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C525	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
				C526	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C323	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				
C324	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C527	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C325	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C528	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C327	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C530	1-216-295-91	SHORT 0	
C330	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C532	1-216-295-91	SHORT 0	
				C534	1-216-295-91	SHORT 0	
C331	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V				
C332	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C538	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C333	1-216-295-91	SHORT 0		C539	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
C337	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C540	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C338	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C542	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
				C543	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C339	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V				
C340	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C545	1-126-396-11	ELECT CHIP 47UF	20.00% 16V
C341	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C546	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C346	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C548	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C347	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C549	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
				C550	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C349	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				
C350	1-126-204-11	ELECT CHIP 47UF	20.00% 16V	C551	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C353	1-126-204-11	ELECT CHIP 47UF	20.00% 16V	C554	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C354	1-104-601-11	ELECT CHIP 10UF	20.00% 10V	C555	1-163-038-91	CERAMIC CHIP 0.1UF	25V
C355	1-104-601-11	ELECT CHIP 10UF	20.00% 10V	C556	1-126-392-11	ELECT CHIP 100UF	20.00% 6.3V
				C557	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C357	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				
C358	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C559	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C359	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C560	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C360	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V				

REF.NO.	PART.NO	DESCRIPTION	REMARK	REF.NO.	PART.NO	DESCRIPTION	REMARK
C601	1-124-779-00	ELECT CHIP 10UF	20.00% 16V	C705	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C602	1-126-394-11	ELECT CHIP 10UF	20.00% 16V	C706	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C603	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C707	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
C604	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C708	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C605	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C709	1-110-501-11	CERAMIC CHIP 0.33UF	10.00% 16V
C606	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C710	1-163-019-00	CERAMIC CHIP 0.0068UF	10.00% 50V
C607	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C711	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C608	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C712	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C609	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C713	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C610	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C714	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C611	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C715	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C612	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C716	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C613	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C717	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C614	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C718	1-126-204-11	ELECT CHIP 47UF	20.00% 16V
C615	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C719	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C616	1-126-396-11	ELECT CHIP 47UF	20.00% 16V	C722	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C617	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C723	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C618	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C724	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C619	1-163-038-91	CERAMIC CHIP 0.1UF	25V	C725	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C620	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C726	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C621	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C727	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C622	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C728	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C623	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C729	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C624	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C730	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C625	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C735	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C626	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C738	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C627	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C739	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V
C628	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C740	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V
C629	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C801	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
C630	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C802	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C631	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C803	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
C632	1-126-206-11	ELECT CHIP 100UF	20.00% 6.3V	C804	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
C633	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C806	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C634	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C807	1-124-779-00	ELECT CHIP 10UF	20.00% 16V
C635	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C808	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C636	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C809	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C637	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C810	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C638	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C811	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C639	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C812	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C640	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C813	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C642	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C814	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C643	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C815	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C644	1-126-603-11	ELECT CHIP 4.7UF	20.00% 35V	C816	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C645	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C817	1-163-229-11	CERAMIC CHIP 12PF	5.00% 50V
C646	1-163-243-11	CERAMIC CHIP 47PF	5.00% 50V	C818	1-163-229-11	CERAMIC CHIP 12PF	5.00% 50V
C703	1-126-394-11	ELECT CHIP 10UF	20.00% 16V	C819	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C704	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C820	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V

REF.NO.	PART.NO	DESCRIPTION	REMARK		REF.NO.	PART.NO	DESCRIPTION	REMARK
C821	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FB802	1-414-766-21	IND FERRITE 0UH	
C822	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V					
C823	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V				< FILTER >	
C824	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V					
C825	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL304	1-234-177-21	FILTER, CHIP EMI	
					FL305	1-234-177-21	FILTER, CHIP EMI	
C826	1-164-489-11	CERAMIC CHIP 0.22UF	10.00% 16V		FL306	1-239-558-11	FILTER, CHIP EMI	
C827	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL501	1-233-877-11	FILTER, LOW PASS	
C829	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL502	1-233-504-21	FILTER, LOW PASS	
C834	1-163-038-91	CERAMIC CHIP 0.1UF	25V					
C835	1-163-038-91	CERAMIC CHIP 0.1UF	25V		FL503	1-233-504-21	FILTER, LOW PASS	
					FL504	1-234-177-21	FILTER, CHIP EMI	
C837	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL505	1-234-177-21	FILTER, CHIP EMI	
C839	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL506	1-234-177-21	FILTER, CHIP EMI	
C840	1-126-206-11	ELECT CHIP 100UF	20.00% 6.3V		FL508	1-234-177-21	FILTER, CHIP EMI	
C841	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V					
C842	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL509	1-234-177-21	FILTER, CHIP EMI	
					FL510	1-234-177-21	FILTER, CHIP EMI	
C843	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL511	1-234-177-21	FILTER, CHIP EMI	
C844	1-163-038-91	CERAMIC CHIP 0.1UF	25V		FL512	1-234-177-21	FILTER, CHIP EMI	
C848	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V		FL601	1-234-177-21	FILTER, CHIP EMI	
C849	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V					
C850	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL602	1-234-177-21	FILTER, CHIP EMI	
					FL603	1-234-177-21	FILTER, CHIP EMI	
C851	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL606	1-239-560-11	FILTER, CHIP EMI	
C852	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL701	1-234-177-21	FILTER, CHIP EMI	
C901	1-163-038-91	CERAMIC CHIP 0.1UF	25V		FL703	1-234-177-21	FILTER, CHIP EMI	
C902	1-163-038-91	CERAMIC CHIP 0.1UF	25V					
C903	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		FL704	1-234-177-21	FILTER, CHIP EMI	
					FL705	1-234-177-21	FILTER, CHIP EMI	
C904	1-124-779-00	ELECT CHIP 10UF	20.00% 16V		FL801	1-234-177-21	FILTER, CHIP EMI	
C905	1-109-982-11	CERAMIC CHIP 1UF	10.00% 10V		FL802	1-234-177-21	FILTER, CHIP EMI	
C906	1-124-779-00	ELECT CHIP 10UF	20.00% 16V		FL803	1-234-177-21	FILTER, CHIP EMI	
C907	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V					
					FL804	1-234-177-21	FILTER, CHIP EMI	
		< CONNECTOR >			FL805	1-234-177-21	FILTER, CHIP EMI	
					FL806	1-234-177-21	FILTER, CHIP EMI	
CN502	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P			FL807	1-234-177-21	FILTER, CHIP EMI	
					FL808	1-234-177-21	FILTER, CHIP EMI	
		< DIODE >						
					FL810	1-234-177-21	FILTER, CHIP EMI	
D301	8-719-041-97	DIODE MA113-(TX)			FL901	1-234-509-21	FILTER, LOW PASS	
D302	8-719-041-97	DIODE MA113-(TX)			FL902	1-233-876-11	FILTER, LOW PASS	
D501	8-719-422-12	DIODE UDZ-TE-17-3.9B			FL903	1-233-876-11	FILTER, LOW PASS	
					FL904	1-234-177-21	FILTER, CHIP EMI	
		< FERRITE BEAD >						
					FL905	1-234-177-21	FILTER, CHIP EMI	
FB501	1-414-234-21	FERRITE 0UH						
FB502	1-414-234-21	FERRITE 0UH					< IC >	
FB503	1-414-234-21	FERRITE 0UH						
FB504	1-414-234-21	FERRITE 0UH			IC302	8-752-388-98	IC CXD2303AQ-TL	
FB601	1-414-766-21	IND FERRITE 0UH			IC303	8-752-088-27	IC CXA3266Q-T6	
					IC304	8-759-285-51	IC PC74HC00D-T	
FB701	1-414-766-21	IND FERRITE 0UH			IC305	8-759-232-74	IC SN74HC163ANSR	
FB702	1-414-766-21	IND FERRITE 0UH			IC306	8-759-232-74	IC SN74HC163ANSR	
FB801	1-414-766-21	IND FERRITE 0UH						

REF.NO.	PART.NO	DESCRIPTION	REMARK	REF.NO.	PART.NO	DESCRIPTION	REMARK
IC307	8-759-084-79	IC TC7S14F(TE85R)		Q517	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC308	8-759-084-79	IC TC7S14F(TE85R)		Q518	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC309	8-759-640-16	IC TC7SET04F(TE85R)		Q519	1-801-806-11	TRANSISTOR DTC144EKA-T146	
IC310	8-759-285-52	IC PC74HC02D-T		Q520	1-801-806-11	TRANSISTOR DTC144EKA-T146	
IC311	8-759-708-05	IC TA78L005AP-TPE6		Q521	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC501	8-759-447-90	IC TLC5733AIPM		Q522	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC504	8-759-430-32	IC TLC2933IPWR		Q523	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC505	8-759-640-16	IC TC7SET04F(TE85R)		Q524	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC506	8-759-640-16	IC TC7SET04F(TE85R)		Q601	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC601	8-752-398-47	IC CXD2090Q		Q602	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
IC602	8-759-665-38	IC MB81F161622C-80FN		Q901	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC603	8-759-295-09	IC TLC2932IPW-E20		Q902	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC604	8-752-072-94	IC CXA1875AM-T4		Q903	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC701	8-759-640-18	IC TMC57127-MMP-54		Q904	8-729-028-28	TRANSISTOR 2SK2036(TE85L)	
IC704	8-759-640-17	IC MSM534031E-22GS-KR1		Q905	8-729-028-28	TRANSISTOR 2SK2036(TE85L)	
IC705	8-759-242-70	IC TC7WU04F(TE12R)		Q907	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC801	8-759-592-40	IC CXD9509Q		Q908	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC802	8-759-595-53	IC MB81F643242B-10FN		Q909	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
IC901	8-752-369-84	IC CXD2309Q-T6					
						< RESISTOR >	
		< COIL >					
				R302	1-216-013-00	RES-CHIP 33 5% 1/10W	
L302	1-412-029-11	INDUCTOR CHIP 10UH		R303	1-216-667-11	METAL CHIP 4.7K 0.5% 1/10W	
L303	1-412-029-11	INDUCTOR CHIP 10UH		R305	1-216-049-91	RES-CHIP 1K 5% 1/10W	
L501	1-412-026-11	INDUCTOR CHIP 1UH		R306	1-216-658-11	METAL CHIP 2K 0.5% 1/10W	
L502	1-412-026-11	INDUCTOR CHIP 1UH		R309	1-216-009-91	RES-CHIP 22 5% 1/10W	
L503	1-412-026-11	INDUCTOR CHIP 1UH					
				R310	1-216-009-91	RES-CHIP 22 5% 1/10W	
L504	1-412-026-11	INDUCTOR CHIP 1UH		R311	1-216-009-91	RES-CHIP 22 5% 1/10W	
L505	1-412-029-11	INDUCTOR CHIP 10UH		R313	1-216-009-91	RES-CHIP 22 5% 1/10W	
L506	1-412-026-11	INDUCTOR CHIP 1UH		R316	1-216-009-91	RES-CHIP 22 5% 1/10W	
L508	1-412-029-11	INDUCTOR CHIP 10UH		R318	1-216-009-91	RES-CHIP 22 5% 1/10W	
L509	1-412-029-11	INDUCTOR CHIP 10UH					
				R319	1-216-049-91	RES-CHIP 1K 5% 1/10W	
L511	1-412-026-11	INDUCTOR CHIP 1UH		R321	1-216-009-91	RES-CHIP 22 5% 1/10W	
L512	1-412-026-11	INDUCTOR CHIP 1UH		R323	1-216-009-91	RES-CHIP 22 5% 1/10W	
L604	1-412-029-11	INDUCTOR CHIP 10UH		R324	1-216-009-91	RES-CHIP 22 5% 1/10W	
L605	1-412-029-11	INDUCTOR CHIP 10UH		R325	1-216-073-00	RES-CHIP 10K 5% 1/10W	
		< TRANSISTOR >		R328	1-216-025-91	RES-CHIP 100 5% 1/10W	
				R330	1-216-037-00	RES-CHIP 330 5% 1/10W	
Q301	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R331	1-216-033-00	RES-CHIP 220 5% 1/10W	
Q302	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R332	1-216-037-00	RES-CHIP 330 5% 1/10W	
Q303	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R333	1-216-295-91	SHORT 0	
Q501	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R					
Q502	8-729-120-28	TRANSISTOR 2SC2412K-T-146-S		R335	1-216-013-00	RES-CHIP 33 5% 1/10W	
				R336	1-216-013-00	RES-CHIP 33 5% 1/10W	
Q503	8-729-120-28	TRANSISTOR 2SC2412K-T-146-S		R337	1-216-097-91	RES-CHIP 100K 5% 1/10W	
Q510	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R338	1-216-295-91	SHORT 0	
Q511	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R339	1-216-295-91	SHORT 0	
Q512	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R					
Q516	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R		R340	1-216-073-00	RES-CHIP 10K 5% 1/10W	
				R341	1-216-295-91	SHORT 0	

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R342	1-216-295-91	SHORT	0			R559	1-216-077-91	RES-CHIP	15K	5%	1/10W
R344	1-216-295-91	SHORT	0			R560	1-216-619-11	METAL CHIP	47	0.5%	1/10W
R345	1-216-073-00	RES-CHIP	10K	5%	1/10W	R561	1-216-043-91	RES-CHIP	560	5%	1/10W
R347	1-216-295-91	SHORT	0			R562	1-216-043-91	RES-CHIP	560	5%	1/10W
R350	1-216-295-91	SHORT	0			R563	1-216-043-91	RES-CHIP	560	5%	1/10W
R501	1-216-025-91	RES-CHIP	100	5%	1/10W	R571	1-216-295-91	SHORT	0		
R502	1-216-025-91	RES-CHIP	100	5%	1/10W	R572	1-216-619-11	METAL CHIP	47	0.5%	1/10W
R503	1-216-295-91	SHORT	0			R573	1-216-679-11	METAL CHIP	15K	0.5%	1/10W
R504	1-216-295-91	SHORT	0			R574	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R505	1-216-295-91	SHORT	0			R575	1-216-625-11	METAL CHIP	82	0.5%	1/10W
R506	1-216-025-91	RES-CHIP	100	5%	1/10W	R576	1-216-625-11	METAL CHIP	82	0.5%	1/10W
R507	1-216-025-91	RES-CHIP	100	5%	1/10W	R577	1-216-619-11	METAL CHIP	47	0.5%	1/10W
R508	1-216-025-91	RES-CHIP	100	5%	1/10W	R578	1-216-619-11	METAL CHIP	47	0.5%	1/10W
R509	1-216-025-91	RES-CHIP	100	5%	1/10W	R579	1-216-077-91	RES-CHIP	15K	5%	1/10W
R510	1-216-043-91	RES-CHIP	560	5%	1/10W	R580	1-216-295-91	SHORT	0		
R511	1-216-043-91	RES-CHIP	560	5%	1/10W	R582	1-216-041-00	RES-CHIP	470	5%	1/10W
R512	1-216-043-91	RES-CHIP	560	5%	1/10W	R584	1-216-041-00	RES-CHIP	470	5%	1/10W
R513	1-216-043-91	RES-CHIP	560	5%	1/10W	R594	1-216-041-00	RES-CHIP	470	5%	1/10W
R514	1-216-043-91	RES-CHIP	560	5%	1/10W	R596	1-216-049-91	RES-CHIP	1K	5%	1/10W
R515	1-216-043-91	RES-CHIP	560	5%	1/10W	R597	1-216-073-00	RES-CHIP	10K	5%	1/10W
R516	1-216-049-91	RES-CHIP	1K	5%	1/10W	R600	1-216-066-00	RES-CHIP	5.1K	5%	1/10W
R517	1-216-049-91	RES-CHIP	1K	5%	1/10W	R601	1-216-073-00	RES-CHIP	10K	5%	1/10W
R518	1-216-295-91	SHORT	0			R602	1-216-073-00	RES-CHIP	10K	5%	1/10W
R520	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R603	1-216-073-00	RES-CHIP	10K	5%	1/10W
R521	1-216-295-91	SHORT	0			R604	1-216-033-00	RES-CHIP	220	5%	1/10W
R523	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R605	1-216-295-91	SHORT	0		
R524	1-216-295-91	SHORT	0			R608	1-216-295-91	SHORT	0		
R526	1-216-645-11	METAL CHIP	560	0.5%	1/10W	R609	1-216-073-00	RES-CHIP	10K	5%	1/10W
R528	1-216-037-00	RES-CHIP	330	5%	1/10W	R610	1-216-033-00	RES-CHIP	220	5%	1/10W
R529	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R611	1-216-073-00	RES-CHIP	10K	5%	1/10W
R530	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R612	1-216-073-00	RES-CHIP	10K	5%	1/10W
R531	1-216-031-00	RES-CHIP	180	5%	1/10W	R613	1-216-073-00	RES-CHIP	10K	5%	1/10W
R532	1-216-669-11	METAL CHIP	5.6K	0.5%	1/10W	R616	1-216-073-00	RES-CHIP	10K	5%	1/10W
R533	1-216-031-00	RES-CHIP	180	5%	1/10W	R617	1-216-295-91	SHORT	0		
R536	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R618	1-216-295-91	SHORT	0		
R537	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R619	1-216-073-00	RES-CHIP	10K	5%	1/10W
R540	1-216-049-91	RES-CHIP	1K	5%	1/10W	R621	1-216-295-91	SHORT	0		
R548	1-216-619-11	METAL CHIP	47	0.5%	1/10W	R622	1-216-295-91	SHORT	0		
R549	1-216-619-11	METAL CHIP	47	0.5%	1/10W	R623	1-216-295-91	SHORT	0		
R550	1-216-625-11	METAL CHIP	82	0.5%	1/10W	R625	1-216-295-91	SHORT	0		
R551	1-216-625-11	METAL CHIP	82	0.5%	1/10W	R626	1-216-073-00	RES-CHIP	10K	5%	1/10W
R552	1-216-619-11	METAL CHIP	47	0.5%	1/10W	R628	1-216-295-91	SHORT	0		
R553	1-216-295-91	SHORT	0			R629	1-216-073-00	RES-CHIP	10K	5%	1/10W
R554	1-216-619-11	METAL CHIP	47	0.5%	1/10W	R631	1-216-295-91	SHORT	0		
R555	1-216-077-91	RES-CHIP	15K	5%	1/10W	R634	1-216-295-91	SHORT	0		
R557	1-216-049-91	RES-CHIP	1K	5%	1/10W	R635	1-216-295-91	SHORT	0		
R558	1-216-025-91	RES-CHIP	100	5%	1/10W	R638	1-216-295-91	SHORT	0		

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R639	1-216-017-91	RES-CHIP	47	5%	1/10W	R696	1-216-049-91	RES-CHIP	1K	5%	1/10W
R640	1-216-009-91	RES-CHIP	22	5%	1/10W	R697	1-216-117-00	RES-CHIP	680K	5%	1/10W
R642	1-216-295-91	SHORT	0			R698	1-216-117-00	RES-CHIP	680K	5%	1/10W
R643	1-216-295-91	SHORT	0			R699	1-216-295-91	SHORT	0		
R645	1-216-295-91	SHORT	0			R703	1-216-295-91	SHORT	0		
R651	1-216-295-91	SHORT	0			R704	1-216-295-91	SHORT	0		
R653	1-216-025-91	RES-CHIP	100	5%	1/10W	R705	1-216-295-91	SHORT	0		
R654	1-216-033-00	RES-CHIP	220	5%	1/10W	R709	1-216-005-00	RES-CHIP	15	5%	1/10W
R655	1-216-295-91	SHORT	0			R710	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R657	1-216-009-91	RES-CHIP	22	5%	1/10W	R712	1-216-049-91	RES-CHIP	1K	5%	1/10W
R658	1-216-049-91	RES-CHIP	1K	5%	1/10W	R713	1-216-295-91	SHORT	0		
R659	1-216-025-91	RES-CHIP	100	5%	1/10W	R714	1-216-121-91	RES-CHIP	1M	5%	1/10W
R660	1-216-025-91	RES-CHIP	100	5%	1/10W	R715	1-216-033-00	RES-CHIP	220	5%	1/10W
R661	1-216-025-91	RES-CHIP	100	5%	1/10W	R801	1-216-009-91	RES-CHIP	22	5%	1/10W
R663	1-216-295-91	SHORT	0			R802	1-216-009-91	RES-CHIP	22	5%	1/10W
R664	1-216-009-91	RES-CHIP	22	5%	1/10W	R804	1-216-073-00	RES-CHIP	10K	5%	1/10W
R665	1-216-035-00	RES-CHIP	270	5%	1/10W	R806	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R666	1-216-646-11	METAL CHIP	620	0.5%	1/10W	R807	1-216-637-11	METAL CHIP	270	0.5%	1/10W
R667	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R812	1-216-073-00	RES-CHIP	10K	5%	1/10W
R668	1-216-009-91	RES-CHIP	22	5%	1/10W	R813	1-216-295-91	SHORT	0		
R669	1-216-295-91	SHORT	0			R814	1-216-073-00	RES-CHIP	10K	5%	1/10W
R670	1-216-295-91	SHORT	0			R815	1-216-073-00	RES-CHIP	10K	5%	1/10W
R671	1-216-073-00	RES-CHIP	10K	5%	1/10W	R816	1-216-073-00	RES-CHIP	10K	5%	1/10W
R672	1-216-073-00	RES-CHIP	10K	5%	1/10W	R817	1-216-613-11	METAL CHIP	27	0.5%	1/10W
R673	1-216-073-00	RES-CHIP	10K	5%	1/10W	R818	1-216-295-91	SHORT	0		
R674	1-216-073-00	RES-CHIP	10K	5%	1/10W	R820	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R675	1-216-073-00	RES-CHIP	10K	5%	1/10W	R822	1-216-295-91	SHORT	0		
R676	1-216-073-00	RES-CHIP	10K	5%	1/10W	R823	1-216-073-00	RES-CHIP	10K	5%	1/10W
R677	1-216-073-00	RES-CHIP	10K	5%	1/10W	R824	1-216-073-00	RES-CHIP	10K	5%	1/10W
R678	1-216-073-00	RES-CHIP	10K	5%	1/10W	R825	1-216-621-11	METAL CHIP	56	0.5%	1/10W
R679	1-216-073-00	RES-CHIP	10K	5%	1/10W	R826	1-216-641-11	METAL CHIP	390	0.5%	1/10W
R680	1-216-073-00	RES-CHIP	10K	5%	1/10W	R827	1-216-607-11	METAL CHIP	15	0.5%	1/10W
R681	1-216-073-00	RES-CHIP	10K	5%	1/10W	R834	1-216-629-11	METAL CHIP	120	0.5%	1/10W
R682	1-216-073-00	RES-CHIP	10K	5%	1/10W	R835	1-216-623-11	METAL CHIP	68	0.5%	1/10W
R683	1-216-073-00	RES-CHIP	10K	5%	1/10W	R836	1-216-611-11	METAL CHIP	22	0.5%	1/10W
R684	1-216-073-00	RES-CHIP	10K	5%	1/10W	R840	1-216-295-91	SHORT	0		
R685	1-216-073-00	RES-CHIP	10K	5%	1/10W	R844	1-216-009-91	RES-CHIP	22	5%	1/10W
R686	1-216-073-00	RES-CHIP	10K	5%	1/10W	R845	1-216-009-91	RES-CHIP	22	5%	1/10W
R687	1-216-295-91	SHORT	0			R846	1-216-009-91	RES-CHIP	22	5%	1/10W
R688	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R847	1-216-009-91	RES-CHIP	22	5%	1/10W
R689	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R848	1-216-009-91	RES-CHIP	22	5%	1/10W
R690	1-216-295-91	SHORT	0			R849	1-216-009-91	RES-CHIP	22	5%	1/10W
R691	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R850	1-216-009-91	RES-CHIP	22	5%	1/10W
R692	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R851	1-216-009-91	RES-CHIP	22	5%	1/10W
R693	1-216-009-91	RES-CHIP	22	5%	1/10W	R852	1-216-009-91	RES-CHIP	22	5%	1/10W
R694	1-216-295-91	SHORT	0			R853	1-216-009-91	RES-CHIP	22	5%	1/10W
R695	1-216-047-91	RES-CHIP	820	5%	1/10W	R854	1-216-009-91	RES-CHIP	22	5%	1/10W

REF.NO.	PART.NO	DESCRIPTION			REMARK	REF.NO.	PART.NO	DESCRIPTION			REMARK
R855	1-216-009-91	RES-CHIP	22	5%	1/10W	R904	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R856	1-216-009-91	RES-CHIP	22	5%	1/10W	R905	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R857	1-216-009-91	RES-CHIP	22	5%	1/10W	R906	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R858	1-216-009-91	RES-CHIP	22	5%	1/10W	R907	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R859	1-216-009-91	RES-CHIP	22	5%	1/10W	R908	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R860	1-216-009-91	RES-CHIP	22	5%	1/10W	R909	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R861	1-216-009-91	RES-CHIP	22	5%	1/10W	R910	1-216-049-91	RES-CHIP	1K	5%	1/10W
R862	1-216-009-91	RES-CHIP	22	5%	1/10W	R911	1-216-049-91	RES-CHIP	1K	5%	1/10W
R863	1-216-009-91	RES-CHIP	22	5%	1/10W	R912	1-216-049-91	RES-CHIP	1K	5%	1/10W
R864	1-216-009-91	RES-CHIP	22	5%	1/10W	R914	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R865	1-216-009-91	RES-CHIP	22	5%	1/10W	R916	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R866	1-216-009-91	RES-CHIP	22	5%	1/10W	R917	1-216-295-91	SHORT	0		
R867	1-216-009-91	RES-CHIP	22	5%	1/10W	R919	1-216-295-91	SHORT	0		
R868	1-216-009-91	RES-CHIP	22	5%	1/10W	R939	1-216-295-91	SHORT	0		
R869	1-216-009-91	RES-CHIP	22	5%	1/10W	R940	1-216-295-91	SHORT	0		
R870	1-216-009-91	RES-CHIP	22	5%	1/10W	R941	1-216-295-91	SHORT	0		
R871	1-216-009-91	RES-CHIP	22	5%	1/10W	R942	1-216-037-00	RES-CHIP	330	5%	1/10W
R872	1-216-009-91	RES-CHIP	22	5%	1/10W	R943	1-216-033-00	RES-CHIP	220	5%	1/10W
R873	1-216-009-91	RES-CHIP	22	5%	1/10W	R951	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R874	1-216-009-91	RES-CHIP	22	5%	1/10W	R952	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R875	1-216-009-91	RES-CHIP	22	5%	1/10W	R956	1-216-089-91	RES-CHIP	47K	5%	1/10W
R876	1-216-009-91	RES-CHIP	22	5%	1/10W	R957	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R877	1-216-009-91	RES-CHIP	22	5%	1/10W	R958	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R878	1-216-009-91	RES-CHIP	22	5%	1/10W	R959	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R879	1-216-009-91	RES-CHIP	22	5%	1/10W	R960	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R880	1-216-009-91	RES-CHIP	22	5%	1/10W	R961	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R881	1-216-009-91	RES-CHIP	22	5%	1/10W	R962	1-216-635-11	METAL CHIP	220	0.5%	1/10W
R882	1-216-009-91	RES-CHIP	22	5%	1/10W	R979	1-216-295-91	SHORT	0		
R883	1-216-009-91	RES-CHIP	22	5%	1/10W	R981	1-216-037-00	RES-CHIP	330	5%	1/10W
R884	1-216-009-91	RES-CHIP	22	5%	1/10W	R982	1-216-037-00	RES-CHIP	330	5%	1/10W
R885	1-216-009-91	RES-CHIP	22	5%	1/10W	R983	1-216-089-91	RES-CHIP	47K	5%	1/10W
R886	1-216-009-91	RES-CHIP	22	5%	1/10W	R984	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R887	1-216-009-91	RES-CHIP	22	5%	1/10W	R985	1-216-113-00	RES-CHIP	470K	5%	1/10W
R888	1-216-009-91	RES-CHIP	22	5%	1/10W	R986	1-216-061-00	RES-CHIP	3.3K	5%	1/10W
R889	1-216-009-91	RES-CHIP	22	5%	1/10W	R987	1-216-049-91	RES-CHIP	1K	5%	1/10W
R890	1-216-009-91	RES-CHIP	22	5%	1/10W	R988	1-216-033-00	RES-CHIP	220	5%	1/10W
R891	1-216-009-91	RES-CHIP	22	5%	1/10W	R989	1-216-081-00	RES-CHIP	22K	5%	1/10W
R892	1-216-009-91	RES-CHIP	22	5%	1/10W	R990	1-216-113-00	RES-CHIP	470K	5%	1/10W
R893	1-216-009-91	RES-CHIP	22	5%	1/10W	R991	1-216-295-91	SHORT	0		
R894	1-216-009-91	RES-CHIP	22	5%	1/10W	R993	1-216-089-91	RES-CHIP	47K	5%	1/10W
R895	1-216-009-91	RES-CHIP	22	5%	1/10W	R994	1-216-033-00	RES-CHIP	220	5%	1/10W
R896	1-216-009-91	RES-CHIP	22	5%	1/10W	R995	1-216-033-00	RES-CHIP	220	5%	1/10W
R897	1-216-009-91	RES-CHIP	22	5%	1/10W	R996	1-216-037-00	RES-CHIP	330	5%	1/10W
R898	1-216-009-91	RES-CHIP	22	5%	1/10W	R997	1-216-037-00	RES-CHIP	330	5%	1/10W
R901	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R998	1-216-073-00	RES-CHIP	10K	5%	1/10W
R902	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W	R2801	1-216-629-11	METAL CHIP	120	0.5%	1/10W
R903	1-216-663-11	METAL CHIP	3.3K	0.5%	1/10W	R2802	1-216-623-11	METAL CHIP	68	0.5%	1/10W

The components identified by shading and marked ⚠ are critical for safety
Replace only with the part number specified.

REF. NO.	PART.NO	DESCRIPTION			REMARK
R2803	1-216-603-11	METAL CHIP	10	0.5%	1/10W
R2804	1-216-627-11	METAL CHIP	100	0.5%	1/10W
R2805	1-216-623-11	METAL CHIP	68	0.5%	1/10W
R2806	1-216-611-11	METAL CHIP	22	0.5%	1/10W
R2809	1-216-295-91	SHORT	0		
R2810	1-216-295-91	SHORT	0		
R2813	1-216-295-91	SHORT	0		
R2815	1-216-295-91	SHORT	0		
R2817	1-216-295-91	SHORT	0		
R2818	1-216-295-91	SHORT	0		
R2820	1-216-295-91	SHORT	0		
R2822	1-216-295-91	SHORT	0		

< RESISTOR NETWORK >

REF. NO.	PART.NO	DESCRIPTION	
RB001	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB002	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB003	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB004	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB005	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB006	1-239-412-11	NETWORK RESISTOR (CHIP)	100
RB007	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB008	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB009	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB010	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB011	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB012	1-239-414-11	NETWORK RESISTOR (CHIP)	150
RB013	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB014	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB015	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB016	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB017	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB018	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB019	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB020	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB021	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB022	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB023	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB024	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB025	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB026	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB027	1-239-409-11	NETWORK RESISTOR (CHIP)	47
RB301	1-239-621-11	NETWORK RESISTOR (CHIP)	22
RB302	1-239-621-11	NETWORK RESISTOR (CHIP)	22

< CRYSTAL >

REF. NO.	PART.NO	DESCRIPTION
X702	1-781-889-21	VIBRATOR, CRYSTAL
X801	1-781-649-21	OSCILLATOR, CRYSTAL

REF. NO.	PART.NO	DESCRIPTION			REMARK
X802	1-781-650-21	VIBRATOR, CRYSTAL			

*A-1624-086-A   F1 Board, Complete

   *4-374-846-01 COVER, CAPACITOR, CAP TYPE

< CAPACITOR >

C7626	⚠ 1-136-527-12	FILM	0.47UF	20.00% 300V

< CONNECTOR >

CN7611	⚠ *1-580-843-11	PIN, CONNECTOR (POWER)
CN7622	1-695-915-11	TAB (CONTACT)
CN7633	⚠ *1-580-843-11	PIN, CONNECTOR (POWER)
CN7655	1-695-915-11	TAB (CONTACT)

< FUSE >

F7626	⚠ 1-576-232-11	FUSE (H.B.C.) 5A/250V
	⚠ 1-533-725-11	HOLDER, FUSE (F7626)

< RESISTOR >

R7626	⚠ 1-202-719-00	SOLID	1M	20%	1/2W
R7627	⚠ 1-220-797-11	CEMENTED	0.47	5%	10W

< TRANSFORMER >

LF7627	⚠ 1-433-488-11	TRANSFORMER, LINE FILTER

< VARISTOR >

VD7626	⚠ 1-801-268-51	VARISTOR ERZV14D471

*A-1631-094-A   A Board, Complete
(KV-28FQ75A/28FQ75D/28FQ75E
KV-32FQ75A/32FQ75D/32FQ75E)

*A-1631-098-A   A Board, Complete
(KV-28FQ75B/32FQ75B)

*A-1631-102-A   A Board, Complete
(KV-28FQ75U/32FQ75U)

A Board, Common Parts

   4-382-854-11 SCREW (M3X10), P, SW (+)
   *4-931-401-01 HEAT SINK, V.OUT

< CAPACITOR >

C1100	1-104-664-11	ELECT	47UF	20.00% 25V
C1101	1-126-943-11	ELECT	2200UF	20.00% 25V
C1126	1-162-568-11	CERAMIC CHIP	0.33UF	10.00% 16V
C1127	1-137-194-81	MYLAR	0.47UF	5.00% 50V
C1128	1-163-135-00	CERAMIC CHIP	560PF	5.00% 50V

REF.NO.	PART.NO	DESCRIPTION	REMARK		REF.NO.	PART.NO	DESCRIPTION	REMARK
C1129	1-115-339-11	CERAMIC CHIP 0.1UF	10.00% 50V		C1605	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C1130	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V		C1610	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C1131	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V		C1611	1-126-933-11	ELECT 100UF	20.00% 16V
C1132	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		C1612	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C1133	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C1613	1-126-933-11	ELECT 100UF	20.00% 16V
C1134	1-126-961-11	ELECT 2.2UF	20.00% 50V		C1615	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C1135	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C1617	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C1136	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C1630	1-126-925-11	ELECT 470UF	20.00% 10V
C1137	1-126-953-11	ELECT 2200UF	20.00% 35V		C1631	1-126-925-11	ELECT 470UF	20.00% 10V
C1138	1-126-953-11	ELECT 2200UF	20.00% 35V		C1632	1-136-495-11	MYLAR 0.068UF	5.00% 50V
C1140	1-111-216-91	ELECT 150UF	20.00% 63V		C1633	1-136-495-11	MYLAR 0.068UF	5.00% 50V
C1141	1-164-505-11	CERAMIC CHIP 2.2UF	16V		C1636	1-126-916-11	ELECT 1000UF	20.00% 6.3V
C1142	1-130-777-00	MYLAR 0.1UF	5.00% 63V		C1637	1-126-916-11	ELECT 1000UF	20.00% 6.3V
C1151	1-162-568-11	CERAMIC CHIP 0.33UF	10.00% 16V		C1638	1-126-935-11	ELECT 470UF	20.00% 6.3V
C1152	1-137-194-81	MYLAR 0.47UF	5.00% 50V		C1639	1-126-935-11	ELECT 470UF	20.00% 6.3V
C1153	1-163-135-00	CERAMIC CHIP 560PF	5.00% 50V				< CONNECTOR >	
C1154	1-115-339-11	CERAMIC CHIP 0.1UF	10.00% 50V					
C1155	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V		CN1111	*1-564-520-11	PLUG, CONNECTOR 5P	
C1156	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V		CN1200	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	
C1157	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		CN1301	1-695-298-11	CONNECTOR, BOARD TO BOARD 40P	
					CN1401	1-695-298-11	CONNECTOR, BOARD TO BOARD 40P	
C1158	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		CN1600	1-900-903-64	CONNECTOR ASSY 20P	
C1159	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V					
C1160	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		CN1601	1-900-903-64	CONNECTOR ASSY 20P	
C1162	1-111-216-91	ELECT 150UF	20.00% 63V		CN1602	1-900-903-64	CONNECTOR ASSY 20P	
C1163	1-164-505-11	CERAMIC CHIP 2.2UF	16V		CN1666	1-695-915-11	TAB (CONTACT)	
					CN1700	*1-568-879-11	PIN, CONNECTOR 4P	
C1164	1-130-777-00	MYLAR 0.1UF	5.00% 63V		CN1702	*1-568-878-51	PIN, CONNECTOR 3P	
C1176	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V					
C1177	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		CN1703	1-764-334-11	PLUG, CONNECTOR 11P	
C1178	1-126-964-11	ELECT 10UF	20.00% 50V		CN1801	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	
C1179	1-126-964-11	ELECT 10UF	20.00% 50V		CN1811	1-695-915-11	TAB (CONTACT)	
					CN1901	1-695-298-11	CONNECTOR, BOARD TO BOARD 40P	
C1180	1-126-952-11	ELECT 1000UF	20.00% 35V		CN1902	*1-568-879-11	PIN, CONNECTOR 4P	
C1181	1-126-952-11	ELECT 1000UF	20.00% 35V					
C1182	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		CN1988	*1-568-879-11	PIN, CONNECTOR 4P	
C1183	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V					
C1184	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V				< COMPOSITION CIRCUIT BLOCK >	
C1185	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V		CP1300	1-251-658-11	SPLITTER RF	
C1226	1-104-661-91	ELECT 330UF	20.00% 16V					
C1227	1-164-505-11	CERAMIC CHIP 2.2UF	16V				< DIODE >	
C1300	1-126-933-11	ELECT 100UF	20.00% 16V					
C1301	1-163-059-91	CERAMIC CHIP 0.01UF	10.00% 50V		D1100	8-719-914-43	DIODE DAN202K-T-146	
					D1101	8-719-914-44	DIODE DAP202K-T-146	
C1326	1-163-059-91	CERAMIC CHIP 0.01UF	10.00% 50V		D1102	8-719-914-43	DIODE DAN202K-T-146	
C1327	1-163-059-91	ELECT 220UF	20.00% 10V		D1103	8-719-914-43	DIODE DAN202K-T-146	
C1328	1-163-117-00	CERAMIC CHIP 100PF	5.00% 50V		D1104	8-719-914-43	DIODE DAN202K-T-146	
C1350	1-163-059-91	CERAMIC CHIP 0.01UF	10.00% 50V					
C1351	1-126-934-11	ELECT 220UF	20.00% 10V		D1201	8-719-976-96	DIODE UDZ-TE-17-4.7B	
					D1202	8-719-421-57	DIODE MA73-TX	
C1601	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		D1401	8-719-056-82	DIODE UDZ-TE-17-6.2B	
C1603	1-126-933-11	ELECT 100UF	20.00% 16V		D1402	8-719-056-82	DIODE UDZ-TE-17-6.2B	

REF. NO.	PART.NO	DESCRIPTION	REMARK
D1405	8-719-914-44	DIODE DAP202K-T-146	
D1406	8-719-914-43	DIODE DAN202K-T-146	
D1407	8-719-158-15	DIODE UDZ-TE-17-5.6B	
D1408	8-719-158-15	DIODE UDZ-TE-17-5.6B	
D1601	8-719-056-83	DIODE UDZ-TE-17-6.8B	
D1602	8-719-914-43	DIODE DAN202K-T-146	
D1626	8-719-914-43	DIODE DAN202K-T-146	
D1627	8-719-914-43	DIODE DAN202K-T-146	
D1630	8-719-500-70	DIODE D5S4M	
D1631	8-719-500-70	DIODE D5S4M	

< FERRITE BEAD >

REF. NO.	PART.NO	DESCRIPTION	REMARK
FB1126	1-535-303-00	LEAD, JUMPER (5.0MM)	
FB1127	1-410-397-21	FERRITE 1.1UH	
FB1151	1-535-303-00	LEAD, JUMPER (5.0MM)	
FB1152	1-410-397-21	FERRITE 1.1UH	
FB1401	1-414-234-22	INDUCTOR CHIP 0UH	
FB1630	1-535-303-00	LEAD, JUMPER (5.0MM)	
FB1631	1-535-303-00	LEAD, JUMPER (5.0MM)	
FB1901	1-414-553-11	FERRITE 0UH	
FB1903	1-414-553-11	FERRITE 0UH	
FB1904	1-414-553-11	FERRITE 0UH	
FB1905	1-414-553-11	FERRITE 0UH	
FB1906	1-414-553-11	FERRITE 0UH	
FB1907	1-414-553-11	FERRITE 0UH	

< IC >

REF. NO.	PART.NO	DESCRIPTION	REMARK
IC1126	8-759-544-25	IC TDA7482	
IC1151	8-759-544-25	IC TDA7482	
IC1176	8-759-333-24	IC LM1876TF	
IC1400	8-752-072-94	IC CXA1875AM-T4	
IC1601	8-759-574-76	IC KA78R05-SYDTU	
IC1604	8-759-544-13	IC KA78R09-YDTU	
IC1605	8-759-574-76	IC KA78R05-SYDTU	
IC1630	8-759-640-19	IC PQ1CG2032FZ	
IC1631	8-759-640-19	IC PQ1CG2032FZ	

< COIL >

REF. NO.	PART.NO	DESCRIPTION	REMARK
L1126	1-416-857-11	INDUCTOR 65UH	
L1127	1-414-158-11	INDUCTOR 2.2UH	
L1128	1-414-158-11	INDUCTOR 2.2UH	
L1151	1-416-857-11	INDUCTOR 65UH	
L1152	1-414-158-11	INDUCTOR 2.2UH	
L1153	1-414-158-11	INDUCTOR 2.2UH	
L1300	1-414-183-41	INDUCTOR 10UH	
L1326	1-414-183-41	INDUCTOR 10UH	
L1350	1-414-183-41	INDUCTOR 10UH	
L1630	1-419-249-11	INDUCTOR 15UH	

REF. NO.	PART.NO	DESCRIPTION	REMARK
L1631	1-419-249-11	INDUCTOR 15UH	
L1632	1-419-249-11	INDUCTOR 15UH	
L1633	1-419-249-11	INDUCTOR 15UH	
L1634	1-412-525-31	INDUCTOR 10UH	
L1635	1-412-525-31	INDUCTOR 10UH	

< TRANSISTOR >

REF. NO.	PART.NO	DESCRIPTION	REMARK
Q1100	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q1101	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1201	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1202	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1204	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1226	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1227	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1229	8-729-027-38	TRANSISTOR DTA144EKA-T146	
Q1300	1-801-806-11	TRANSISTOR DTC144EKA-T146	
Q1326	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1327	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1328	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1329	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q1350	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1351	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q1601	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q1602	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R	
Q1626	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	

< RESISTOR >

REF. NO.	PART.NO	DESCRIPTION	REMARK
JR1203	1-216-296-91	SHORT 0	
JR1401	1-216-295-91	SHORT 0	
JR1402	1-216-295-91	SHORT 0	
R1100	1-216-025-91	RES-CHIP 100 5% 1/10W	
R1101	1-216-057-00	RES-CHIP 2.2K 5% 1/10W	
R1102	1-216-057-00	RES-CHIP 2.2K 5% 1/10W	
R1103	1-216-089-91	RES-CHIP 47K 5% 1/10W	
R1104	1-216-296-91	SHORT 0	
R1126	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R1127	1-216-073-00	RES-CHIP 10K 5% 1/10W	
R1128	1-216-041-00	RES-CHIP 470 5% 1/10W	
R1129	1-249-422-11	CARBON 2.7K 5% 1/4W	
R1151	1-216-631-11	METAL CHIP 150 0.5% 1/10W	
R1152	1-216-075-00	RES-CHIP 12K 5% 1/10W	
R1153	1-216-041-00	RES-CHIP 470 5% 1/10W	
R1154	1-249-422-11	CARBON 2.7K 5% 1/4W	
R1174	1-249-422-11	CARBON 2.7K 5% 1/4W	
R1175	1-249-422-11	CARBON 2.7K 5% 1/4W	
R1176	1-216-063-91	RES-CHIP 3.9K 5% 1/10W	
R1177	1-216-063-91	RES-CHIP 3.9K 5% 1/10W	

REF. NO.	PART.NO	DESCRIPTION			REMARK
R1178	1-216-357-00	METAL OXIDE	4.7	5%	1W
R1179	1-216-357-00	METAL OXIDE	4.7	5%	1W
R1180	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1181	1-216-045-00	RES-CHIP	680	5%	1/10W
R1182	1-216-081-00	RES-CHIP	22K	5%	1/10W
R1183	1-216-045-00	RES-CHIP	680	5%	1/10W
R1184	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1185	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1201	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1202	1-216-083-00	RES-CHIP	27K	5%	1/10W
R1203	1-216-083-00	RES-CHIP	27K	5%	1/10W
R1204	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R1205	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1206	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1208	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1209	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R1210	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1226	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1227	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1228	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1229	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1230	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R1232	1-216-295-91	SHORT	0		
R1233	1-216-049-91	RES-CHIP	1K	5%	1/10W
R1300	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1301	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1326	1-216-025-91	RES-CHIP	100	5%	1/10W
R1327	1-216-025-91	RES-CHIP	100	5%	1/10W
R1328	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1329	1-216-025-91	RES-CHIP	100	5%	1/10W
R1330	1-216-041-00	RES-CHIP	470	5%	1/10W
R1331	1-216-041-00	RES-CHIP	470	5%	1/10W
R1332	1-216-041-00	RES-CHIP	470	5%	1/10W
R1333	1-216-075-00	RES-CHIP	12K	5%	1/10W
R1334	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R1335	1-216-025-91	RES-CHIP	100	5%	1/10W
R1336	1-216-041-00	RES-CHIP	470	5%	1/10W
R1337	1-216-041-00	RES-CHIP	470	5%	1/10W
R1338	1-216-001-00	RES-CHIP	10	5%	1/10W
R1339	1-216-041-00	RES-CHIP	470	5%	1/10W
R1340	1-216-043-91	RES-CHIP	560	5%	1/10W
R1342	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1350	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1351	1-216-025-91	RES-CHIP	100	5%	1/10W
R1352	1-216-025-91	RES-CHIP	100	5%	1/10W
R1353	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1354	1-216-025-91	RES-CHIP	100	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R1355	1-216-041-00	RES-CHIP	470	5%	1/10W
R1356	1-216-041-00	RES-CHIP	470	5%	1/10W
R1357	1-216-041-00	RES-CHIP	470	5%	1/10W
R1405	1-216-025-91	RES-CHIP	100	5%	1/10W
R1406	1-216-025-91	RES-CHIP	100	5%	1/10W
R1407	1-216-025-91	RES-CHIP	100	5%	1/10W
R1408	1-216-025-91	RES-CHIP	100	5%	1/10W
R1409	1-216-025-91	RES-CHIP	100	5%	1/10W
R1410	1-216-025-91	RES-CHIP	100	5%	1/10W
R1411	1-216-295-91	SHORT	0		
R1412	1-216-295-91	SHORT	0		
R1413	1-216-025-91	RES-CHIP	100	5%	1/10W
R1420	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1425	1-216-025-91	RES-CHIP	100	5%	1/10W
R1601	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R1602	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R1609	1-216-089-91	RES-CHIP	47K	5%	1/10W
R1610	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R1611	1-216-049-91	RES-CHIP	1K	5%	1/10W
R1612	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1613	1-216-073-00	RES-CHIP	10K	5%	1/10W
R1617	1-216-295-91	SHORT	0		
R1618	1-216-295-91	SHORT	0		
R1630	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R1631	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R1632	1-216-651-11	METAL CHIP	1K	0.5%	1/10W
R1633	1-216-652-11	METAL CHIP	1.1K	0.5%	1/10W
R1634	1-216-650-11	METAL CHIP	910	0.5%	1/10W
R1635	1-216-656-11	METAL CHIP	1.6K	0.5%	1/10W

**A Board Variant Parts KV-28FQ75A/28FQ75D/28FQ75E
KV-32FQ75A/32FQ75D/32FQ75E**

< TUNER >

TU1326	1-693-338-21	TUNER/VIF (AEP)
TU1350	1-693-338-21	TUNER/VIF (AEP)

A Board Variant Parts KV-28FQ75B/32FQ75B

< CAPACITOR >

C1186	1-115-339-11	CERAMIC CHIP 0.01UF	10.00%	50V
C1187	1-115-339-11	CERAMIC CHIP 0.01UF	10.00%	50V

< TUNER >

TU1326	1-693-340-21	TUNER/VIF (FR)
TU1350	1-693-340-21	TUNER/VIF (FR)

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.	PART.NO	DESCRIPTION	REMARK
				C9511	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
				C9512	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
				C9513	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
				C9514	1-163-235-11	CERAMIC CHIP 22PF	5.00% 50V
				C9515	1-163-235-11	CERAMIC CHIP 22PF	5.00% 50V

A Board Variant Parts KV-28FQ75U/32FQ75U

				C9516	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
				C9517	1-163-009-11	CERAMIC CHIP 0.001UF	10.00% 50V
				C9518	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
				C9519	1-126-964-11	ELECT 10UF	20.00% 50V
				C9520	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V

< TUNER >

| TU1326 | 1-693-339-21 | TUNER/VIF (UK) |
| TU1350 | 1-693-339-21 | TUNER/VIF (UK) |

< CONNECTOR >

| CN9101 | 1-695-301-11 | CONNECTOR, BOARD TO BOARD 40P |

*A-1634-054-A   M1 Board, Complete

< DIODE >

D9100	8-719-988-61	DIODE 1SS355TE-17
D9101	8-719-988-61	DIODE 1SS355TE-17
D9102	8-719-988-61	DIODE 1SS355TE-17
D9103	8-719-988-61	DIODE 1SS355TE-17
D9104	8-719-056-83	DIODE UDZ-TE-17-6.8B

< CAPACITOR >

C9100	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C9101	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C9102	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C9104	1-104-664-11	ELECT 47UF	20.00% 25V
C9105	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V

| D9105 | 8-719-914-43 | DIODE DAN202K-T-146 |
| D9107 | 8-719-025-31 | DIODE 02CZ5.6-TE85L |

C9110	1-165-321-11	CERAMIC CHIP 0.68UF	10.00% 16V
C9111	1-164-157-11	CERAMIC CHIP 0.068UF	10.00% 25V
C9112	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9113	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9114	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V

< FILTER >

FL9101	1-236-071-11	ENCAPSULATED COMPONENT
FL9500	1-236-071-11	ENCAPSULATED COMPONENT
FL9501	1-236-071-11	ENCAPSULATED COMPONENT

C9115	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C9117	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9118	1-104-664-11	ELECT 47UF	20.00% 25V
C9119	1-163-259-91	CERAMIC CHIP 220PF	5.00% 50V
C9121	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V

< IC >

IC9100	8-759-988-13	IC LM393PS-E20
IC9104	8-759-259-18	IC MB3793-42PNF-ER
IC9105	8-759-544-30	IC SAB-C161R1-LM
IC9107	8-759-395-27	IC TC55257DFTL-70V-EL
IC9108	8-759-564-06	IC M24C32-MN6T

C9122	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C9123	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9124	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9125	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9126	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V

IC9109	8-759-597-95	IC M27C800-100K1-AE513
IC9110	8-759-559-96	IC HEF4094BT
IC9400	8-759-680-29	IC M29F040B-70N1T1
IC9500	8-759-188-33	IC 7400SJX
IC9501	8-759-666-17	IC MSM5116400D-60SJR1

C9127	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V
C9128	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V
C9129	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V
C9130	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V
C9131	1-163-105-00	CERAMIC CHIP 33PF	5.00% 50V

| IC9502 | 8-759-665-84 | IC SDA5275-3PC02-22 |

C9132	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9400	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C9500	1-104-664-11	ELECT 47UF	20.00% 25V
C9502	1-104-664-11	ELECT 47UF	20.00% 25V
C9503	1-126-964-11	ELECT 10UF	20.00% 50V

< COIL >

| L9400 | 1-412-029-11 | INDUCTOR CHIP 10UH |
| L9401 | 1-412-029-11 | INDUCTOR CHIP 10UH |

C9504	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C9505	1-104-665-11	ELECT 100UF	20.00% 25V
C9506	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C9507	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C9508	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V

| C9509 | 1-163-251-11 | CERAMIC CHIP 100PF | 5.00% 50V |
| C9510 | 1-115-340-11 | CERAMIC CHIP 0.22UF | 10.00% 25V |

REF.NO.	PART.NO	DESCRIPTION			REMARK	REF.NO.	PART.NO	DESCRIPTION			REMARK
						R9142	1-216-041-00	RES-CHIP	470	5%	1/10W
	< TRANSISTOR >					R9143	1-216-049-91	RES-CHIP	1K	5%	1/10W
						R9144	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
Q9100	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R9145	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q9101	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R9146	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q9102	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R									
Q9103	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R9147	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q9105	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R9148	1-216-073-00	RES-CHIP	10K	5%	1/10W
						R9149	1-216-025-91	RES-CHIP	100	5%	1/10W
Q9106	8-729-027-46	TRANSISTOR DTC114YKA-T146				R9150	1-216-025-91	RES-CHIP	100	5%	1/10W
Q9107	8-729-027-46	TRANSISTOR DTC114YKA-T146				R9151	1-216-025-91	RES-CHIP	100	5%	1/10W
Q9108	8-729-027-46	TRANSISTOR DTC114YKA-T146									
Q9109	8-729-027-46	TRANSISTOR DTC114YKA-T146				R9153	1-216-025-91	RES-CHIP	100	5%	1/10W
Q9110	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R9159	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
						R9161	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q9500	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R9162	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q9501	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R9164	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q9502	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R									
Q9503	1-801-806-11	TRANSISTOR DTC144EKA-T146				R9166	1-216-073-00	RES-CHIP	10K	5%	1/10W
Q9504	1-801-806-11	TRANSISTOR DTC144EKA-T146				R9168	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
						R9172	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
	< RESISTOR >					R9173	1-216-295-91	SHORT	0		
						R9174	1-216-025-91	RES-CHIP	100	5%	1/10W
R9100	1-216-073-00	RES-CHIP	10K	5%	1/10W						
R9101	1-216-033-00	RES-CHIP	220	5%	1/10W	R9175	1-216-025-91	RES-CHIP	100	5%	1/10W
R9102	1-216-033-00	RES-CHIP	220	5%	1/10W	R9176	1-216-025-91	RES-CHIP	100	5%	1/10W
R9103	1-216-025-91	RES-CHIP	100	5%	1/10W	R9177	1-216-025-91	RES-CHIP	100	5%	1/10W
R9104	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9178	1-216-025-91	RES-CHIP	100	5%	1/10W
						R9179	1-216-097-91	RES-CHIP	100K	5%	1/10W
R9105	1-216-073-00	RES-CHIP	10K	5%	1/10W						
R9106	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9184	1-216-025-91	RES-CHIP	100	5%	1/10W
R9107	1-216-025-91	RES-CHIP	100	5%	1/10W	R9185	1-216-025-91	RES-CHIP	100	5%	1/10W
R9108	1-216-025-91	RES-CHIP	100	5%	1/10W	R9186	1-216-025-91	RES-CHIP	100	5%	1/10W
R9109	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9187	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
						R9188	1-216-073-00	RES-CHIP	10K	5%	1/10W
R9110	1-216-081-00	RES-CHIP	22K	5%	1/10W						
R9111	1-216-025-91	RES-CHIP	100	5%	1/10W	R9189	1-216-025-91	RES-CHIP	100	5%	1/10W
R9112	1-216-025-91	RES-CHIP	100	5%	1/10W	R9191	1-216-025-91	RES-CHIP	100	5%	1/10W
R9113	1-216-033-00	RES-CHIP	220	5%	1/10W	R9192	1-216-025-91	RES-CHIP	100	5%	1/10W
R9114	1-216-083-00	RES-CHIP	27K	5%	1/10W	R9193	1-216-097-91	RES-CHIP	100K	5%	1/10W
						R9194	1-216-097-91	RES-CHIP	100K	5%	1/10W
R9115	1-216-081-00	RES-CHIP	22K	5%	1/10W						
R9116	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9195	1-216-097-91	RES-CHIP	100K	5%	1/10W
R9117	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9196	1-216-073-00	RES-CHIP	10K	5%	1/10W
R9119	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9197	1-216-073-00	RES-CHIP	10K	5%	1/10W
R9120	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9500	1-216-295-91	SHORT	0		
						R9501	1-216-295-91	SHORT	0		
R9121	1-216-017-91	RES-CHIP	47	5%	1/10W						
R9122	1-216-049-91	RES-CHIP	1K	5%	1/10W	R9502	1-216-295-91	SHORT	0		
R9123	1-216-073-00	RES-CHIP	10K	5%	1/10W	R9504	1-216-041-00	RES-CHIP	470	5%	1/10W
R9127	1-216-049-91	RES-CHIP	1K	5%	1/10W	R9505	1-216-051-00	RES-CHIP	1.2K	5%	1/10W
R9128	1-216-097-91	RES-CHIP	100K	5%	1/10W	R9506	1-216-073-00	RES-CHIP	10K	5%	1/10W
						R9507	1-216-097-91	RES-CHIP	100K	5%	1/10W
R9135	1-216-295-91	SHORT	0								
R9138	1-216-049-91	RES-CHIP	1K	5%	1/10W	R9508	1-216-017-91	RES-CHIP	47	5%	1/10W
R9140	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R9509	1-216-049-91	RES-CHIP	1K	5%	1/10W
R9141	1-216-049-91	RES-CHIP	1K	5%	1/10W						

REF.NO.	PART.NO	DESCRIPTION			REMARK		REF.NO.	PART.NO	DESCRIPTION			REMARK
R9510	1-216-017-91	RES-CHIP	47	5%	1/10W		C5331	1-163-089-00	CERAMIC CHIP	6PF		0.50PF 50V
R9511	1-216-049-91	RES-CHIP	1K	5%	1/10W		C5332	1-163-227-11	CERAMIC CHIP	10PF		0.50PF 50V
R9512	1-216-017-91	RES-CHIP	47	5%	1/10W		C5333	1-163-035-00	CERAMIC CHIP	0.047UF		50V
R9513	1-216-017-91	RES-CHIP	47	5%	1/10W		C5334	1-163-113-00	CERAMIC CHIP	68PF		5.00% 50V
R9514	1-216-017-91	RES-CHIP	47	5%	1/10W		C5350	1-107-907-11	ELECT	22UF		20.00% 50V
R9515	1-216-295-91	SHORT	0				C5351	1-163-087-00	CERAMIC CHIP	4PF		0.25PF 50V
R9516	1-216-295-91	SHORT	0				C5352	1-163-017-00	CERAMIC CHIP	0.0047UF		10.00% 50V
R9517	1-216-295-91	SHORT	0				C5353	1-163-075-00	CERAMIC CHIP	0.047UF		50V
R9518	1-216-049-91	RES-CHIP	1K	5%	1/10W		C5354	1-128-528-11	ELECT	470UF		20.00% 16V
R9519	1-216-039-00	RES-CHIP	390	5%	1/10W		C5355	1-107-967-11	ELECT	1UF		20.00% 400V
R9520	1-216-039-00	RES-CHIP	390	5%	1/10W		C5356	1-136-207-11	MYLAR	0.047UF		10.00% 400V
R9521	1-216-039-00	RES-CHIP	390	5%	1/10W		C5357	1-163-231-11	CERAMIC CHIP	15PF		5.00% 50V
R9522	1-216-295-91	SHORT	0				C5358	1-163-087-00	CERAMIC CHIP	4PF		0.25PF 50V
R9523	1-216-295-91	SHORT	0				C5359	1-163-035-00	CERAMIC CHIP	0.047UF		50V
R9524	1-216-295-91	SHORT	0				C5360	1-163-113-00	CERAMIC CHIP	68PF		5.00% 50V
R9525	1-216-057-00	RES-CHIP	2.2K	5%	1/10W		C5375	1-107-902-11	ELECT	1UF		20.00% 50V
R9526	1-216-057-00	RES-CHIP	2.2K	5%	1/10W		C5376	1-102-106-00	CERAMIC	100PF		10.00% 50V
R9527	1-216-057-00	RES-CHIP	2.2K	5%	1/10W		C5377	1-104-331-11	CERAMIC	0.0022UF		10.00% 1KV
R9528	1-216-025-91	RES-CHIP	100	5%	1/10W		C5378	1-162-116-00	CERAMIC	680PF		10.00% 2KV
R9529	1-216-025-91	RES-CHIP	100	5%	1/10W		C5379	1-162-114-00	CERAMIC	0.0047UF		2KV
R9530	1-216-025-91	RES-CHIP	100	5%	1/10W		C5380	1-107-652-11	ELECT	10UF		20.00% 250V
R9531	1-216-295-91	SHORT	0				C5381	1-117-214-11	CERAMIC	0.001UF		10.00% 2KV
							C5382	1-162-114-00	CERAMIC	0.0047UF		2KV

< CRYSTAL >

| X9101 | 1-781-107-21 | VIBRATOR, SERAMIC |
| X9500 | 1-760-551-21 | VIBRATOR, CERAMIC |

*A-1638-139-A   C Board, Complete

| 4-382-854-11 | SCREW (M3X10), P, SW (+) |

< CAPACITOR >

C5301	1-163-075-00	CERAMIC CHIP 0.047UF		50V
C5302	1-128-528-11	ELECT	470UF	20.00% 16V
C5303	1-163-087-00	CERAMIC CHIP 4PF		0.25PF 50V
C5304	1-107-967-11	ELECT	1UF	20.00% 400V
C5305	1-136-207-11	MYLAR	0.047UF	10.00% 400V
C5306	1-163-017-00	CERAMIC CHIP 0.0047UF		10.00% 50V
C5307	1-163-233-11	CERAMIC CHIP 18PF		5.00% 50V
C5308	1-163-089-00	CERAMIC CHIP 6PF		0.50PF 50V
C5309	1-163-035-00	CERAMIC CHIP 0.047UF		50V
C5310	1-163-113-00	CERAMIC CHIP 68PF		5.00% 50V
C5325	1-163-087-00	CERAMIC CHIP 4PF		0.25PF 50V
C5326	1-163-017-00	CERAMIC CHIP 0.0047UF		10.00% 50V
C5328	1-128-528-11	ELECT	470UF	20.00% 16V
C5329	1-107-967-11	ELECT	1UF	20.00% 400V
C5330	1-136-207-11	MYLAR	0.047UF	10.00% 400V

< CONNECTOR >

CN5400	1-564-511-11	PLUG, CONNECTOR 8P
CN5511	1-695-915-11	TAB (CONTACT)
CN5600	1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P

< DIODE >

D5300	8-719-911-19	DIODE 1SS119-25TD
D5302	8-719-901-83	DIODE 1SS83TD
D5325	8-719-911-19	DIODE 1SS119-25TD
D5327	8-719-901-83	DIODE 1SS83TD
D5350	8-719-911-19	DIODE 1SS119-25TD
D5351	8-719-991-33	DIODE 1SS133T-77
D5353	8-719-901-83	DIODE 1SS83TD
D5375	8-719-991-33	DIODE 1SS133T-77
D5376	8-719-991-33	DIODE 1SS133T-77
D5377	8-719-908-03	DIODE GP08DPKG23
D5378	8-719-921-88	DIODE MTZJ-T-77-13B
D5379	8-719-982-96	DIODE MTZJ-T-77-2.2A
D5380	8-719-982-96	DIODE MTZJ-T-77-2.2A
D5381	8-719-031-34	DIODE RGP02-20EG23

< IC >

| IC5300 | 8-759-360-83 | IC TDA6111Q/N4 |

C   D

REF. NO.	PART.NO	DESCRIPTION			REMARK
IC5325	8-759-360-83	IC TDA6111Q/N4			
IC5350	8-759-360-83	IC TDA6111Q/N4			
		< SOCKET >			
J5375 ⚠	1-540-071-22	SOCKET, CRT			
		< COIL >			
L5300	1-408-591-11	INDUCTOR	1UH		
L5325	1-408-591-11	INDUCTOR	1UH		
L5350	1-408-591-11	INDUCTOR	1UH		
L5375	1-410-671-31	INDUCTOR	47UH		
L5376	1-532-637-00	LINK, IC 1A/150V			
L5377	1-414-183-41	INDUCTOR	10UH		
		< TRANSISTOR >			
Q5300	8-729-255-12	TRANSISTOR 2SC2551O-TPE2			
Q5301	8-729-216-22	TRANSISTOR 2SB709A-QRS-TX			
Q5325	8-729-255-12	TRANSISTOR 2SC2551O-TPE2			
Q5326	8-729-216-22	TRANSISTOR 2SB709A-QRS-TX			
Q5350	8-729-029-56	TRANSISTOR DTA144ESA-TP			
Q5351	8-729-255-12	TRANSISTOR 2SC2551O-TPE2			
Q5352	8-729-216-22	TRANSISTOR 2SB709A-QRS-TX			
Q5375	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q5376	8-729-026-39	TRANSISTOR 2SA933AS-RT			
		< RESISTOR >			
R5300	1-249-417-11	CARBON	1K	5%	1/4W
R5301	1-247-807-31	CARBON	100	5%	1/4W
R5302	1-535-303-00	LEAD, JUMPER (5.0MM)			
R5303	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R5304	1-202-557-00	SOLID	220	20%	1/2W
R5305	1-215-929-11	METAL OXIDE	100K	5%	3W
R5306	1-249-424-11	CARBON	3.9K	5%	1/4W
R5307	1-247-863-91	CARBON	22K	5%	1/4W
R5308	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R5309	1-216-658-11	METAL CHIP	2K	0.5%	1/10W
R5310	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5325	1-249-417-11	CARBON	1K	5%	1/4W
R5326	1-247-807-31	CARBON	100	5%	1/4W
R5327	1-535-303-00	LEAD, JUMPER (5.0MM)			
R5328	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R5329	1-202-557-00	SOLID	220	20%	1/2W
R5330	1-215-929-11	METAL OXIDE	100K	5%	3W
R5331	1-249-424-11	CARBON	3.9K	5%	1/4W
R5332	1-247-863-91	CARBON	22K	5%	1/4W
R5333	1-216-057-00	RES-CHIP	2.2K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R5334	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5335	1-216-658-11	METAL CHIP	2K	0.5%	1/10W
R5350	1-249-417-11	CARBON	1K	5%	1/4W
R5351	1-247-807-31	CARBON	100	5%	1/4W
R5352	1-249-416-11	CARBON	820	5%	1/4W
R5353	1-249-421-11	CARBON	2.2K	5%	1/4W
R5354	1-249-418-11	CARBON	1.2K	5%	1/4W
R5355	1-535-303-00	LEAD, JUMPER (5.0MM)			
R5356	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R5357	1-202-557-00	SOLID	220	20%	1/2W
R5358	1-215-929-11	METAL OXIDE	100K	5%	3W
R5359	1-247-863-91	CARBON	22K	5%	1/4W
R5360	1-249-424-11	CARBON	3.9K	5%	1/4W
R5361	1-249-431-11	CARBON	15K	5%	1/4W
R5362	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R5363	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R5364	1-216-658-11	METAL CHIP	2K	0.5%	1/10W
R5375	1-249-435-11	CARBON	33K	5%	1/4W
R5376	1-249-429-11	CARBON	10K	5%	1/4W
R5377	1-249-430-11	CARBON	12K	5%	1/4W
R5378	1-249-429-11	CARBON	10K	5%	1/4W
R5379	1-249-438-11	CARBON	56K	5%	1/4W
R5380	1-247-863-91	CARBON	22K	5%	1/4W
R5381	1-216-055-00	RES-CHIP	1.8K	5%	1/10W
R5382	1-202-549-00	SOLID	100	20%	1/2W
R5383	1-535-143-51	LEAD, JUMPER (20.0MM)			
R5384	1-535-143-51	LEAD, JUMPER (20.0MM)			
R5385	1-202-549-00	SOLID	100	20%	1/2W
R5386	1-202-884-11	SOLID	820K	20%	1/2W
R5387	1-202-884-11	SOLID	820K	20%	1/2W
R5388	1-215-911-11	METAL OXIDE	100	5%	3W
R5389	1-249-417-11	CARBON	1K	5%	1/4W
		< VARIABLE RESISTOR >			
RV5375	1-241-656-21	RES, ADJ, METAL FILM 110M			
RV5376	1-230-641-11	RES, ADJ, METAL GLAZE 2.2M			

*A-1640-328-A   D Board, Complete (KV-28FQ75)
*A-1640-323-A   D Board, Complete (KV-32FQ75)

D Board, Common Parts

	PART.NO	DESCRIPTION			
	1-695-915-11	TAB (CONTACT)			
	4-201-023-01	SPACER, INSULATING			
	4-202-373-01	SPRING, IC			
	4-382-854-11	SCREW (M3X10), P, SW (+)			
	*4-931-401-01	HEAT SINK, V.OUT			

D

REF.NO.	PART.NO	DESCRIPTION		REMARK		

< CAPACITOR >

REF.NO.		PART.NO	DESCRIPTION		REMARK		
C6600	⚠	1-113-927-11	CERAMIC	10000PF	20.00%	250V	
C6603		1-126-933-11	ELECT	100UF	20.00%	16V	
C6604		1-126-767-11	ELECT	1000UF	20.00%	16V	
C6605	⚠	1-119-888-51	CERAMIC	2200PF	20.00%	250V	
C6606	⚠	1-119-888-51	CERAMIC	2200PF	20.00%	250V	
C6607	⚠	1-136-415-51	FILM	0.33UF	20.00%	300V	
C6608	⚠	1-161-964-91	CERAMIC	0.0047UF		250V	
C6609	⚠	1-161-964-91	CERAMIC	0.0047UF		250V	
C6610	⚠	1-161-964-91	CERAMIC	0.0047UF		250V	
C6611	⚠	1-161-964-91	CERAMIC	0.0047UF		250V	
C6612		1-113-927-11	CERAMIC	10000PF	20.00%	250V	
C6616		1-164-625-11	CERAMIC	680PF	10.00%	500V	
C6617		1-164-625-11	CERAMIC	680PF	10.00%	500V	
C6618		1-136-175-00	MYLAR	0.68UF	5.00%	50V	
C6619		1-137-194-91	MYLAR	0.47UF	5.00%	50V	
C6620		1-136-618-11	FILM	0.047UF	5.00%	1.25KV	
C6621		1-136-175-00	MYLAR	0.68UF	5.00%	50V	
C6622		1-164-625-11	CERAMIC	680PF	10.00%	500V	
C6623		1-137-194-91	MYLAR	0.47UF	5.00%	50V	
C6624		1-126-968-11	ELECT	100UF	20.00%	50V	
C6626		1-164-625-11	CERAMIC	680PF	10.00%	500V	
C6627		1-164-625-11	CERAMIC	680PF	10.00%	500V	
C6628		1-126-936-11	ELECT	3300UF	20.00%	16V	
C6629		1-128-548-11	ELECT	4700UF	20.00%	25V	
C6630		1-110-626-11	ELECT	330UF	20.00%	160V	
C6631		1-126-955-11	ELECT	4700UF	20.00%	35V	
C6632		1-126-955-11	ELECT	4700UF	20.00%	35V	
C6634		1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6635		1-104-664-11	ELECT	47UF	20.00%	25V	
C6636		1-102-129-00	CERAMIC	0.01UF	10.00%	50V	
C6637		1-102-129-00	CERAMIC	0.01UF	10.00%	50V	
C6638		1-137-368-11	MYLAR	0.0047UF	5.00%	50V	
C6639		1-102-228-00	CERAMIC	470PF	10.00%	500V	
C6641		1-126-967-11	ELECT	47UF	20.00%	50V	
C6642		1-128-551-11	ELECT	22UF	20.00%	25V	
C6647		1-104-664-11	ELECT	47UF	20.00%	25V	
C6649		1-126-965-11	ELECT	22UF	20.00%	50V	
C6651		1-161-964-91	CERAMIC	0.0047UF		250V	
C6652		1-107-679-91	ELECT	10UF	20.00%	450V	
C6653		1-126-968-11	ELECT	100UF	20.00%	50V	
C6654		1-162-117-00	CERAMIC	100PF	10.00%	500V	
C6655		1-107-974-11	CERAMIC	47PF	5.00%	2KV	
C6656		1-126-967-11	ELECT	47UF	20.00%	50V	
C6657		1-126-941-11	ELECT	470UF	20.00%	25V	
C6658		1-104-665-11	ELECT	100UF	20.00%	25V	

REF.NO.	PART.NO	DESCRIPTION		REMARK		
C6659	1-104-665-11	ELECT	100UF	20.00%	25V	
C6661	1-117-753-11	ELECT(BLOCK)	470UF	20.00%	450V	
C6662	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6664	1-136-153-00	MYLAR	0.01UF	5.00%	50V	
C6665	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6666	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6667	1-126-933-11	ELECT	100UF	20.00%	16V	
C6668	1-126-933-11	ELECT	100UF	20.00%	16V	
C6669	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6670	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6671	1-104-664-11	ELECT	47UF	20.00%	16V	
C6672	1-104-664-11	ELECT	47UF	20.00%	16V	
C6677	1-136-165-00	MYLAR	0.1UF	5.00%	50V	
C6679	1-130-495-00	MYLAR	0.1UF	5.00%	50V	
C6680	1-137-150-11	MYLAR	0.01UF	5.00%	50V	
C6681	1-126-964-11	ELECT	10UF	20.00%	50V	
C6682	1-107-679-91	ELECT	10UF	20.00%	450V	
C6700	1-102-129-00	CERAMIC	0.01UF	10.00%	50V	
C6703	1-128-527-11	ELECT	330UF	20.00%	25V	
C6704	1-126-968-11	ELECT	100UF	20.00%	50V	
C6705	1-128-527-11	ELECT	330UF	20.00%	25V	
C6706	1-137-401-11	MYLAR	0.22UF	10.00%	100V	
C6707	1-129-702-00	MYLAR	0.001UF	10.00%	400V	
C6708	1-106-220-00	MYLAR	0.1UF	10.00%	100V	
C6709	1-102-129-00	CERAMIC	0.01UF	10.00%	50V	
C6710	1-130-785-11	MYLAR	0.47UF	10.00%	100V	
C6727	1-102-228-00	CERAMIC	470PF	10.00%	500V	
C6801	1-104-664-11	ELECT	47UF	20.00%	25V	
C6802	1-126-960-11	ELECT	1UF	20.00%	50V	
C6803	1-126-960-11	ELECT	1UF	20.00%	50V	
C6804	1-102-114-00	CERAMIC	470PF	10.00%	50V	
C6805	1-102-114-00	CERAMIC	470PF	10.00%	50V	
C6808	1-102-030-00	CERAMIC	330PF	10.00%	500V	
C6809	1-102-030-00	CERAMIC	330PF	10.00%	500V	
C6810	1-107-368-11	MYLAR	0.047UF	10.00%	200V	
C6811	1-107-368-11	MYLAR	0.047UF	10.00%	200V	
C6812	1-162-131-11	CERAMIC	220PF	10.00%	2KV	
C6813	1-162-134-11	CERAMIC	470PF	10.00%	2KV	
C6816	1-130-471-00	MYLAR	0.001UF	5.00%	50V	
C6817	1-125-893-11	FILM	680PF	3.00%	1.5KV	
C6818	1-125-893-11	FILM	680PF	3.00%	1.5KV	
C6819	1-125-893-11	FILM	680PF	3.00%	1.5KV	
C6820	1-125-893-11	FILM	680PF	3.00%	1.5KV	
C6824	1-107-846-11	FILM	0.1UF	5.00%	250V	
C6827	1-107-846-11	FILM	0.1UF	5.00%	250V	
C6828	1-127-681-11	FILM MELF	10000PF	2%	100V	
C6829	1-127-680-11	FILM MELF	4700PF	2%	100V	

D

REF. NO.	PART.NO	DESCRIPTION		REMARK		
C6830	1-107-655-11	ELECT	47UF	20.00%	250V	
C6831	1-102-228-00	CERAMIC	470PF	10.00%	500V	
C6832	1-126-941-11	ELECT	470UF	20.00%	25V	
C6833	1-126-941-11	ELECT	470UF	20.00%	25V	
C6834	1-102-228-00	CERAMIC	470PF	10.00%	500V	
C6835	1-102-228-00	CERAMIC	470PF	10.00%	500V	
C6836	1-123-024-21	ELECT	33UF		160V	
C6837	1-106-375-12	MYLAR	0.022UF	10.00%	250V	
C6840	1-137-150-11	MYLAR	0.01UF	5.00%	50V	
C6841	1-104-664-11	ELECT	47UF	20.00%	16V	
C6844	1-115-513-21	FILM	0.18UF	5.00%	250V	
C6851	1-162-131-11	CERAMIC	220PF	10.00%	2KV	
C6852	1-162-129-00	CERAMIC	150PF	10.00%	2KV	
C6853	1-129-898-00	FILM	0.0022UF	5.00%	630V	
C6855	1-136-205-11	MYLAR	0.022UF	10.00%	400V	
C6856	1-102-030-00	CERAMIC	330PF	10.00%	500V	
C6857	1-130-785-11	MYLAR	0.47UF	10.00%	100V	
C6861	1-130-471-00	MYLAR	0.001UF	5.00%	50V	
C6862	1-130-471-00	MYLAR	0.001UF	5.00%	50V	

< CONNECTOR >

CN6100	1-785-802-11	PIN, CONNECTOR (WITH PWB) 20P	
CN6101	1-785-802-11	PIN, CONNECTOR (WITH PWB) 20P	
CN6102	1-785-802-11	PIN, CONNECTOR (WITH PWB) 20P	
CN6500	1-508-766-00	PIN, CONNECTOR (5MM PITCH) 4P	
CN6600	1-695-299-11	CONNECTOR, BOARD TO BOARD 50P	
CN6611	*1-785-270-12	PIN, DY CONNECTOR (PC BOARD)	
CN6620 ⚠	1-508-765-00	PIN, CONNECTOR (5MM PITCH) 3P	
CN6666 ⚠	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
CN6700 ⚠	*1-691-291-11	PIN, CONNECTOR (PC BOARD) 5P	

< DIODE >

D6600	8-719-911-19	DIODE 1SS119-25TD	
D6601	8-719-063-73	DIODE D1NL20U-TR	
D6602	8-719-109-89	DIODE MTZJ-T-77-5.6B	
D6603	8-719-911-19	DIODE 1SS119-25TD	
D6604	8-719-510-53	DIODE D4SB60L-F	
D6605	8-719-991-33	DIODE 1SS133T-77	
D6610	8-719-063-73	DIODE D1NL20U-TR	
D6613	8-719-911-19	DIODE 1SS119-25TD	
D6615	8-719-911-19	DIODE 1SS119-25TD	
D6616	8-719-510-12	DIODE D10SC4M-F	
D6617	8-719-500-71	DIODE D8LC40F	
D6618	8-719-079-50	DIODE RBA-402L	
D6619	8-719-510-12	DIODE D10SC4M-F	
D6621	8-719-991-33	DIODE 1SS133T-77	
D6622	8-719-991-33	DIODE 1SS133T-77	

REF. NO.	PART.NO	DESCRIPTION	REMARK
D6623	8-719-911-19	DIODE 1SS119-25TD	
D6624	8-719-991-33	DIODE 1SS133T-77	
D6625	8-719-991-33	DIODE 1SS133T-77	
D6626	8-719-991-33	DIODE 1SS133T-77	
D6627	8-719-982-27	DIODE MTZJ-T-77-33C	
D6628	8-719-109-97	DIODE MTZJ-T-77-6.8	
D6629	8-719-991-33	DIODE 1SS133T-77	
D6630	8-719-991-33	DIODE 1SS133T-77	
D6631	8-719-991-33	DIODE 1SS133T-77	
D6651	8-719-068-00	DIODE ERC04-06SE	
D6652	8-719-923-78	DIODE MTZJ-T-77-12	
D6653	8-719-063-73	DIODE D1NL20U-TR	
D6654	8-719-059-23	DIODE P6KE200AG23	
D6655	8-719-979-64	DIODE UF4005PKG23	
D6656	8-719-063-73	DIODE D1NL20U-TR	
D6658	8-719-068-00	DIODE ERC04-06SE	
D6659	8-719-063-73	DIODE D1NL20U-TR	
D6676	8-719-991-33	DIODE 1SS133T-77	
D6677	8-719-921-40	DIODE MTZJ-T-77-4.7B	
D6678	8-719-921-40	DIODE MTZJ-T-77-4.7B	
D6679	8-719-991-33	DIODE 1SS133T-77	
D6681	8-719-991-33	DIODE 1SS133T-77	
D6700	8-719-200-02	DIODE ERA15-02TP1	
D6701	8-719-110-41	DIODE MTZJ-T-77-15B	
D6803	8-719-200-02	DIODE ERA15-02TP1	
D6804	1-535-143-11	LEAD, JUMPER (10.0MM)	
D6805	8-719-302-43	DIODE RGP10GPKG23	
D6806	8-719-979-85	DIODE RGP15GPKG23	
D6807	8-719-510-73	DIODE S3L20UF4	
D6808	8-719-510-73	DIODE S3L20UF4	
D6809	8-719-991-33	DIODE 1SS133T-77	
D6810	1-247-895-91	CARBON 470K 5% 1/4W	
D6811	8-719-110-41	DIODE MTZJ-T-77-15B	
D6851	8-719-970-87	DIODE ERA38-06TP1	
D6852	8-719-970-87	DIODE ERA38-06TP1	

< FERRITE BEAD >

FB6602	1-410-396-41	FERRITE 0.45UH	
FB6603	1-410-396-41	FERRITE 0.45UH	

< IC >

IC6600	1-810-051-11	POWER MODULE DM-48	
IC6604	8-729-045-40	TRANSISTOR MX0842A-F	
IC6651	8-759-468-89	IC TOP209P	
IC6652	8-759-394-35	IC BA12T	
IC6653	8-759-544-13	IC KA78R09-YDTU	
IC6654	8-759-574-76	IC KA78R05-SYDTU	

D

REF. NO.	PART.NO	DESCRIPTION			REMARK
IC6667	8-759-908-15	IC TL431CZ			
IC6676	8-759-908-15	IC TL431CZ			
IC6700	8-759-192-71	IC STV9379			
IC6801	8-759-103-93	IC LM393P			
		< COIL >			
L6604	1-412-525-31	INDUCTOR	10UH		
L6605	1-412-523-41	INDUCTOR	6.8UH		
L6606	1-412-525-31	INDUCTOR	10UH		
L6651	1-414-183-41	INDUCTOR	10UH		
L6700	1-412-524-11	INDUCTOR	8.2UH		
L6801	1-412-519-11	INDUCTOR	3.3UH		
L6802	1-412-519-11	INDUCTOR	3.3UH		
L6803	1-412-533-21	INDUCTOR	47UH		
L6805	1-408-947-00	INDUCTOR	2.2MH		
L6806	1-535-303-00	LEAD, JUMPER	(5.0MM)		
L6807	1-410-397-21	FERRITE	1.1UH		
L6851	1-535-303-00	LEAD, JUMPER	(5.0MM)		
		< FILTER >			
LF6603	1-406-659-11	INDUCTOR	10UH		
LF6604	1-406-659-11	INDUCTOR	10UH		
LF6801	1-406-985-11	INDUCTOR	2.2MH		
LF6851	1-406-674-11	INDUCTOR	3.3MH		
		< IC LINK >			
PS6601 ⚠	1-801-550-21	PROTECTOR, MODULE 2.5A MP250			
PS6602 ⚠	1-801-550-21	PROTECTOR, MODULE 2.5A MP250			
PS6603 ⚠	1-801-549-21	PROTECTOR, MODULE 4.0A MP250			
PS6604 ⚠	1-801-550-21	PROTECTOR, MODULE 2.5A MP250			
		< TRANSISTOR >			
Q6600	8-729-046-47	TRANSISTOR KSC2500-BTA			
Q6602	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q6603	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q6605	8-729-046-47	TRANSISTOR KSC2500-BTA			
Q6606	8-729-029-56	TRANSISTOR DTA144ESA-TP			
Q6607	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q6608	8-729-029-66	TRANSISTOR DTC114ESA-TP			
Q6611	8-729-029-66	TRANSISTOR DTC114ESA-TP			
Q6651	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q6652	8-729-029-86	TRANSISTOR DTC124ESA-TP			
Q6667	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q6676	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q6677	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q6678	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q6679	8-729-026-39	TRANSISTOR 2SA933AS-RT			

REF. NO.	PART.NO	DESCRIPTION			REMARK
Q6680	8-729-029-66	TRANSISTOR DTC114ESA-TP			
Q6681	8-729-029-66	TRANSISTOR DTC114ESA-TP			
Q6700	8-729-039-68	TRANSISTOR IRF620			
Q6801	8-729-119-80	TRANSISTOR 2SC2688-LK			
Q6802	8-729-119-80	TRANSISTOR 2SC2688-LK			
Q6803	8-729-046-18	TRANSISTOR 2SC5480-01			
Q6804	8-729-046-18	TRANSISTOR 2SC5480-01			
Q6805	8-729-038-83	TRANSISTOR 2SK2251-01-F19			
Q6806	8-729-047-59	TRANSISTOR STP5NB40FP			
Q6807	8-729-030-02	TRANSISTOR DTC144ESA-TP			
Q6851	8-729-043-95	TRANSISTOR 2SC3840K			
		< RESISTOR >			
R6601 ⚠	1-202-968-11	CEMENTED	1.2	5%	10W
R6602	1-247-863-91	CARBON	22K	5%	1/4W
R6603	1-249-430-11	CARBON	12K	5%	1/4W
R6604	1-249-421-11	CARBON	2.2K	5%	1/4W
R6605	1-249-417-11	CARBON	1K	5%	1/4W
R6606 ⚠	1-202-968-11	CEMENTED	1.2	5%	10W
R6608 ⚠	1-220-797-11	CEMENTED	0.47	5%	10W
R6611 ⚠	1-260-125-11	CARBON	150K	5%	1/2W
R6612	1-260-125-11	CARBON	150K	5%	1/2W
R6613	1-216-369-00	METAL OXIDE	1	5%	2W
R6614	1-260-125-11	CARBON	150K	5%	1/2W
R6615	1-260-125-11	CARBON	150K	5%	1/2W
R6616	1-216-369-00	METAL OXIDE	1	5%	2W
R6619	1-249-425-11	CARBON	4.7K	5%	1/4W
R6620	1-249-443-11	CARBON	0.47	5%	1/4W
R6624	1-249-425-11	CARBON	4.7K	5%	1/4W
R6625	1-249-429-11	CARBON	10K	5%	1/4W
R6626	1-247-807-31	CARBON	100	5%	1/4W
R6627	1-249-429-11	CARBON	10K	5%	1/4W
R6628	1-260-129-11	CARBON	330K	5%	1/2W
R6629	1-260-129-11	CARBON	330K	5%	1/2W
R6630	1-249-417-11	CARBON	1K	5%	1/4W
R6631	1-249-425-11	CARBON	4.7K	5%	1/4W
R6632	1-207-905-00	WIREWOUND	0.27	10%	2W
R6633	1-249-429-11	CARBON	10K	5%	1/4W
R6635	1-535-143-11	LEAD, JUMPER (10.0MM)			
R6637	1-249-421-11	CARBON	2.2K	5%	1/4W
R6638	1-247-895-91	CARBON	470K	5%	1/4W
R6639	1-249-416-11	CARBON	820	5%	1/4W
R6640	1-249-417-11	CARBON	1K	5%	1/4W
R6641	1-260-127-11	CARBON	220K	5%	1/2W
R6642	1-249-389-11	CARBON	4.7	5%	1/4W
R6643	1-249-417-11	CARBON	1K	5%	1/4W
R6644	1-249-429-11	CARBON	10K	5%	1/4W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R6645	1-260-131-11	CARBON	470K	5%	1/2W
R6646	1-249-429-11	CARBON	10K	5%	1/4W
R6647	1-249-410-11	CARBON	270	5%	1/4W
R6648	1-247-863-91	CARBON	22K	5%	1/4W
R6649	1-215-926-00	METAL OXIDE	33K	5%	3W
R6651	1-247-791-91	CARBON	22	5%	1/4W
R6652	1-249-389-11	CARBON	4.7	5%	1/4W
R6653	1-249-421-11	CARBON	2.2K	5%	1/4W
R6655	1-249-429-11	CARBON	10K	5%	1/4W
R6656	1-218-265-11	METAL	8.2M	5%	1W
R6657	1-215-421-00	METAL	1K	1%	1/4W
R6666	1-202-933-61	FUSIBLE	0.1	10%	1/2W
R6667	1-215-441-00	METAL	6.8K	1%	1/4W
R6668	1-249-428-11	CARBON	8.2K	5%	1/4W
R6669	1-249-413-11	CARBON	470	5%	1/4W
R6676	1-249-417-11	CARBON	1K	5%	1/4W
R6677	1-249-417-11	CARBON	1K	5%	1/4W
R6678	1-249-417-11	CARBON	1K	5%	1/4W
R6679	1-215-479-00	METAL	270K	1%	1/4W
R6681	1-215-467-00	METAL	82K	1%	1/4W
R6682	1-215-447-00	METAL	12K	1%	1/4W
R6683	1-215-429-00	METAL	2.2K	1%	1/4W
R6684	1-247-807-31	CARBON	100	5%	1/4W
R6685	1-249-417-11	CARBON	1K	5%	1/4W
R6686	1-215-449-00	METAL	15K	1%	1/4W
R6687	1-249-431-11	CARBON	15K	5%	1/4W
R6688	1-249-417-11	CARBON	1K	5%	1/4W
R6689	1-247-843-11	CARBON	3.3K	5%	1/4W
R6690	1-249-429-11	CARBON	10K	5%	1/4W
R6691	1-215-446-00	METAL	11K	1%	1/4W
R6692	1-215-445-00	METAL	10K	1%	1/4W
R6700	1-215-441-00	METAL	6.8K	1%	1/4W
R6701	1-215-437-00	METAL	4.7K	1%	1/4W
R6702	1-215-441-00	METAL	6.8K	1%	1/4W
R6703	1-215-437-00	METAL	4.7K	1%	1/4W
R6704	1-249-383-11	CARBON	1.5	5%	1/4W
R6705	1-247-791-91	CARBON	22	5%	1/4W
R6706	1-249-389-11	CARBON	4.7	5%	1/4W
R6707	1-215-888-00	METAL OXIDE	220	5%	2W
R6708	1-214-798-21	METAL	1.8	1%	1/2W
R6709	1-214-798-21	METAL	1.8	1%	1/2W
R6710	1-247-843-11	CARBON	3.3K	5%	1/4W
R6711	1-249-418-11	CARBON	1.2K	5%	1/4W
R6801	1-215-440-00	METAL	6.2K	1%	1/4W
R6802	1-214-915-00	METAL	120K	1%	1/2W
R6803	1-249-421-11	CARBON	2.2K	5%	1/4W
R6804	1-249-408-11	CARBON	180	5%	1/4W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R6805	1-249-408-11	CARBON	180	5%	1/4W
R6806	1-249-411-11	CARBON	330	5%	1/4W
R6807	1-249-411-11	CARBON	330	5%	1/4W
R6808	1-260-340-11	CARBON	10K	5%	1/2W
R6809	1-260-340-11	CARBON	10K	5%	1/2W
R6811	1-216-461-00	METAL OXIDE	5.6K	5%	2W
R6812	1-215-895-11	METAL OXIDE	3.3K	5%	2W
R6813	1-215-920-11	METAL OXIDE	3.3K	5%	3W
R6814	1-215-880-00	METAL OXIDE	10	5%	2W
R6815	1-215-880-00	METAL OXIDE	10	5%	2W
R6816	1-216-361-00	METAL OXIDE	0.22	5%	2W
R6817	1-216-361-00	METAL OXIDE	0.22	5%	2W
R6818	1-249-405-11	CARBON	100	5%	1/4W
R6819	1-247-807-31	CARBON	100	5%	1/4W
R6820	1-535-143-51	LEAD, JUMPER (20.0MM)			
R6821	1-535-143-51	LEAD, JUMPER (20.0MM)			
R6831	1-260-124-11	CARBON	120K	5%	1/2W
R6832	1-216-434-11	METAL OXIDE	1.8K	5%	1W
R6833	1-202-972-61	FUSIBLE	1	5%	1/4W
R6834	1-535-303-00	LEAD, JUMPER (5.0MM)			
R6835	1-260-288-11	CARBON	0.47	5%	1/2W
R6836	1-249-431-11	CARBON	15K	5%	1/4W
R6837	1-215-919-11	METAL OXIDE	2.2K	5%	3W
R6838	1-214-905-11	METAL	47K	1%	1/2W
R6839	1-215-919-11	METAL OXIDE	2.2K	5%	3W
R6840	1-247-843-11	CARBON	3.3K	5%	1/4W
R6842	1-260-123-11	CARBON	100K	5%	1/2W
R6843	1-249-429-11	CARBON	10K	5%	1/4W
R6844	1-249-441-11	CARBON	100K	5%	1/4W
R6845	1-247-863-91	CARBON	22K	5%	1/4W
R6851	1-260-123-11	CARBON	100K	5%	1/2W
R6852	1-260-123-11	CARBON	100K	5%	1/2W
R6853	1-260-123-11	CARBON	100K	5%	1/2W
R6854	1-249-417-11	CARBON	1K	5%	1/4W
R6880	1-215-436-00	METAL	4.3K	1%	1/4W
R6885	1-215-493-00	METAL	1M	1%	1/4W
R6886	1-215-477-00	METAL	220K	1%	1/4W
R6887	1-215-461-00	METAL	47K	1%	1/4W
R6888	1-249-441-11	CARBON	100K	5%	1/4W
R6891	1-535-303-00	LEAD, JUMPER (5.0MM)			
R6892	1-535-303-00	LEAD, JUMPER (5.0MM)			
R6895	1-249-443-11	CARBON	0.47	5%	1/4W
R6896	1-249-443-11	CARBON	0.47	5%	1/4W
R6898	1-215-493-00	METAL	1M	1%	1/4W
R6899	1-215-493-00	METAL	1M	1%	1/4W

D **E**

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
						R6897	1-215-489-00	METAL	680K 1%	1/4W	
< RELAY >											
RY6601 ⚠	1-755-266-11	RELAY, AC POWER									
RY6602 ⚠	1-755-167-11	RELAY, AC POWER									

*A-1640-383-A   E Board, Complete (KV-28FQ75)
*A-1640-384-A   E Board, Complete (KV-32FQ75)

REF. NO.	PART.NO	DESCRIPTION			REMARK
< TRANSFORMER >					
T6600	1-431-616-11	TRANSFORMER, CONVERTER			
T6601 ⚠	1-433-516-11	TRANSFORMER, CONVERTER (PIT)			
T6651	1-431-732-21	TRANSFORMER, CONVERTER (SRT)			
T6801	1-433-489-31	TRANSFORMER, FERRITE (HDT)			
T6802	1-433-489-31	TRANSFORMER, FERRITE (HDT)			
T6804 ⚠	1-453-340-11	TRANSFORMER ASSY, FLYBACK (NX-4522//U214)			
T6852	1-433-487-11	TRANSFORMER, FERRITE (DFT)			

E Board Common Parts

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION			REMARK
< THERMISTOR >					
TH6600	1-809-827-11	THERMISTOR, POSITIVE			
TH6700	1-800-193-00	THERMISTOR			

D Board Variant Parts KV-28FQ75

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION	VALUE	TOL	VOLT
C6814	1-117-641-11	FILM	7500PF	3.00%	1.2KV
C6815	1-117-836-11	FILM	6800PF	3.00%	1.5KV
C6825	1-115-514-11	FILM	0.22UF	5.00%	250V
C6826	1-115-520-11	FILM	0.68UF	5.00%	250V

< RESISTOR >

REF. NO.	PART.NO	DESCRIPTION	VALUE	TOL	WATT
R6810	1-215-920-11	METAL OXIDE	3.3K	5%	3W
R6856	1-216-486-00	METAL OXIDE	8.2K	5%	3W
R6857	1-216-486-00	METAL OXIDE	8.2K	5%	3W
R6858	1-216-486-00	METAL OXIDE	8.2K	5%	3W
R6859	1-216-486-00	METAL OXIDE	8.2K	5%	3W
R6897	1-215-485-00	METAL	470K	1%	1/4W

D Board Variant Parts KV-32FQ75

< CAPACITOR >

REF. NO.	PART.NO	DESCRIPTION	VALUE	TOL	VOLT
C6814	1-117-640-11	FILM	6800PF	3.00%	1.2KV
C6815	1-117-835-11	FILM	6200PF	3.00%	1.5KV
C6825	1-117-662-11	FILM	0.18UF	5.00%	250V
C6826	1-115-519-11	FILM	0.56UF	5.00%	250V

< RESISTOR >

REF. NO.	PART.NO	DESCRIPTION	VALUE	TOL	WATT
R6810	1-216-484-00	METAL OXIDE	3.9K	5%	3W
R6856	1-215-922-11	METAL OXIDE	6.8K	5%	3W
R6857	1-215-922-11	METAL OXIDE	6.8K	5%	3W
R6858	1-215-922-11	METAL OXIDE	6.8K	5%	3W
R6859	1-215-922-11	METAL OXIDE	6.8K	5%	3W

E Board Common Parts < CAPACITOR > table:

REF. NO.	PART.NO	DESCRIPTION	VALUE	TOL	VOLT
C4316	1-104-664-11	ELECT	47UF	20.00%	25V
C4317	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4318	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4319	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4320	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4321	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4322	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4324	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4325	1-163-093-00	CERAMIC CHIP	10PF	5.00%	50V
C4329	1-126-963-11	ELECT	4.7UF	20.00%	50V
C4330	1-137-581-11	FILM	0.1UF	5.00%	100V
C4331	1-126-959-11	ELECT	0.47UF	20.00%	50V
C4332	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4333	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4334	1-126-967-11	ELECT	47UF	20.00%	50V
C4336	1-126-967-11	ELECT	47UF	20.00%	50V
C4338	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4340	1-126-967-11	ELECT	47UF	20.00%	50V
C4342	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
C4343	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4344	1-163-809-11	CERAMIC CHIP	0.047UF	10.00%	25V
C4345	1-126-967-11	ELECT	47UF	20.00%	50V
C4346	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4347	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4348	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4349	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4350	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4351	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V
C4352	1-126-967-11	ELECT	47UF	20.00%	50V
C4353	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V
C4354	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V
C4355	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4356	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4357	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4358	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4359	1-164-161-11	CERAMIC CHIP	0.0022UF	10.00%	50V
C4360	1-126-963-11	ELECT	4.7UF	20.00%	50V
C4362	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C4363	1-126-967-11	ELECT	47UF	20.00%	50V
C4364	1-126-967-11	ELECT	47UF	20.00%	50V

REF.NO.	PART.NO	DESCRIPTION	REMARK			REF.NO.	PART.NO	DESCRIPTION	REMARK		
C4366	1-163-059-91	CERAMIC CHIP 0.01UF	10.00% 50V			Q4313	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
C4367	1-104-760-11	CERAMIC CHIP 0.047UF	10.00% 50V			Q4315	1-801-806-11	TRANSISTOR DTC144EKA-T146			
C4369	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V			Q4316	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R			
C4370	1-126-967-11	ELECT 47UF	20.00% 50V			Q4317	8-729-900-53	TRANSISTOR DTC114EKA-T146			
C4371	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V								
								< RESISTOR >			
C4377	1-126-960-11	ELECT 1UF	20.00% 50V								
C4379	1-163-243-11	CERAMIC CHIP 47PF	5.00% 50V			R4301	1-216-025-91	RES-CHIP	100	5%	1/10W
C4519	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V			R4302	1-216-025-91	RES-CHIP	100	5%	1/10W
						R4303	1-216-025-91	RES-CHIP	100	5%	1/10W
						R4304	1-216-025-91	RES-CHIP	100	5%	1/10W
		< CONNECTOR >				R4305	1-216-025-91	RES-CHIP	100	5%	1/10W
CN4101	1-695-301-11	CONNECTOR, BOARD TO BOARD 40P				R4306	1-216-025-91	RES-CHIP	100	5%	1/10W
CN4500	*1-564-511-11	PLUG, CONNECTOR 8P				R4307	1-216-045-00	RES-CHIP	680	5%	1/10W
CN4502	*1-568-878-51	PIN, CONNECTOR 3P				R4308	1-216-045-00	RES-CHIP	680	5%	1/10W
						R4309	1-216-045-00	RES-CHIP	680	5%	1/10W
		< DIODE >				R4313	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
D4304	8-719-923-60	DIODE MTZJ-T-77-9.1				R4314	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
D4305	8-719-923-60	DIODE MTZJ-T-77-9.1				R4331	1-216-073-00	RES-CHIP	10K	5%	1/10W
D4311	8-719-914-43	DIODE DAN202K-T-146				R4332	1-216-073-00	RES-CHIP	10K	5%	1/10W
D4312	8-719-914-43	DIODE DAN202K-T-146				R4333	1-216-073-00	RES-CHIP	10K	5%	1/10W
D4313	8-719-401-63	DIODE MA3062M-TX				R4334	1-216-025-91	RES-CHIP	100	5%	1/10W
		< FERRITE BEAD >				R4335	1-216-025-91	RES-CHIP	100	5%	1/10W
						R4336	1-216-025-91	RES-CHIP	100	5%	1/10W
FB4387	1-414-234-22	INDUCTOR CHIP 0UH				R4337	1-216-025-91	RES-CHIP	100	5%	1/10W
FB4388	1-414-234-22	INDUCTOR CHIP 0UH				R4339	1-216-049-91	RES-CHIP	1K	5%	1/10W
FB4389	1-414-234-22	INDUCTOR CHIP 0UH				R4340	1-216-111-00	RES-CHIP	390K	5%	1/10W
		< IC >				R4341	1-216-295-91	SHORT	0		
						R4343	1-216-025-91	RES-CHIP	100	5%	1/10W
IC4301	8-752-090-88	IC CXA2100AQ-TL				R4344	1-216-025-91	RES-CHIP	100	5%	1/10W
						R4345	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
		< COIL >				R4346	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
L4301	1-414-183-41	INDUCTOR 10UH				R4347	1-216-025-91	RES-CHIP	100	5%	1/10W
L4302	1-414-183-41	INDUCTOR 10UH				R4348	1-216-025-91	RES-CHIP	100	5%	1/10W
L4303	1-414-183-41	INDUCTOR 10UH				R4350	1-216-025-91	RES-CHIP	100	5%	1/10W
L4304	1-414-183-41	INDUCTOR 10UH				R4354	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
L4305	1-414-183-41	INDUCTOR 10UH				R4355	1-216-009-91	RES-CHIP	22	5%	1/10W
L4306	1-414-183-41	INDUCTOR 10UH				R4356	1-216-009-91	RES-CHIP	22	5%	1/10W
L4308	1-414-186-31	INDUCTOR 33UH				R4357	1-216-009-91	RES-CHIP	22	5%	1/10W
L4309	1-414-186-31	INDUCTOR 33UH				R4358	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
						R4359	1-216-041-00	RES-CHIP	470	5%	1/10W
		< TRANSISTOR >				R4360	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
Q4304	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4361	1-216-133-00	RES-CHIP	3.3M	5%	1/10W
Q4307	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4363	1-216-025-91	RES-CHIP	100	5%	1/10W
Q4308	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4365	1-216-025-91	RES-CHIP	100	5%	1/10W
Q4309	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4366	1-216-025-91	RES-CHIP	100	5%	1/10W
Q4310	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4367	1-216-025-91	RES-CHIP	100	5%	1/10W
Q4311	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R				R4370	1-216-089-91	RES-CHIP	47K	5%	1/10W
Q4312	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R									

REF. NO.	PART.NO	DESCRIPTION			REMARK
R4371	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R4372	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4373	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4374	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4375	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4376	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4377	1-216-049-91	RES-CHIP	1K	5%	1/10W
R4378	1-216-101-00	RES-CHIP	150K	5%	1/10W
R4379	1-216-091-00	RES-CHIP	56K	5%	1/10W
R4380	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4382	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4383	1-216-079-00	RES-CHIP	18K	5%	1/10W
R4384	1-216-025-91	RES-CHIP	100	5%	1/10W
R4387	1-216-031-00	RES-CHIP	180	5%	1/10W
R4388	1-216-031-00	RES-CHIP	180	5%	1/10W
R4389	1-216-031-00	RES-CHIP	180	5%	1/10W
R4394	1-216-025-91	RES-CHIP	100	5%	1/10W
R4395	1-216-295-91	SHORT	0		
R4396	1-216-295-91	SHORT	0		
R4398	1-216-025-91	RES-CHIP	100	5%	1/10W
R4399	1-216-025-91	RES-CHIP	100	5%	1/10W
R4401	1-216-105-91	RES-CHIP	220K	5%	1/10W
R4404	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4518	1-216-025-91	RES-CHIP	100	5%	1/10W
R4519	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4520	1-216-295-91	SHORT	0		
R4521	1-216-295-91	SHORT	0		
R4522	1-216-073-00	RES-CHIP	10K	5%	1/10W

< CRYSTAL >

X4300	1-767-127-11	VIBRATOR, CERAMIC	

E Board Variant Parts KV-32FQ75

< CAPACITOR >

C4380	1-163-017-00	CERAMIC CHIP	0.0047UF	10.00%	50V

< TRANSISTOR >

Q4318	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R

< RESISTOR >

R4403	1-216-073-00	RES-CHIP	10K	5%	1/10W
R4405	1-216-689-11	RES-CHIP	39K	5%	1/10W
R4406	1-216-105-91	RES-CHIP	220K	5%	1/10W
R4407	1-216-091-00	RES-CHIP	56K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK
*A-1640-382-A		**D1 Board, Complete (KV-28FQ75)**			
*A-1640-385-A		**D1 Board, Complete (KV-32FQ75)**			

D1 Board Common Parts

	4-382-854-11	SCREW (M3X10), P, SW (+)

< CAPACITOR >

C6100	1-136-165-00	MYLAR	0.1UF	5.00%	50V
C6101	1-136-165-00	MYLAR	0.1UF	5.00%	50V
C6102	1-136-165-00	MYLAR	0.1UF	5.00%	50V
C6103	1-163-205-00	CERAMIC CHIP	0.001UF	5.00%	50V
C6104	1-163-205-00	CERAMIC CHIP	0.001UF	5.00%	50V
C6105	1-126-967-11	ELECT	47UF	20.00%	50V
C6106	1-163-133-00	CERAMIC CHIP	470PF	5.00%	50V
C6108	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
C6109	1-126-967-11	ELECT	47UF	20.00%	50V
C6110	1-126-967-11	ELECT	47UF	20.00%	50V
C6112	1-163-037-11	CERAMIC CHIP	0.022UF	10.00%	50V
C6113	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
C6114	1-126-964-11	ELECT	10UF	20.00%	50V
C6115	1-163-005-11	CERAMIC CHIP	470PF	10.00%	50V
C6116	1-163-275-11	CERAMIC CHIP	0.001UF	5.00%	50V
C6117	1-163-275-11	CERAMIC CHIP	0.001UF	5.00%	50V
C6119	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
C6120	1-163-809-11	CERAMIC CHIP	0.047UF	10.00%	25V
C6121	1-126-964-11	ELECT	10UF	20.00%	50V
C6122	1-126-967-11	ELECT	47UF	20.00%	50V
C6125	1-163-017-00	CERAMIC CHIP	0.0047UF	10.00%	50V
C6126	1-163-809-11	CERAMIC CHIP	0.047UF	10.00%	25V
C6127	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
C6128	1-163-017-00	CERAMIC CHIP	0.0047UF	10.00%	50V
C6129	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V
C6131	1-126-964-11	ELECT	10UF	20.00%	50V
C6132	1-163-259-91	CERAMIC CHIP	220PF	5.00%	50V
C6199	1-163-229-11	CERAMIC CHIP	12PF	5.00%	50V
C6207	1-126-967-11	ELECT	47UF	20.00%	50V
C6208	1-126-967-11	ELECT	47UF	20.00%	50V
C6209	1-163-133-00	CERAMIC CHIP	470PF	5.00%	50V
C6210	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V
C6250	1-104-664-11	ELECT	47UF	20.00%	16V
C6251	1-216-295-91	SHORT	0		
C6253	1-115-339-11	CERAMIC CHIP	0.1UF	10.00%	50V
C6254	1-136-177-00	MYLAR	1UF	5.00%	50V
C6255	1-136-177-00	MYLAR	1UF	5.00%	50V
C6256	1-163-117-00	CERAMIC CHIP	100PF	5.00%	50V
C6257	1-115-339-11	CERAMIC CHIP	0.1UF	10.00%	50V

REF.NO.	PART.NO	DESCRIPTION		REMARK		REF.NO.	PART.NO	DESCRIPTION	REMARK
C6258	1-163-127-00	CERAMIC CHIP	270PF	5.00%	50V			< CONNECTOR >	
C6259	1-110-501-11	CERAMIC CHIP	0.33UF	10.00%	16V				
C6260	1-104-664-11	ELECT	47UF	20.00%	16V	CN6502	*1-568-881-51	PIN, CONNECTOR 6P	
C6261	1-115-339-11	CERAMIC CHIP	0.1UF	10.00%	50V	CN6600	*1-508-786-00	PIN, CONNECTOR (5MM PITCH) 2P	
C6262	1-136-165-00	MYLAR	0.1UF	5.00%	50V	CN6601	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P	
						CN6622	*1-564-506-11	PLUG, CONNECTOR 3P	
C6263	1-163-109-00	CERAMIC CHIP	47PF	5.00%	50V	CN6633	*1-564-506-11	PLUG, CONNECTOR 3P	
C6264	1-126-964-11	ELECT	10UF	20.00%	50V				
C6306	1-126-964-11	ELECT	10UF	20.00%	50V			< DIODE >	
C6307	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V				
C6350	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	D6102	8-719-914-43	DIODE DAN202K-T-146	
						D6104	8-719-914-43	DIODE DAN202K-T-146	
C6351	1-126-967-11	ELECT	47UF	20.00%	50V	D6105	8-719-914-43	DIODE DAN202K-T-146	
C6353	1-115-339-11	CERAMIC CHIP	0.1UF	10.00%	50V	D6107	8-719-914-43	DIODE DAN202K-T-146	
C6354	1-136-159-00	MYLAR	0.033UF	5.00%	50V	D6108	8-719-921-40	DIODE MTZJ-T-77-4.7B	
C6355	1-163-251-11	CERAMIC CHIP	100PF	5.00%	50V				
C6356	1-163-809-11	CERAMIC CHIP	0.047UF	10.00%	25V	D6127	8-719-914-43	DIODE DAN202K-T-146	
						D6128	8-719-914-43	DIODE DAN202K-T-146	
C6357	1-136-165-00	MYLAR	0.1UF	5.00%	50V	D6129	8-719-914-43	DIODE DAN202K-T-146	
C6358	1-104-329-11	CERAMIC CHIP	0.1UF	10.00%	50V	D6198	8-535-303-00	LEAD, JUMPER (5.0MM)	
C6359	1-104-329-11	CERAMIC CHIP	0.1UF	10.00%	50V	D6253	8-719-911-19	DIODE 1SS119-25TD	
C6360	1-107-714-11	ELECT	10UF	20.00%	50V				
C6361	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	D6254	1-535-303-00	LEAD, JUMPER (5.0MM)	
						D6255	8-719-914-43	DIODE DAN202K-T-146	
C6362	1-164-182-11	CERAMIC CHIP	0.0033UF	10.00%	50V	D6350	8-719-914-43	DIODE DAN202K-T-146	
C6363	1-104-665-11	ELECT	100UF	20.00%	25V	D6351	8-719-914-43	DIODE DAN202K-T-146	
C6364	1-136-347-11	FILM	0.0047UF	5.00%	630V	D6352	8-719-914-43	DIODE DAN202K-T-146	
C6365	1-163-809-11	CERAMIC CHIP	0.047UF	10.00%	25V				
C6367	1-104-329-11	CERAMIC CHIP	0.1UF	10.00%	50V	D6353	8-719-987-87	DIODE ERA82-004TP1	
						D6354	8-719-914-43	DIODE DAN202K-T-146	
C6368	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V	D6355	8-719-914-43	DIODE DAN202K-T-146	
C6370	1-136-347-11	FILM	0.0047UF	5.00%	630V	D6358	8-719-914-43	DIODE DAN202K-T-146	
C6373	1-136-153-00	MYLAR	0.01UF	5.00%	50V	D6359	8-719-302-43	DIODE RGP10GPKG23	
C6374	1-129-716-00	FILM	0.015UF	5.00%	630V				
C6375	1-102-110-00	CERAMIC	220PF	10.00%	50V	D6401	8-719-914-43	DIODE DAN202K-T-146	
						D6402	8-719-982-03	DIODE MTZJ-T-77-3.6A	
C6376	1-104-664-11	ELECT	47UF	20.00%	16V	D6403	8-719-921-63	DIODE MTZJ-T-77-7.5B	
C6377	1-128-551-11	ELECT	22UF	20.00%	25V	D6404	8-719-914-43	DIODE DAN202K-T-146	
C6378	1-115-339-11	CERAMIC CHIP	0.1UF	10.00%	50V	D6405	8-719-921-63	DIODE MTZJ-T-77-7.5B	
C6380	1-136-165-00	MYLAR	0.1UF	5.00%	50V				
C6381	1-126-960-11	ELECT	1UF	20.00%	50V			< IC >	
C6385	1-104-664-11	ELECT	47UF	20.00%	25V	IC6100	8-759-450-95	IC LM393N	
C6386	1-104-664-11	ELECT	47UF	20.00%	25V	IC6101	8-759-450-95	IC LM393N	
C6388	1-126-964-11	ELECT	10UF	20.00%	50V	IC6102	8-759-701-50	IC NJM3404AD	
C6389	1-126-964-11	ELECT	10UF	20.00%	50V	IC6103	8-759-450-95	IC LM393N	
C6392	1-104-664-11	ELECT	47UF	20.00%	25V	IC6250	8-759-478-66	IC CXA8070P	
C6401	1-126-964-11	ELECT	10UF	20.00%	50V	IC6251	8-759-903-16	IC LM318P	
C6402	1-107-714-11	ELECT	10UF	20.00%	50V	IC6302	8-752-072-94	IC CXA1875AM-T4	
C6407	1-136-161-00	MYLAR	0.047UF	5.00%	50V	IC6350	8-759-008-70	IC LM358N	
C6408	1-136-161-00	MYLAR	0.047UF	5.00%	50V	IC6351	8-759-450-95	IC LM393N	
C6409	1-126-964-11	ELECT	10UF	20.00%	50V	IC6352	8-759-450-95	IC LM393N	
C6420	1-136-497-81	FILM	0.1UF	5.00%	50V	IC6353	8-759-231-53	IC L7805CV	
C6421	1-136-497-81	FILM	0.1UF	5.00%	50V	IC6354	8-759-325-48	IC CA0005AD	

D1

REF. NO.	PART.NO	DESCRIPTION	REMARK
IC6355	8-759-008-70	IC LM358N	
IC6356	8-759-822-38	IC LA6510	
		< FILTER >	
LF6350	1-406-989-21	INDUCTOR 10MH	
LF6351	1-406-989-21	INDUCTOR 10MH	
		< IC LINK >	
PS6376 ⚠	1-532-637-00	LINK, IC 1A (ICP-N25)	
		< TRANSISTOR >	
Q6100	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6101	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6102	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6103	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6104	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6105	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6106	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6107	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6108	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6110	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6112	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6113	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6118	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6119	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6120	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6122	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6123	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6125	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6126	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6127	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6128	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6129	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6201	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6202	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6250	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6251	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6252	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R	
Q6253	8-729-045-04	TRANSISTOR 2SC5511	
Q6254	8-729-045-04	TRANSISTOR 2SC5511	
Q6350	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6351	8-729-119-78	TRANSISTOR 2SC1740S-RT	
Q6352	8-729-140-97	TRANSISTOR 2SB734-T-3	
Q6353	8-729-140-97	TRANSISTOR 2SB734-T-3	
Q6354	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
Q6356	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	

REF. NO.	PART.NO	DESCRIPTION			REMARK
Q6358	8-729-038-83	TRANSISTOR 2SK2251-01-F19			
Q6401	1-801-806-11	TRANSISTOR DTC144EKA-T146			
Q6402	1-801-806-11	TRANSISTOR DTC144EKA-T146			
Q6403	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R			
Q6404	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
Q6405	8-729-026-49	TRANSISTOR 2SA1037AK-T146-R			
Q6455	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R			
Q6465	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R			
		< RESISTOR >			
R6100	1-216-033-00	RES-CHIP	220	5%	1/10W
R6101	1-216-033-00	RES-CHIP	220	5%	1/10W
R6102	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6103	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6104	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6105	1-216-049-91	RES-CHIP	1K	5%	1/10W
R6106	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6109	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6110	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6111	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6112	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6113	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6114	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6115	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6116	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6117	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6118	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6119	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6120	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6121	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6122	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6123	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6124	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6125	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6126	1-216-037-00	RES-CHIP	330	5%	1/10W
R6128	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6129	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6131	1-216-037-00	RES-CHIP	330	5%	1/10W
R6132	1-216-037-00	RES-CHIP	330	5%	1/10W
R6133	1-216-037-00	RES-CHIP	330	5%	1/10W
R6135	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V
R6136	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6137	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6138	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6139	1-216-691-11	METAL CHIP	47K	0.5%	1/10W
R6140	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6143	1-216-057-00	RES-CHIP	2.2K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R6146	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6270	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W
R6148	1-216-295-91	SHORT	0			R6271	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6149	1-216-025-91	RES-CHIP	100	5%	1/10W	R6278	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6154	1-216-049-91	RES-CHIP	1K	5%	1/10W	R6279	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6155	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6280	1-212-849-00	FUSIBLE	4.7	5%	1/4W
R6160	1-216-295-91	SHORT	0			R6281	1-212-849-00	FUSIBLE	4.7	5%	1/4W
R6162	1-216-049-91	RES-CHIP	1K	5%	1/10W	R6282	1-215-886-11	METAL OXIDE	100	5%	2W
R6165	1-216-699-91	METAL CHIP	100K	0.5%	1/10W	R6283	1-216-393-00	METAL OXIDE	2.2	5%	3W
R6168	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6285	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6169	1-216-699-91	METAL CHIP	100K	0.5%	1/10W	R6313	1-216-295-91	SHORT	0		
R6170	1-216-037-00	RES-CHIP	330	5%	1/10W	R6322	1-216-049-91	RES-CHIP	1K	5%	1/10W
R6171	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6323	1-216-049-91	RES-CHIP	1K	5%	1/10W
R6177	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6324	1-216-025-91	RES-CHIP	100	5%	1/10W
R6180	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6325	1-216-025-91	RES-CHIP	100	5%	1/10W
R6182	1-216-089-91	RES-CHIP	47K	5%	1/10W	R6350	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6183	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6351	1-218-762-11	METAL CHIP	270K	0.5%	1/10W
R6188	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6353	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R6190	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6355	1-218-774-11	METAL CHIP	820K	0.5%	1/10W
R6191	1-215-925-11	METAL OXIDE	22K	5%	3W	R6356	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6192	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R6357	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6194	1-216-065-91	RES-CHIP	4.7K	5%	1/10W	R6358	1-216-047-91	RES-CHIP	820	5%	1/10W
R6195	1-216-683-11	METAL CHIP	22K	0.5%	1/10W	R6359	1-216-097-91	RES-CHIP	100K	5%	1/10W
R6196	1-249-377-11	CARBON	0.47	5%	1/4W	R6360	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6198	1-216-081-00	RES-CHIP	22K	5%	1/10W	R6361	1-216-097-91	RES-CHIP	100K	5%	1/10W
R6199	1-216-081-00	RES-CHIP	22K	5%	1/10W	R6362	1-216-687-11	METAL CHIP	33K	0.5%	1/10W
R6205	1-216-025-91	RES-CHIP	100	5%	1/10W	R6363	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6208	1-216-089-91	RES-CHIP	47K	5%	1/10W	R6364	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6210	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6365	1-216-033-00	RES-CHIP	220	5%	1/10W
R6211	1-216-073-00	RES-CHIP	10K	5%	1/10W	R6366	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6212	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6367	1-216-679-11	METAL CHIP	15K	0.5%	1/10W
R6215	1-216-089-91	RES-CHIP	47K	5%	1/10W	R6368	1-218-760-11	METAL CHIP	220K	0.5%	1/10W
R6216	1-216-089-91	RES-CHIP	47K	5%	1/10W	R6369	1-218-762-11	METAL CHIP	270K	0.5%	1/10W
R6217	1-216-073-00	RES-CHIP	10K	5%	1/10W	R6371	1-216-474-11	METAL OXIDE	82	5%	3W
R6218	1-216-295-91	SHORT	0			R6372	1-216-033-00	RES-CHIP	220	5%	1/10W
R6254	1-216-049-91	RES-CHIP	1K	5%	1/10W	R6373	1-216-681-11	METAL CHIP	18K	0.5%	1/10W
R6255	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R6374	1-216-689-11	METAL CHIP	39K	0.5%	1/10W
R6256	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6375	1-216-041-00	RES-CHIP	470	5%	1/10W
R6257	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R6377	1-216-689-11	METAL CHIP	39K	0.5%	1/10W
R6258	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R6378	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6259	1-216-097-91	RES-CHIP	100K	5%	1/10W	R6379	1-216-295-91	SHORT	0		
R6260	1-216-049-91	RES-CHIP	1K	5%	1/10W	R6380	1-218-754-11	METAL CHIP	120K	0.5%	1/10W
R6261	1-216-097-91	RES-CHIP	100K	5%	1/10W	R6381	1-216-045-00	RES-CHIP	680	5%	1/10W
R6262	1-260-321-71	CARBON	270	5%	1/2W	R6382	1-218-754-11	METAL CHIP	120K	0.5%	1/10W
R6263	1-216-025-91	RES-CHIP	100	5%	1/10W	R6383	1-216-687-11	METAL CHIP	33K	0.5%	1/10W
R6264	1-216-025-91	RES-CHIP	100	5%	1/10W	R6384	1-216-043-91	RES-CHIP	560	5%	1/10W
R6267	1-216-049-91	RES-CHIP	1K	5%	1/10W	R6385	1-216-295-91	SHORT	0		
R6269	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W	R6386	1-216-699-91	METAL CHIP	100K	0.5%	1/10W

D1

REF. NO.	PART.NO	DESCRIPTION			REMARK
R6387	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R6391	1-249-417-11	CARBON	1K	5%	1/4W
R6394	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
R6395	1-216-081-00	RES-CHIP	22K	5%	1/10W
R6397	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6398	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6399	1-218-756-11	METAL CHIP	150K	0.5%	1/10W
R6400	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6401	1-216-295-91	SHORT	0		
R6402	1-216-295-91	SHORT	0		
R6403	1-216-661-11	METAL CHIP	2.7K	0.5%	1/10W
R6404	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6405	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6409	1-216-025-91	RES-CHIP	100	5%	1/10W
R6410	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6411	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6412	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6413	1-216-679-11	METAL CHIP	15K	0.5%	1/10W
R6414	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6415	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6416	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6418	1-216-091-00	RES-CHIP	56K	5%	1/10W
R6419	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6420	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6421	1-216-637-11	METAL CHIP	270	0.5%	1/10W
R6422	1-216-639-11	METAL CHIP	330	0.5%	1/10W
R6423	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R6426	1-216-081-00	RES-CHIP	22K	5%	1/10W
R6427	1-216-081-00	RES-CHIP	22K	5%	1/10W
R6429	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6430	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6432	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6433	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6437	1-249-422-11	CARBON	2.7K	5%	1/4W
R6438	1-249-421-11	CARBON	2.2K	5%	1/4W
R6439	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6440	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6441	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6442	1-216-039-00	RES-CHIP	390	5%	1/10W
R6455	1-216-295-91	SHORT	0		
R6456	1-216-097-91	RES-CHIP	100K	5%	1/10W
R6457	1-216-075-00	RES-CHIP	12K	5%	1/10W
R6458	1-216-089-91	RES-CHIP	47K	5%	1/10W
R6459	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R6460	1-249-393-11	CARBON	10	5%	1/4W
R6461	1-249-411-11	CARBON	330	5%	1/4W
R6462	1-249-406-11	CARBON	120	5%	1/4W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R6463	1-216-095-00	RES-CHIP	82K	5%	1/10W
R6464	1-216-079-00	RES-CHIP	18K	5%	1/10W

D1 Board Variant Parts KV-28FQ75

< CAPACITOR >

C6130	1-163-259-91	CERAMIC CHIP	220PF	5.00%	16V
C6134	1-102-508-91	CERAMIC	10PF	0.50%	50V

< RESISTOR >

R6107	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R6108	1-216-657-11	METAL CHIP	1.8K	0.5%	1/10W
R6127	1-216-659-11	METAL CHIP	2.2K	5%	1/10W
R6130	1-218-768-11	METAL CHIP	470K	0.5%	1/10W
R6141	1-216-683-11	METAL CHIP	22K	0.5%	1/10W
R6142	1-216-670-11	METAL CHIP	6.2K	0.5%	1/10W
R6144	1-216-105-41	RES-CHIP	220K	5%	1/10W
R6145	1-216-053-00	RES-CHIP	1.5K	5%	1/10W
R6158	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R6159	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R6161	1-216-671-11	METAL CHIP	6.8K	0.5%	1/10W
R6174	1-216-075-00	RES-CHIP	12K	5%	1/10W
R6175	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6176	1-216-295-91	SHORT	0		
R6179	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
R6186	1-216-045-00	RES-CHIP	680	5%	1/10W
R6189	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R6193	1-163-251-11	CERAMIC CHIP	100PF	5%	50V
R6200	1-216-695-11	METAL CHIP	68K	0.5%	1/10W
R6206	1-216-107-91	RES-CHIP	270K	5%	1/10W
R6207	1-216-113-00	RES-CHIP	470K	5%	1/10W
R6265	1-216-101-00	RES-CHIP	150K	5%	1/10W
R6268	1-216-081-00	RES-CHIP	22K	5%	1/10W
R6276	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R6277	1-216-677-11	METAL CHIP	12K	0.5%	1/10W
R6284	1-216-113-00	RES-CHIP	470K	5%	1/10W
R6286	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6287	1-216-073-00	RES-CHIP	10K	5%	1/10W
R6370	1-216-675-91	METAL CHIP	10K	0.5%	1/10W
R6428	1-216-103-00	RES-CHIP	180K	5%	1/10W
R6431	1-216-115-00	RES-CHIP	560K	5%	1/10W

D1 Board Variant Parts KV-32FQ75

< RESISTOR >

R6107	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
R6108	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK		
R6127	1-216-663-11	METAL CHIP	3.3K	5%	1/10W		
R6130	1-218-769-11	METAL CHIP	510K	0.5%	1/10W		
R6141	1-216-679-11	METAL CHIP	15K	0.5%	1/10W		
R6142	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W		
R6144	1-216-099-00	RES-CHIP	120K	5%	1/10W		
R6145	1-216-055-00	RES-CHIP	1.8K	5%	1/10W		
R6158	1-216-667-11	METAL CHIP	4.7K	0.5%	1/10W		
R6159	1-216-295-91	SHORT	0				
R6161	1-216-673-11	METAL CHIP	8.2K	0.5%	1/10W		
R6174	1-216-081-00	RES-CHIP	22K	5%	1/10W		
R6175	1-216-069-00	RES-CHIP	6.8K	5%	1/10W		
R6176	1-216-071-00	RES-CHIP	8.2K	5%	1.10W		
R6179	1-216-295-91	SHORT	0				
R6186	1-216-063-91	RES-CHIP	3.9K	5%	1/10W		
R6189	1-216-295-91	SHORT	0				
R6206	1-216-105-91	RES-CHIP	220K	5%	1/10W		
R6207	1-216-105-91	RES-CHIP	220K	5%	1/10W		
R6265	1-216-105-91	RES-CHIP	220K	5%	1/10W		
R6266	1-216-113-00	RES-CHIP	470K	5%	1/10W		
R6268	1-216-093-91	RES-CHIP	68K	5%	1/10W		
R6276	1-216-686-11	METAL CHIP	30K	0.5%	1/10W		
R6277	1-216-686-11	METAL CHIP	30K	0.5%	1/10W		
R6284	1-216-109-00	RES-CHIP	330K	5%	1/10W		
R6286	1-216-071-00	RES-CHIP	8.2K	5%	1/10W		
R6287	1-216-081-00	RES-CHIP	22K	5%	1/10W		
R6370	1-216-677-11	METAL CHIP	12K	0.5%	1/10W		
R6428	1-216-101-00	RES-CHIP	150K	5%	1/10W		
R6431	1-216-113-00	RES-CHIP	470K	5%	1/10W		

*A-1651-133-A   J Board, Complete

<CAPACITOR>

REF. NO.	PART.NO	DESCRIPTION		REMARK		
C8105	1-126-933-11	ELECT	100UF	20.00%	16V	
C8106	1-126-933-11	ELECT	100UF	20.00%	16V	
C8107	1-126-935-11	ELECT	470UF	20.00%	16V	
C8108	1-126-933-11	ELECT	100UF	20.00%	16V	
C8109	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8110	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8111	1-126-933-11	ELECT	100UF	20.00%	16V	
C8112	1-107-715-11	ELECT	22UF	20.00%	16V	
C8144	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8145	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8150	1-163-251-11	CERAMIC CHIP	100PF	5.00%	50V	
C8151	1-163-017-00	CERAMIC CHIP	0.0047UF	10.00%	50V	
C8152	1-164-346-11	CERAMIC CHIP	1UF		16V	
C8153	1-107-682-11	CERAMIC CHIP	1UF	10.00%	16V	
C8154	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V	

REF. NO.	PART.NO	DESCRIPTION		REMARK		
C8155	1-107-682-11	CERAMIC CHIP	1UF	10.00%	16V	
C8156	1-164-505-11	CERAMIC CHIP	2.2UF		16V	
C8157	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V	
C8159	1-104-664-11	ELECT	47UF	20.00%	16V	
C8200	1-104-664-11	ELECT	47UF	20.00%	16V	
C8201	1-163-241-11	CERAMIC CHIP	39PF	5.00%	50V	
C8202	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8203	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8204	1-164-506-11	CERAMIC CHIP	4.7UF		16V	
C8205	1-165-319-11	CERAMIC CHIP	0.1UF		50V	
C8208	1-164-506-11	CERAMIC CHIP	4.7UF		16V	
C8209	1-163-251-11	CERAMIC CHIP	100PF	5.00%	50V	
C8210	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8211	1-163-243-11	CERAMIC CHIP	47PF	5.00%	50V	
C8212	1-163-243-11	CERAMIC CHIP	47PF	5.00%	50V	
C8213	1-163-087-00	CERAMIC CHIP	4PF	0.25PF	50V	
C8214	1-163-087-00	CERAMIC CHIP	4PF	0.25PF	50V	
C8215	1-163-243-11	CERAMIC CHIP	47PF	5.00%	50V	
C8216	1-126-933-11	ELECT	100UF	20.00%	16V	
C8217	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8218	1-126-964-11	ELECT	10UF	20.00%	50V	
C8219	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8220	1-126-964-11	ELECT	10UF	20.00%	50V	
C8221	1-104-664-11	ELECT	47UF	20.00%	16V	
C8222	1-104-664-11	ELECT	47UF	20.00%	16V	
C8223	1-104-664-11	ELECT	47UF	20.00%	16V	
C8224	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8225	1-104-664-11	ELECT	47UF	20.00%	16V	
C8227	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V	
C8228	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V	
C8229	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V	
C8230	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V	
C8231	1-163-009-11	CERAMIC CHIP	0.001UF	10.00%	50V	
C8232	1-164-004-11	CERAMIC CHIP	0.1UF	10.00%	25V	
C8233	1-104-664-11	ELECT	47UF	20.00%	16V	
C8234	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8235	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8236	1-126-933-11	ELECT	100UF	20.00%	16V	
C8237	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V	
C8238	1-164-505-11	CERAMIC CHIP	2.2UF		16V	
C8239	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8240	1-107-823-11	CERAMIC CHIP	0.47UF	10.00%	16V	
C8241	1-126-964-11	ELECT	10UF	20.00%	50V	
C8242	1-104-664-11	ELECT	47UF	20.00%	16V	
C8243	1-110-501-11	CERAMIC CHIP	0.33UF	10.00%	16V	
C8301	1-163-037-11	CERAMIC CHIP	0.022UF	10.00%	50V	
C8302	1-163-021-91	CERAMIC CHIP	0.01UF	10.00%	50V	

REF. NO.	PART.NO	DESCRIPTION	REMARK	REF. NO.	PART.NO	DESCRIPTION	REMARK
C8303	1-126-933-11	ELECT 100UF	20.00% 16V	C8417	1-164-346-11	CERAMIC CHIP 1UF	16V
C8304	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8418	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8305	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8419	1-126-964-11	ELECT 10UF	20.00% 50V
C8306	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V	C8420	1-104-664-11	ELECT 47UF	20.00% 16V
C8307	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8421	1-126-933-11	ELECT 100UF	20.00% 16V
C8308	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8423	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C8309	1-126-961-11	ELECT 2.2UF	20.00% 50V	C8424	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8311	1-104-664-11	ELECT 47UF	20.00% 16V	C8427	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C8313	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8437	1-126-963-11	ELECT 4.7UF	20.00% 50V
C8314	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8501	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C8318	1-104-664-11	ELECT 47UF	20.00% 16V	C8503	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8321	1-104-664-11	ELECT 47UF	20.00% 16V	C8504	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8322	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V	C8505	1-126-933-11	ELECT 100UF	20.00% 16V
C8323	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8506	1-163-037-11	CERAMIC CHIP 0.022UF	10.00% 50V
C8324	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8507	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8325	1-126-964-11	ELECT 10UF	20.00% 50V	C8508	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8326	1-104-664-11	ELECT 47UF	20.00% 16V	C8509	1-126-933-11	ELECT 100UF	20.00% 16V
C8327	1-107-682-11	CERAMIC CHIP 1UF	10.00% 16V	C8510	1-104-664-11	ELECT 47UF	20.00% 16V
C8328	1-104-664-11	ELECT 47UF	20.00% 16V	C8511	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8329	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8512	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8331	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8513	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8332	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8514	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8333	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8515	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8334	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8516	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8335	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8517	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8336	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8518	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8337	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8519	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8338	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8520	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8345	1-164-346-11	CERAMIC CHIP 1UF	16V	C8521	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8346	1-126-963-11	ELECT 4.7UF	20.00% 50V	C8601	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8349	1-163-113-00	CERAMIC CHIP 68PF	5.00% 50V	C8602	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8401	1-107-823-11	CERAMIC CHIP 0.47UF	10.00% 16V	C8605	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8402	1-163-037-11	CERAMIC CHIP 0.022UF	10.00% 50V	C8606	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8403	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8607	1-104-664-11	ELECT 47UF	20.00% 16V
C8404	1-126-961-11	ELECT 2.2UF	20.00% 50V	C8608	1-104-664-11	ELECT 47UF	20.00% 16V
C8405	1-104-664-11	ELECT 47UF	20.00% 16V	C8609	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8406	1-104-664-11	ELECT 47UF	20.00% 16V	C8610	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8407	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8611	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8408	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8612	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V
C8409	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8613	1-104-664-11	ELECT 47UF	20.00% 16V
C8410	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8614	1-104-664-11	ELECT 47UF	20.00% 16V
C8411	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V	C8700	1-126-964-11	ELECT 10UF	20.00% 50V
C8412	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V	C8701	1-104-664-11	ELECT 47UF	20.00% 16V
C8413	1-104-664-11	ELECT 47UF	20.00% 16V	C8702	1-163-133-00	CERAMIC CHIP 470PF	5.00% 50V
C8414	1-104-664-11	ELECT 47UF	20.00% 16V	C8703	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8415	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V	C8704	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V
C8416	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V	C8705	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V

REF. NO.	PART.NO	DESCRIPTION	REMARK		REF. NO.	PART.NO	DESCRIPTION	REMARK
C8706	1-163-235-11	CERAMIC CHIP 22PF	5.00% 50V		C8862	1-164-346-11	CERAMIC CHIP 1UF	16V
C8707	1-163-235-11	CERAMIC CHIP 22PF	5.00% 50V		C8863	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8708	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8864	1-164-346-11	CERAMIC CHIP 1UF	16V
C8709	1-126-964-11	ELECT 10UF	20.00% 50V		C8865	1-104-664-11	ELECT 47UF	20.00% 16V
C8710	1-126-933-11	ELECT 100UF	20.00% 16V		C8866	1-164-346-11	CERAMIC CHIP 1UF	16V
C8804	1-126-933-11	ELECT 100UF	20.00% 16V		C8867	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8812	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		C8868	1-126-964-11	ELECT 10UF	20.00% 50V
C8814	1-104-664-11	ELECT 47UF	20.00% 25V		C8869	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V
C8817	1-126-933-11	ELECT 100UF	20.00% 16V		C8896	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8822	1-126-933-11	ELECT 100UF	20.00% 16V		C8897	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8823	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		C8898	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V
C8824	1-104-664-11	ELECT 47UF	20.00% 25V		C8899	1-163-227-11	CERAMIC CHIP 10PF	0.50PF 50V
C8825	1-115-340-11	CERAMIC CHIP 0.22UF	10.00% 25V		C8900	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8826	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V		C8901	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8827	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8902	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8828	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8903	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8829	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8904	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8830	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8905	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8831	1-126-964-11	ELECT 10UF	20.00% 50V		C8906	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8832	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8907	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8833	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8908	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8834	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8909	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8835	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8910	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V
C8836	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8911	1-163-017-00	CERAMIC CHIP 0.0047UF	10.00% 50V
C8837	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8914	1-126-933-11	ELECT 100UF	20.00% 16V
C8838	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		C8977	1-163-009-11	CERAMIC CHIP 0.001UF	10.00% 50V
C8839	1-163-251-11	CERAMIC CHIP 100PF	5.00% 50V		C8978	1-163-009-11	CERAMIC CHIP 0.001UF	10.00% 50V
C8840	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V					
C8841	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V				<FILTER>	
C8842	1-104-664-11	ELECT 47UF	20.00% 16V					
					CF8150	1-760-106-11	FILTER, CERAMIC	
C8843	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V		CF8151	1-567-100-00	FILTER, CERAMIC	
C8844	1-163-021-91	CERAMIC CHIP 0.01UF	10.00% 50V		CF8152	1-760-450-21	FILTER, CERAMIC	
C8846	1-126-933-11	ELECT 100UF	20.00% 16V		CF8200	1-409-327-00	TRAP, CERAMIC (6.5MHZ)	
C8847	1-164-004-11	CERAMIC CHIP 0.1UF	10.00% 25V					
C8849	1-164-346-11	CERAMIC CHIP 1UF	16V				<CONNECTOR>	
C8850	1-164-346-11	CERAMIC CHIP 1UF	16V		CN8101	1-695-302-11	CONNECTOR, BOARD TO BOARD 50P	
C8851	1-126-967-11	ELECT 47UF	20.00% 50V		CN8900	1-561-534-41	SOCKET, PIN 21P	
C8852	1-164-346-11	CERAMIC CHIP 1UF	16V		CN8901	1-695-293-11	SOCKET 21P	
C8853	1-126-967-11	ELECT 47UF	20.00% 50V		CN8902	1-695-293-11	SOCKET 21P	
C8854	1-164-346-11	CERAMIC CHIP 1UF	16V					
							<DIODE>	
C8855	1-164-346-11	CERAMIC CHIP 1UF	16V					
C8856	1-164-346-11	CERAMIC CHIP 1UF	16V		D8150	8-719-421-57	DIODE MA73-TX	
C8857	1-164-346-11	CERAMIC CHIP 1UF	16V		D8151	8-719-421-57	DIODE MA73-TX	
C8858	1-164-346-11	CERAMIC CHIP 1UF	16V		D8152	8-719-421-57	DIODE MA73-TX	
C8859	1-164-346-11	CERAMIC CHIP 1UF	16V		D8153	8-719-056-83	DIODE UDZ-TE-17-6.8B	
					D8200	8-719-158-49	DIODE UDZ-TE-17-12B	
C8860	1-164-346-11	CERAMIC CHIP 1UF	16V					
C8861	1-164-346-11	CERAMIC CHIP 1UF	16V		D8201	8-719-158-49	DIODE UDZ-TE-17-12B	

REF.NO.	PART.NO	DESCRIPTION	REMARK	REF.NO.	PART.NO	DESCRIPTION	REMARK
D8202	8-719-158-49	DIODE UDZ-TE-17-12B		FL8504	1-233-766-21	FILTER	
D8203	8-719-158-49	DIODE UDZ-TE-17-12B		FL8700	1-236-071-11	ENCAPSULATED COMPONENT	
D8801	8-719-158-49	DIODE UDZ-TE-17-12B		FL8701	1-236-071-11	ENCAPSULATED COMPONENT	
D8802	8-719-158-49	DIODE UDZ-TE-17-12B		FL8801	1-236-071-11	ENCAPSULATED COMPONENT	
D8803	8-719-158-49	DIODE UDZ-TE-17-12B		FL8802	1-236-071-11	ENCAPSULATED COMPONENT	
D8804	8-719-158-49	DIODE UDZ-TE-17-12B				<IC>	
D8805	8-719-158-49	DIODE UDZ-TE-17-12B					
D8806	8-719-158-49	DIODE UDZ-TE-17-12B		IC8101	8-759-576-76	IC TDA2822D013TR	
D8807	8-719-158-49	DIODE UDZ-TE-17-12B		IC8150	8-759-478-90	IC U2861B-MFP-G3	
D8808	8-719-158-49	DIODE UDZ-TE-17-12B		IC8151	8-752-072-94	IC CXA1875AM-T4	
				IC8200	8-759-654-42	IC MSP3410D-C5QA-B4	
D8809	8-719-158-49	DIODE UDZ-TE-17-12B		IC8201	8-759-701-36	IC MC3403NS-E20	
D8810	8-719-158-49	DIODE UDZ-TE-17-12B					
D8811	8-719-158-49	DIODE UDZ-TE-17-12B		IC8202	8-759-908-15	IC TL431CZ	
D8812	8-719-158-49	DIODE UDZ-TE-17-12B		IC8301	8-752-096-06	IC CXA2163Q-T6	
D8813	8-719-158-49	DIODE UDZ-TE-17-12B		IC8302	8-759-485-79	IC TC7SET08FU(TE85R)	
				IC8401	8-752-096-06	IC CXA2163Q-T6	
D8814	8-719-158-49	DIODE UDZ-TE-17-12B		IC8402	8-759-485-79	IC TC7SET08FU(TE85R)	
D8900	8-719-056-85	DIODE UDZ-TE-17-8.2B					
D8901	8-719-158-49	DIODE UDZ-TE-17-12B		IC8500	8-752-390-37	IC CXD2064Q-T6	
D8902	8-719-056-85	DIODE UDZ-TE-17-8.2B		IC8601	8-759-182-88	IC PQ09TZ5U	
D8903	8-719-056-85	DIODE UDZ-TE-17-8.2B		IC8602	8-759-576-72	IC LF50CDT-TR	
				IC8603	8-759-576-72	IC LF50CDT-TR	
D8904	8-719-056-85	DIODE UDZ-TE-17-8.2B		IC8604	8-759-576-72	IC LF50CDT-TR	
D8905	8-719-056-85	DIODE UDZ-TE-17-8.2B					
D8906	8-719-056-85	DIODE UDZ-TE-17-8.2B		IC8700	8-752-390-35	IC CXD2057M-T6	
D8907	8-719-158-49	DIODE UDZ-TE-17-12B		IC8801	8-752-096-83	IC CXA2149AQ-TL	
D8908	8-719-056-85	DIODE UDZ-TE-17-8.2B					
						<JACK>	
D8909	8-719-056-85	DIODE UDZ-TE-17-8.2B					
D8910	8-719-056-85	DIODE UDZ-TE-17-8.2B		J8901	1-774-747-11	JACK BLOCK, PIN	
D8911	8-719-056-85	DIODE UDZ-TE-17-8.2B					
D8912	8-719-158-49	DIODE UDZ-TE-17-12B				<CHIP CONDUCTOR>	
D8913	8-719-158-49	DIODE UDZ-TE-17-12B					
				JR8101	1-216-295-91	SHORT 0	
D8914	8-719-158-49	DIODE UDZ-TE-17-12B		JR8402	1-216-295-91	SHORT 0	
D8915	8-719-158-49	DIODE UDZ-TE-17-12B					
						<COIL>	
		<FILTER>					
				L8150	1-414-757-11	INDUCTOR 100UH	
FL8200	1-236-071-11	ENCAPSULATED COMPONENT		L8200	1-412-006-31	INDUCTOR CHIP 10UH	
FL8201	1-233-764-21	FILTER		L8201	1-412-064-11	INDUCTOR CHIP 100UH	
FL8203	1-236-071-11	ENCAPSULATED COMPONENT		L8301	1-412-006-31	INDUCTOR CHIP 10UH	
FL8302	1-236-071-11	ENCAPSULATED COMPONENT					
FL8304	1-236-071-11	ENCAPSULATED COMPONENT				<TRANSISTOR>	
FL8308	1-236-071-11	ENCAPSULATED COMPONENT		Q8100	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
FL8401	1-236-071-11	ENCAPSULATED COMPONENT		Q8101	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
FL8402	1-236-071-11	ENCAPSULATED COMPONENT		Q8150	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	
FL8403	1-236-071-11	ENCAPSULATED COMPONENT		Q8151	1-801-806-11	TRANSISTOR DTC144EKA-T146	
FL8500	1-236-071-11	ENCAPSULATED COMPONENT		Q8152	1-801-806-11	TRANSISTOR DTC144EKA-T146	
FL8501	1-236-071-11	ENCAPSULATED COMPONENT		Q8153	1-801-806-11	TRANSISTOR DTC144EKA-T146	
FL8502	1-233-765-21	FILTER		Q8154	1-801-806-11	TRANSISTOR DTC144EKA-T146	
FL8503	1-233-768-21	FILTER		Q8156	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R	

REF.NO.	PART.NO	DESCRIPTION			REMARK	REF.NO.	PART.NO	DESCRIPTION			REMARK
Q8157	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8150	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
Q8200	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8151	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q8201	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8152	1-216-035-00	RES-CHIP	270	5%	1/10W
Q8202	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8153	1-216-081-00	RES-CHIP	22K	5%	1/10W
Q8300	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8154	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q8302	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8155	1-216-043-91	RES-CHIP	560	5%	1/10W
Q8303	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8156	1-216-081-00	RES-CHIP	22K	5%	1/10W
Q8305	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8157	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q8306	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8158	1-216-043-91	RES-CHIP	560	5%	1/10W
Q8308	8-729-038-96	TRANSISTOR IMZ1A-T109				R8159	1-216-081-00	RES-CHIP	22K	5%	1/10W
Q8309	8-729-038-96	TRANSISTOR IMZ1A-T109				R8160	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
Q8310	8-729-038-96	TRANSISTOR IMZ1A-T109				R8161	1-216-043-91	RES-CHIP	560	5%	1/10W
Q8401	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8162	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q8402	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8163	1-216-295-91	SHORT	0		
Q8403	8-729-038-96	TRANSISTOR IMZ1A-T109				R8164	1-216-295-91	SHORT	0		
Q8404	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8165	1-216-295-91	SHORT	0		
Q8405	8-729-038-96	TRANSISTOR IMZ1A-T109				R8167	1-216-025-91	RES-CHIP	100	5%	1/10W
Q8406	8-729-038-96	TRANSISTOR IMZ1A-T109				R8168	1-216-025-91	RES-CHIP	100	5%	1/10W
Q8501	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8174	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
Q8503	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8175	1-216-065-91	RES-CHIP	4.7K	5%	1/10W
Q8504	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8176	1-216-295-91	SHORT	0		
Q8700	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8178	1-216-073-00	RES-CHIP	10K	5%	1/10W
Q8809	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8200	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q8814	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8201	1-216-295-91	SHORT	0		
Q8816	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8202	1-216-021-00	RES-CHIP	68	5%	1/10W
Q8817	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8203	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q8818	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8204	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q8819	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8205	1-216-069-00	RES-CHIP	6.8K	5%	1/10W
Q8820	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8206	1-216-049-91	RES-CHIP	1K	5%	1/10W
Q8901	8-729-120-28	TRANSISTOR 2SC2412K-T-146-R				R8208	1-216-037-00	RES-CHIP	330	5%	1/10W
Q8902	8-729-216-22	TRANSISTOR 2SA1037K-T-146-R				R8209	1-216-659-11	METAL CHIP	2.2K	0.5%	1/10W
						R8210	1-216-025-91	RES-CHIP	100	5%	1/10W
		<RESISTOR>				R8211	1-216-295-91	SHORT	0		
						R8212	1-216-295-91	SHORT	0		
R8103	1-216-075-00	RES-CHIP	12K	5%	1/10W	R8213	1-216-295-91	SHORT	0		
R8104	1-216-075-00	RES-CHIP	12K	5%	1/10W						
R8105	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8216	1-216-025-91	RES-CHIP	100	5%	1/10W
R8106	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8217	1-216-025-91	RES-CHIP	100	5%	1/10W
R8107	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8218	1-216-049-91	RES-CHIP	1K	5%	1/10W
						R8219	1-216-025-91	RES-CHIP	100	5%	1/10W
R8108	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8220	1-216-025-91	RES-CHIP	100	5%	1/10W
R8109	1-249-389-11	CARBON	4.7	5%	1/4W						
R8110	1-249-389-11	CARBON	4.7	5%	1/4W	R8221	1-216-025-91	RES-CHIP	100	5%	1/10W
R8111	1-216-033-00	RES-CHIP	220	5%	1/10W	R8222	1-216-295-91	SHORT	0		
R8112	1-216-033-00	RES-CHIP	220	5%	1/10W	R8223	1-216-089-91	RES-CHIP	47K	5%	1/10W
						R8224	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8115	1-216-029-00	RES-CHIP	150	5%	1/10W	R8225	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8116	1-216-029-00	RES-CHIP	150	5%	1/10W						
R8117	1-216-029-00	RES-CHIP	150	5%	1/10W	R8226	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8118	1-216-029-00	RES-CHIP	150	5%	1/10W	R8227	1-216-089-91	RES-CHIP	47K	5%	1/10W

REF. NO.	PART.NO	DESCRIPTION			REMARK	REF. NO.	PART.NO	DESCRIPTION			REMARK
R8228	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8344	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8229	1-216-295-91	SHORT	0			R8345	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8230	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8346	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8231	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8347	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8232	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8350	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8233	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8401	1-216-295-91	SHORT	0		
R8234	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8402	1-216-295-91	SHORT	0		
R8235	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8403	1-216-083-00	RES-CHIP	27K	5%	1/10W
R8236	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8405	1-216-063-91	RES-CHIP	3.9K	5%	1/10W
R8237	1-216-043-91	RES-CHIP	560	5%	1/10W	R8406	1-216-017-91	RES-CHIP	47	5%	1/10W
R8238	1-216-063-91	RES-CHIP	3.9K	5%	1/10W	R8407	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8239	1-216-069-00	RES-CHIP	6.8K	5%	1/10W	R8408	1-216-039-00	RES-CHIP	390	5%	1/10W
R8240	1-216-651-11	METAL CHIP	1K	0.5%	1/10W	R8409	1-216-017-91	RES-CHIP	47	5%	1/10W
R8243	1-216-021-00	RES-CHIP	68	5%	1/10W	R8412	1-216-025-91	RES-CHIP	100	5%	1/10W
R8300	1-216-295-91	SHORT	0			R8413	1-216-025-91	RES-CHIP	100	5%	1/10W
R8302	1-216-017-91	RES-CHIP	47	5%	1/10W	R8416	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8306	1-216-083-00	RES-CHIP	27K	5%	1/10W	R8417	1-216-081-00	RES-CHIP	22K	5%	1/10W
R8307	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8418	1-216-295-91	SHORT	0		
R8308	1-216-039-00	RES-CHIP	390	5%	1/10W	R8419	1-216-041-00	RES-CHIP	470	5%	1/10W
R8309	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8420	1-216-041-00	RES-CHIP	470	5%	1/10W
R8310	1-216-037-00	RES-CHIP	330	5%	1/10W	R8421	1-216-041-00	RES-CHIP	470	5%	1/10W
R8312	1-216-091-00	RES-CHIP	56K	5%	1/10W	R8422	1-216-037-00	RES-CHIP	330	5%	1/10W
R8313	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8423	1-216-041-00	RES-CHIP	470	5%	1/10W
R8314	1-216-295-91	SHORT	0			R8424	1-216-041-00	RES-CHIP	470	5%	1/10W
R8315	1-216-121-91	RES-CHIP	1M	5%	1/10W	R8425	1-216-041-00	RES-CHIP	470	5%	1/10W
R8316	1-216-037-00	RES-CHIP	330	5%	1/10W	R8426	1-216-017-91	RES-CHIP	47	5%	1/10W
R8317	1-216-295-91	SHORT	0			R8427	1-216-017-91	RES-CHIP	47	5%	1/10W
R8318	1-216-295-91	SHORT	0			R8428	1-216-017-91	RES-CHIP	47	5%	1/10W
R8319	1-216-295-91	SHORT	0			R8429	1-216-041-00	RES-CHIP	470	5%	1/10W
R8320	1-216-041-00	RES-CHIP	470	5%	1/10W	R8430	1-216-037-00	RES-CHIP	330	5%	1/10W
R8322	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8431	1-216-041-00	RES-CHIP	470	5%	1/10W
R8323	1-216-017-91	RES-CHIP	47	5%	1/10W	R8432	1-216-041-00	RES-CHIP	470	5%	1/10W
R8324	1-216-041-00	RES-CHIP	470	5%	1/10W	R8433	1-216-041-00	RES-CHIP	470	5%	1/10W
R8326	1-216-017-91	RES-CHIP	47	5%	1/10W	R8435	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8328	1-216-025-91	RES-CHIP	100	5%	1/10W	R8436	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8329	1-216-025-91	RES-CHIP	100	5%	1/10W	R8437	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8330	1-216-041-00	RES-CHIP	470	5%	1/10W	R8438	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8331	1-216-041-00	RES-CHIP	470	5%	1/10W	R8439	1-216-295-91	SHORT	0		
R8332	1-216-041-00	RES-CHIP	470	5%	1/10W	R8506	1-216-091-00	RES-CHIP	56K	5%	1/10W
R8333	1-216-041-00	RES-CHIP	470	5%	1/10W	R8507	1-216-295-91	SHORT	0		
R8334	1-216-041-00	RES-CHIP	470	5%	1/10W	R8508	1-216-043-91	RES-CHIP	560	5%	1/10W
R8336	1-216-041-00	RES-CHIP	470	5%	1/10W	R8509	1-216-031-00	RES-CHIP	180	5%	1/10W
R8337	1-216-041-00	RES-CHIP	470	5%	1/10W	R8510	1-216-067-00	RES-CHIP	5.6K	5%	1/10W
R8338	1-216-017-91	RES-CHIP	47	5%	1/10W	R8511	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8339	1-216-017-91	RES-CHIP	47	5%	1/10W	R8512	1-216-295-91	SHORT	0		
R8340	1-216-063-91	RES-CHIP	3.9K	5%	1/10W	R8514	1-216-017-91	RES-CHIP	47	5%	1/10W
R8341	1-216-041-00	RES-CHIP	470	5%	1/10W	R8517	1-216-295-91	SHORT	0		

REF.NO.	PART.NO	DESCRIPTION			REMARK	REF.NO.	PART.NO	DESCRIPTION			REMARK
R8519	1-216-037-00	RES-CHIP	330	5%	1/10W	R8868	1-216-017-91	RES-CHIP	47	5%	1/10W
R8520	1-216-041-00	RES-CHIP	470	5%	1/10W	R8869	1-216-017-91	RES-CHIP	47	5%	1/10W
R8521	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R8871	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8522	1-216-041-00	RES-CHIP	470	5%	1/10W	R8872	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8523	1-216-033-00	RES-CHIP	220	5%	1/10W	R8873	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8525	1-216-295-91	SHORT	0			R8874	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8526	1-216-061-00	RES-CHIP	3.3K	5%	1/10W	R8875	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8527	1-216-047-91	RES-CHIP	820	5%	1/10W	R8876	1-216-093-91	RES-CHIP	68K	5%	1/10W
R8528	1-216-047-91	RES-CHIP	820	5%	1/10W	R8877	1-216-093-91	RES-CHIP	68K	5%	1/10W
R8529	1-216-055-00	RES-CHIP	1.8K	5%	1/10W	R8878	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8530	1-216-051-00	RES-CHIP	1.2K	5%	1/10W	R8879	1-216-689-11	METAL CHIP	39K	0.5%	1/10W
R8531	1-216-053-00	RES-CHIP	1.5K	5%	1/10W	R8880	1-216-295-91	SHORT	0		
R8532	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8881	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8700	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8882	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8701	1-216-073-00	RES-CHIP	10K	5%	1/10W	R8883	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R8702	1-216-025-91	RES-CHIP	100	5%	1/10W	R8885	1-216-645-11	METAL CHIP	560	0.5%	1/10W
R8703	1-216-025-91	RES-CHIP	100	5%	1/10W	R8886	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8704	1-216-025-91	RES-CHIP	100	5%	1/10W	R8888	1-216-033-00	RES-CHIP	220	5%	1/10W
R8705	1-216-295-91	SHORT	0			R8889	1-216-033-00	RES-CHIP	220	5%	1/10W
R8706	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8890	1-216-295-91	SHORT	0		
R8707	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8892	1-216-295-91	SHORT	0		
R8708	1-216-081-00	RES-CHIP	22K	5%	1/10W	R8893	1-216-295-91	SHORT	0		
R8709	1-216-059-00	RES-CHIP	2.7K	5%	1/10W	R8900	1-216-039-00	RES-CHIP	390	5%	1/10W
R8806	1-216-085-00	RES-CHIP	33K	5%	1/10W	R8901	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8807	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8902	1-216-039-00	RES-CHIP	390	5%	1/10W
R8820	1-216-295-91	SHORT	0			R8903	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8826	1-216-051-00	RES-CHIP	1.2K	5%	1/10W	R8904	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8838	1-216-025-91	RES-CHIP	100	5%	1/10W	R8905	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8839	1-216-085-00	RES-CHIP	33K	5%	1/10W	R8906	1-216-035-00	RES-CHIP	270	5%	1/10W
R8840	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8907	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8841	1-216-025-91	RES-CHIP	100	5%	1/10W	R8908	1-216-035-00	RES-CHIP	270	5%	1/10W
R8846	1-216-295-91	SHORT	0			R8909	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8848	1-216-035-00	RES-CHIP	270	5%	1/10W	R8911	1-216-025-91	RES-CHIP	100	5%	1/10W
R8850	1-216-033-00	RES-CHIP	220	5%	1/10W	R8913	1-216-022-00	RES-CHIP	75	5%	1/10W
R8851	1-216-059-00	RES-CHIP	2.7K	5%	1/10W	R8914	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R8853	1-216-051-00	RES-CHIP	1.2K	5%	1/10W	R8915	1-216-022-00	RES-CHIP	75	5%	1/10W
R8854	1-216-029-00	RES-CHIP	150	5%	1/10W	R8916	1-216-017-91	RES-CHIP	47	5%	1/10W
R8855	1-216-031-00	RES-CHIP	180	5%	1/10W	R8917	1-216-017-91	RES-CHIP	47	5%	1/10W
R8856	1-216-055-00	RES-CHIP	1.8K	5%	1/10W	R8918	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8857	1-216-089-91	RES-CHIP	47K	5%	1/10W	R8919	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8858	1-216-079-00	RES-CHIP	18K	5%	1/10W	R8922	1-216-022-00	RES-CHIP	75	5%	1/10W
R8859	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	R8923	1-216-022-00	RES-CHIP	75	5%	1/10W
R8861	1-216-295-91	SHORT	0			R8924	1-216-022-00	RES-CHIP	75	5%	1/10W
R8863	1-216-295-91	SHORT	0			R8925	1-216-022-00	RES-CHIP	75	5%	1/10W
R8865	1-216-022-00	RES-CHIP	75	5%	1/10W	R8926	1-216-017-91	RES-CHIP	47	5%	1/10W
R8866	1-216-022-00	RES-CHIP	75	5%	1/10W	R8927	1-216-017-91	RES-CHIP	47	5%	1/10W
R8867	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8928	1-216-017-91	RES-CHIP	47	5%	1/10W

REF.NO.	PART.NO	DESCRIPTION			REMARK	REF.NO.	PART.NO	DESCRIPTION			REMARK
R8929	1-216-039-00	RES-CHIP	390	5%	1/10W	R8995	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8930	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8996	1-216-059-00	RES-CHIP	2.7K	5%	1/10W
R8931	1-216-039-00	RES-CHIP	390	5%	1/10W	R8997	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R8932	1-216-049-91	RES-CHIP	1K	5%	1/10W	R8998	1-216-041-00	RES-CHIP	470	5%	1/10W
R8933	1-216-089-91	RES-CHIP	47K	5%	1/10W						
								<CRYSTAL>			
R8934	1-216-089-91	RES-CHIP	47K	5%	1/10W						
R8935	1-216-113-00	RES-CHIP	470K	5%	1/10W	X8200	1-781-148-21	VIBRATOR, CRYSTAL			
R8936	1-216-113-00	RES-CHIP	470K	5%	1/10W	X8301	1-781-612-11	VIBRATOR, CRYSTAL			
R8937	1-216-035-00	RES-CHIP	270	5%	1/10W	X8401	1-781-612-11	VIBRATOR, CRYSTAL			
R8938	1-216-057-00	RES-CHIP	2.2K	5%	1/10W	X8700	1-767-342-21	VIBRATOR, CRYSTAL			
R8939	1-216-035-00	RES-CHIP	270	5%	1/10W						

*A-1644-108-A VM Board, Complete

4-382-854-11 SCREW (M3X10), P, SW (+)

REF.NO.	PART.NO	DESCRIPTION			REMARK
R8940	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8941	1-216-025-91	RES-CHIP	100	5%	1/10W
R8942	1-216-009-91	RES-CHIP	22	5%	1/10W
R8943	1-216-022-00	RES-CHIP	75	5%	1/10W

< CAPACITOR >

REF.NO.	PART.NO	DESCRIPTION			REMARK
C5400	1-107-883-11	ELECT	330UF	20.00%	16V
C5401	1-126-935-11	ELECT	470UF	20.00%	16V
C5402	1-137-150-11	MYLAR	0.01UF	5.00%	50V
C5403	1-126-935-11	ELECT	470UF	20.00%	6.3V
C5405	1-126-933-11	ELECT	100UF	20.00%	16V
C5406	1-126-935-11	ELECT	470UF	20.00%	6.3V
C5407	1-107-364-11	MYLAR	0.01UF	10.00%	200V
C5408	1-107-364-11	MYLAR	0.01UF	10.00%	200V
C5409	1-107-649-11	ELECT	2.2UF	20.00%	250V
C5410	1-130-471-00	MYLAR	0.001UF	5.00%	50V
C5411	1-130-471-00	MYLAR	0.001UF	5.00%	50V
C5412	1-126-935-11	ELECT	470UF	20.00%	16V
C5413	1-126-935-11	ELECT	470UF	20.00%	16V
C5414	1-107-652-11	ELECT	10UF	20.00%	250V
C5415	1-107-363-91	MYLAR	0.0068UF	10.00%	200V
C5417	1-102-959-91	CERAMIC	22PF	5.00%	50V
C5418	1-102-947-00	CERAMIC	10PF	0.50PF	50V

Full resistor section (left column continued):

REF.NO.	PART.NO	DESCRIPTION			REMARK
R8944	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R8945	1-216-022-00	RES-CHIP	75	5%	1/10W
R8946	1-216-017-91	RES-CHIP	47	5%	1/10W
R8947	1-216-039-00	RES-CHIP	390	5%	1/10W
R8948	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8949	1-216-022-00	RES-CHIP	75	5%	1/10W
R8950	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8951	1-216-017-91	RES-CHIP	47	5%	1/10W
R8952	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8953	1-216-035-00	RES-CHIP	270	5%	1/10W
R8954	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8955	1-216-039-00	RES-CHIP	390	5%	1/10W
R8956	1-216-049-91	RES-CHIP	1K	5%	1/10W
R8957	1-216-025-91	RES-CHIP	100	5%	1/10W
R8958	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8959	1-216-022-00	RES-CHIP	75	5%	1/10W
R8960	1-216-017-91	RES-CHIP	47	5%	1/10W
R8961	1-216-022-00	RES-CHIP	75	5%	1/10W
R8962	1-216-071-00	RES-CHIP	8.2K	5%	1/10W
R8963	1-216-113-00	RES-CHIP	470K	5%	1/10W
R8964	1-216-035-00	RES-CHIP	270	5%	1/10W
R8965	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8968	1-216-022-00	RES-CHIP	75	5%	1/10W
R8969	1-216-017-91	RES-CHIP	47	5%	1/10W
R8974	1-216-057-00	RES-CHIP	2.2K	5%	1/10W
R8977	1-216-037-00	RES-CHIP	330	5%	1/10W
R8978	1-216-037-00	RES-CHIP	330	5%	1/10W
R8979	1-216-045-00	RES-CHIP	680	5%	1/10W
R8980	1-216-045-00	RES-CHIP	680	5%	1/10W
R8981	1-216-089-91	RES-CHIP	47K	5%	1/10W
R8982	1-216-079-00	RES-CHIP	18K	5%	1/10W
R8994	1-216-073-00	RES-CHIP	10K	5%	1/10W

< CONNECTOR >

REF.NO.	PART.NO	DESCRIPTION
CN5402	*1-568-878-51	PIN, CONNECTOR 3P
CN5444	*1-770-723-11	CONNECTOR, BOARD TO BOARD 8P
CN5602	*1-568-881-51	PIN, CONNECTOR 6P

< DIODE >

REF.NO.	PART.NO	DESCRIPTION
D5400	8-719-991-33	DIODE 1SS133T-77
D5401	8-719-510-02	DIODE D1NS4-TR
D5402	1-535-303-00	LEAD, JUMPER (5.0MM)
D5403	8-719-991-33	DIODE 1SS133T-77
D5404	8-719-991-33	DIODE 1SS133T-77
D5405	8-719-924-11	DIODE MTZJ-T-77-22
D5406	8-719-924-11	DIODE MTZJ-T-77-22

REF. NO.	PART.NO	DESCRIPTION			REMARK
		< FERRITE BEAD >			
FB5400	1-535-303-00	LEAD, JUMPER (5.0MM)			
FB5401	1-535-303-00	LEAD, JUMPER (5.0MM)			
		< COIL >			
L5400	1-410-784-41	INDUCTOR	0.18UH		
L5401	1-408-602-31	INDUCTOR	8.2UH		
		< TRANSISTOR >			
Q5400	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q5401	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q5402	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q5403	8-729-119-78	TRANSISTOR 2SC1740S-RT			
Q5404	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q5405	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q5406	8-729-045-05	TRANSISTOR 2SA2005			
Q5407	8-729-045-04	TRANSISTOR 2SC5511			
Q5408	8-729-026-39	TRANSISTOR 2SA933AS-RT			
Q5409	8-729-119-78	TRANSISTOR 2SC1740S-RT			
		< RESISTOR >			
R5401	1-247-843-11	CARBON	3.3K	5%	1/4W
R5402	1-249-413-11	CARBON	470	5%	1/4W
R5403	1-249-393-11	CARBON	10	5%	1/4W
R5404	1-249-420-11	CARBON	1.8K	5%	1/4W
R5405	1-249-425-11	CARBON	4.7K	5%	1/4W
R5406	1-249-425-11	CARBON	4.7K	5%	1/4W
R5407	1-249-399-11	CARBON	33	5%	1/4W
R5408	1-247-807-31	CARBON	100	5%	1/4W
R5409	1-247-815-91	CARBON	220	5%	1/4W
R5410	1-249-401-11	CARBON	47	5%	1/4W
R5411	1-249-401-11	CARBON	47	5%	1/4W
R5412	1-249-429-11	CARBON	10K	5%	1/4W
R5413	1-249-414-11	CARBON	560	5%	1/4W
R5414	1-249-432-11	CARBON	18K	5%	1/4W
R5415	1-247-739-11	CARBON	100	5%	1/2W
R5416	1-249-389-11	CARBON	4.7	5%	1/4W
R5417	1-249-432-11	CARBON	18K	5%	1/4W
R5418	1-249-414-11	CARBON	560	5%	1/4W
R5419	1-249-421-11	CARBON	2.2K	5%	1/4W
R5420	1-249-421-11	CARBON	2.2K	5%	1/4W
R5421	1-249-387-11	CARBON	3.3	5%	1/4W
R5422	1-249-405-11	CARBON	100	5%	1/4W
R5423	1-215-915-11	METAL OXIDE	470	5%	3W
R5425	1-535-303-00	LEAD, JUMPER (5.0MM)			
R5427	1-249-401-11	CARBON	47	5%	1/4W

REF. NO.	PART.NO	DESCRIPTION			REMARK
R5428	1-249-413-11	CARBON	470	5%	1/4W
R5429	1-249-413-11	CARBON	470	5%	1/4W
R5430	1-249-417-11	CARBON	1K	5%	1/4W
R5432	1-249-415-11	CARBON	680	5%	1/4W
R5433	1-249-400-11	CARBON	39	5%	1/4W
R5434	1-249-395-11	CARBON	15	5%	1/4W

REF. NO.	PART.NO	DESCRIPTION	REMARK

MISCELLANEOUS

⚠	1-416-466-11	COIL DEMAGNETIC (KV-28FQ75)	
⚠	1-416-769-11	COIL DEMAGNETIC (KV-32FQ75)	
	1-452-032-00	MAGNET, DISK; 10MM	
	1-452-094-00	MAGNET, ROTATABLE DISK; 15MM	
⚠	1-453-340-11	TRANSFORMER ASSY, FLYBACK (NX-4522//U214)	
	1-542-436-11	SPEAKER (24x4.2CM)	
	1-529-417-11	SPEAKER (8CM)	
	1-419-363-11	COIL, NA ROTATION	
⚠	1-571-433-31	SWITCH, PUSH (AC POWER)	
⚠	1-792-389-11	CORD, POWER (WITH CONNECTOR) (KV-28FQ75A/28FQ75B/28FQ75D/28FQ75E KV-32FQ75A/32FQ75B/32FQ75D/32FQ75E)	
⚠	1-792-592-11	CORD, POWER (WITH PLUG) (KV-28FQ75U/32FQ75U)	
⚠	8-453-011-11	NECK ASSY, (NA-299-M)	
	1-693-338-21	MAIN TUNER/VIF (KV-28FQ75A/28FQ75D/28FQ75E KV-32FQ75A/32FQ75D/32FQ75E)	
	1-693-340-21	MAIN TUNER/VIF (KV-28FQ75B/32FQ75B)	
	1-693-339-21	MAIN TUNER/VIF (KV-28FQ75U/32FQ75U)	
	1-693-338-21	SUB TUNER/VIF (KV-28FQ75A/28FQ75D/28FQ75E KV-32FQ75A/32FQ75D/32FQ75E)	
	1-693-340-21	SUB TUNER/VIF (KV-28FQ75B/32FQ75B)	
	1-693-339-21	SUB TUNER/VIF (KV-28FQ75U/32FQ75U)	
⚠	8-737-786-05	PICTURE TUBE (W66LLX060X) (KV-28FQ75)	
⚠	8-735-054-05	PICTURE TUBE (W76LLX060X) (KV-32FQ75)	
⚠	1-451-481-11	DEFLECTION YOKE (Y28RVC2) (KV-28FQ75)	
⚠	1-451-480-11	DEFLECTION YOKE (Y32RVC2) (KV-32FQ75)	
⚠	1-251-807-22	CAP ASSY, HIGH VOLTAGE	
	1-542-437-11	TWEETER (2CM)	
	1-790-082-11	CABLE, RF	
	*A-1620-128-A	BL BOARD, COMPLETE	

ACCESSORIES AND PACKAGING MATERIALS

	4-205-571-41	MANUAL, INSTRUCTION (KV-28FQ75A/32FQ75A) (ITALIAN)	
	4-205-563-51	MANUAL, INSTRUCTION (KV-28FQ75B/32FQ75B) (GERMAN/FRENCH/ENGLISH/ITALIAN/DUTCH)	
	4-205-563-11	MANUAL, INSTRUCTION (KV-28FQ75D/32FQ75D) (GERMAN/GREEK)	
	4-205-563-71	MANUAL, INSTRUCTION (KV-28FQ75E/32FQ75E) (DANISH/SPANISH/FINNISH/NORWEGIAN/PORTUGUESE/ SWEDISH)	
	4-205-563-61	MANUAL, INSTRUCTION (KV-28FQ75U/32FQ75U) (ENGLISH)	
	*4-379-957-01	BAG, PROTECTION (KV-28FQ75)	
	*4-029-168-01	BAG, PROTECTION (KV-32FQ75)	
	*4-205-229-01	INDIVIDUAL CARTON (KV-28FQ75)	

REF. NO.	PART.NO	DESCRIPTION	REMARK
	*4-205-228-01	INDIVIDUAL CARTON (KV-32FQ75)	
	*4-205-235-01	CUSHION (UPPER) (ASSY) (KV-28FQ75)	
	*4-205-227-01	CUSHION (UPPER) (ASSY) (KV-32FQ75)	
	*4-205-234-01	CUSHION (LOWER) (ASSY) (KV-28FQ75)	
	*4-205-226-01	CUSHION (LOWER) (ASSY) (KV-32FQ75)	

REMOTE COMMANDER

	1-418-572-21	REMOTE COMMANDER (RM-893)	

SONY

SERVICE MANUAL   AE-5A CHASSIS

| MODEL	COMMANDER	DEST	CHASSIS NO.	MODEL	COMMANDER	DEST	CHASSIS NO.
KV-28FQ75A RM-893	ET	SCC-Q45B-A	*KV-32FQ75A* RM-893	ET	SCC-Q45C-A
KV-28FQ75B RM-893	FR	SCC-Q44B-A	*KV-32FQ75B* RM-893	FR	SCC-Q44C-A
KV-28FQ75D RM-893	AEP	SCC-Q41E-A	*KV-32FQ75D* RM-893	AEP	SCC-Q41F-A
KV-28FQ75E RM-893	ESP	SCC-Q43C-A	*KV-32FQ75E* RM-893	ESP	SCC-Q43B-A
KV-28FQ75U RM-893	UK	SCC-Q46B-A	*KV-32FQ75U* RM-893	UK	SCC-Q46A-A

CORRECTION - 1

SUBJECT : CHANGES TO FRONT CONTROL ASSEMBLY

File this correction with the service manual

INTRODUCTION : Changes in the structure of the front control assembly.

SECTION 6-2. PICTURE TUBE ....See page 113

REF. NO.	PART.NO	DESCRIPTION	REMARK
51	X-4200-609-3	BEZNET ASSY (KV-28FQ75)	
	X-4200-576-2	BEZNET ASSY (KV-32FQ75)	
54	4-205-463-11	WINDOW, ORNAMENTAL	
58	4-202-555-01	SHAFT, DOOR	
61	4-205-464-11	GUIDE, LIGHT	
71	4-057-303-03	HOLDER, DGC (KV-28FQ75)	
	4-059-569-02	HOLDER, DGC (KV-32FQ75)	
72 ⚠	1-251-317-63	CAP ASSY, HIGH-VOLTAGE	
81	*A-1624-085-A	F3 BOARD, COMPLETE	
82	*A-1646-210-A	H5 BOARD, COMPLETE	
83	*A-1646-211-A	H6 BOARD, COMPLETE	
84	*X-4200-632-2	BRACKET ASSY	85-90
85	3-022-410-31	DAMPER	
86	*4-205-460-11	BRACKET, CONTROL	
87	4-047-464-01	CATCHER, PUSH	
88	4-205-462-12	BUTTON, POWER	
89	4-202-964-11	SPRING	
90	*4-205-461-11	BRACKET DOOR	